

עברית
ENGLISH




מדריך למשתמש
User Guide

LG G2



מדריך למשתמש

מדריך הווידאו יציג בפניך את התכונות המרכזיות החדשנות של G2. הוא זמין בטלפון: לחץ על < > . (זמן בשפות: אנגלית, צרפתית, איטלקית, גרמנית, ספרדית וסינית מסורתית.)



- תצוגות מסכים ואירורים עשויים להיראות שונים מלאה שאתה רואה בטלפון שלך.
- יתכן שחלק מהתוכן במדריך זה לא יחול על הטלפון שלך. הדבר תלוי בתוכנה ובספק השירות שלך. כל המידע במסמך זה נתון לשינוי ללא הודעה מוקדמת.
- מכשיר זה אינן מתאימים לאנשים לקו"י ראייה מפני שהמקלחת שלו נמצאת בסמוך המ gag.
- Copyright ©2013 LG Electronics, Inc. כל הזכויות שמורות. LG והסמל של LG הם סימנים מסחריים רשומים של LG Group ושל חברות הקשורות אליה. כל הסימנים המסחריים האחרים הם רכושים של בעלייהם בהתאם.
- Gmail™, Google Maps™, Google™ Play Store™-ו Hangouts™, YouTube™ Google, Inc. הם סימנים מסחריים של

תיקן העניינים

33.....	הרשות Wi-Fi	הנחיות לשימוש בטוח ויעיל.....
34.....	Bluetooth	הודעה חשובה.....
35.....	יתוף החיבור של נתוני הטלפון.....	היכרות עם הטלפון שלכם.....
37.....	Wi-Fi Direct	סקירה כללית של הטלפון.....
37.....	SmartShare ב-USB	התקנת כרטיסי ה-USIM-Micro
38.....	חיבורם למחשב עם כבל USB	טעינת הטלפון.....
40.....	שירותות	נעילת המסר וביטול הנעילה.....
40.....	ביצוע שיחה.....	הפעל מסך.....
40.....	התקשרות לאנשי הקשר.....	אוזניות סטריאו עם מיקרופון.....
40.....	מענה לשיחה ודחיתת שיחה.....	Plug & Pop.....
41.....	התאמת עוצמת הקול בשיחה.....	המסך הראשי.....
41.....	ביצוע שיחה נוספת.....	עצות בנוגע למסך המגע.....
41.....	צפיה ביוםני השירותים.....	מסך הראשי.....
42.....	הגדרות שיחה.....	מסך ראשי מורחב.....
43.....	ארגוני קשר.....	התאמת אישיות של המסך הראשי.....
43.....	חיפוש איש קשר.....	חרזה לישומים שהיו בשימוש
43.....	הוסף איש קשר חדש.....	לאחורונה.....
43.....	ארגוני קשר מועדפים.....	לוח התאראות.....
44.....	יצירת קבוצה.....	פתחת לוח ההתראות.....
45.....	שליחת הודעות.....	סמלים מחוונים בשורת המזב.....
45.....	שליחת הודעה.....	מקלדת וירטואלית.....
46.....	תיבה ברצף.....	הזנת אותיות עם סימני הטעמה.....
46.....	שינוי הגדרות ההודעה.....	הגדרת חשבון Google.....
47.....	הודעת דוא"ל.....	התחברות לרשות ולמכשירים.....
47.....	ניהול חשבון דוא"ל.....	Wi-Fi.....
47.....	עובדת עם תיקיות החשבון.....	התחברות לרשות Wi-Fi והתחברות
48.....	חיבור ושליחה של דוא"ל.....	הפעלת Wi-Fi ותחברות

66..... הרשמה ל-VuTalk לפני השימוש	49..... מצלמה
67..... הגדרות VuTalk	49..... הכרת התצוגה המקדימה
67... קיון תקשורת חיצונית עם VuTalk	50..... שימוש בהגדרות המתקדמות
68..... Voice Mate	51..... צילום מהיר
68..... שימוש ב-Voice Mate	51..... שימוש במצב 'צלם ונקה'
68..... Voice Mate	52..... שימוש במצב מצלמה כפולה
69..... הגדרות	53..... שימוש במצב צילום לכידת זמן
69..... LG SmartWorld	53..... לאחר שצילמת תמונה
69..... גישה ל-LG SmartWorld	54..... מתוך הגלריה
69..... טלפון	55..... מצלמת יידאו
69... LG SmartWorld	55..... הכרת התצוגה המקדימה
70..... אופן השימוש ב-LG SmartWorld	56..... שימוש בהגדרות המתקדמות
70..... On-Screen Phone	57..... הקלטת סרטון וידאו מהיר
70..... סמלי טלפון במסך המחשב	57..... לאחר הקלטת וידאו
71..... תכונות הטלפון במסך המחשב	58..... מתוך הגלריה
71..... כיצד להתקין On-Screen Phone	58..... כוונן העצמה בעת צפייה בסרטוני וידאו
71..... במחשב	58..... שימוש בזום שמע
מולטימדיה	58..... שימוש במצב הקלהה כפולה
72..... גליה	59..... שימוש בזום מעקב
72..... הצגת תמונות	60..... פונקציה
73..... הפעלת סרטוני וידאו	60..... QuickMemo
73..... ערכית תמונות	61..... שימוש באפשרויות של QuickMemo
73..... מחיקת תמונות/סרטוני וידאו	61..... הצגת ה-QuickMemo שנשמר
73..... הגדירה כטפט	62..... QuickTranslator
73..... סרטוני וידאו	63..... QSlide
74..... הפעלת קובץ וידאו	64..... QuickRemote
75..... עורך הוויידיאו	65..... מיקוד אל רצועה
76..... מוסיקה	66..... VuTalk
76..... האוסף קובץ מוסיקה לטלפון	
77..... עבר מוסיקה באמצעות סנכרון מדיה (MTP)	
77..... השמעת שיר	

86.....	סנכרון עם מכשירים אחרים	כלי שירות
87.....	הגדמות	לש הצד (החלפת משימות
87.....	הרשאות	מהירה עם שלוש אצבעות)
91.....	צליל	מצב אורח
92.....	תצוגה	הגדרת התראה
94.....	כלי	שימוש במחשבון
101.....	תוכנת מחשב (LG PC Suite)	הוסף אירע ללוח השנה
104.....	עדכן תוכנת הטלפון	רשמיול
104.....	עדכן תוכנת הטלפון	הקלטה צליילים או קול
106.....	אודוט מדריך למשתמש זה	שליחת ה הקלטה הקולית
106.....	אודוט מדריך למשתמש זה	מנהל המשימות
107.....	סימנים מסחריים	משימות
107.....	DivX HD	POLARIS Viewer 5
107.....	Dolby Digital Plus	Google+
108.....	אבייזרים	חיפוש קולי
109.....	פתרונות בעיות	הורדות
112.....	שאלות נפוצות	האינטרנט
		אינטרנט
		שימוש בסרגל הכלים של
		האינטרנט
		הציג דפי אינטרנט
		פתחת דף
		חיפוש באינטרנט באופן קולי
		סימניות
		היסטוריה
		שימוש בדף מוקפץ
		Chrome
		הציג דפי אינטרנט
		פתחת דף

הקפד לקרוא הנחיות פשוטות אלה. אי עמידה בהנחיות אלו עלולה להיות מסוכנת או בלתי חוקית.

חשיפה לאנרגיית תדר רדיו

מידע על חשיפה לגלי רדיו ושיעור ספיגת סגולית (SAR).
דגם טלפון נייד זה  תוכנן לעמוד בדרישות הבטיחות הרלוונטיות לחשיפה לגלי רדיו. דרישות אלו מבוססות על קווים מוחמים מדעים, ואלה כוללים שלוי בטיחות המיעדים להבטיח את בטיחותם של כל בני האדם, ללא קשר לגילם או במצב בריאותם.

- הנחיות החשיפה לגלי רדיו משתמשות ביחידת מידת הנקראת "שיעור ספיגת סגולית" (SAR). בדיקות SAR מבוצעות באמצעות שיטות מתוקנות, כאשר הטלפון משדר ברמת העוצמה המרבית המאושרת עבורו בכל תחומי התדרים בשימוש.
- אף כי עשויים להיות הבדלים בין רמות SAR של דגמי טלפונים שונים של LG, כל הטלפונים מתוכננים לעמוד בהנחיות המתאימות לשימושם לגלי רדיו.
- מגבלת SAR המומלצת על ידי הוועדה הבינ-לאומית להגנה מפני קרינה בלתי מינית (ICNIRP) היא ממוצע של 2 ואט/ק"ג על כל 10 ג"ר של רקמה.
- ערך SAR הגובה ביוטר עבור דגם טלפון זה שנמדד לשימוש באוזן הוא 0.409 ואט/ק"ג (10 ג"ר), כאשר הוא נישא על הגוף, ערך זה עומד על 0.470 ואט/ק"ג (10 ג"ר).
- מכשיר זה עומד בהנחיות החשיפה ל-RF כמשמעותם בו בתנחות השימוש הרגילה ליד האוזן או כשהוא ממוקם לפחות 1.5 ס"מ מהגוף. כאשר נעשה שימוש בנוירטיק נשיה או בתפס או מנשא לחגורה, אסור שתהייה בהם מתכת כלשהי, והמרחק בין המכשיר לגוף צריך להיות לפחות 1.5 ס"מ. כדי לשדר קובי צנונים או הודעות, מכשיר זה מחיב חיבור אינטלי לרשת. במקרים מסוימים עלול שידור קבצי נתונים או הודעות להיותמושחה עד שchipר זה יהיה זמין. הקפד על שמירת הוראות המרחק המינימלי המוצרכות לעיל עד לסיום השידור.

טיפול במוצר ותחזוקה

⚠️ אזהרה

השתמשו רק בסוללות, במטענים וב아버지ים המאושרים לשימוש עבור דגם ספציפי זה של טלפון. השימוש בסוגים אחרים עשוי לבטל את האישור או האחוריות החלים על הטלפון ועלול להיות מסוכן.

- אין לפרק יחידה זו. כאשר נדרש תיקון, פנה לטכני שירות מוסמך.
- תיקונים במסגרת האחוריות, לפי שיקול דעתה של LG, עשויים לכלול חלקים או לוחות חלופיים, חדשים או מחודשים, ובלבד שהם מצויים בפונקציונליות זהה לזו של החלקים המקוריים.
- אין לקרב את המऋיר למכשירים חממיים כגון טלויזיות, מכשיiri רדיו ומחשבים אישיים.
- יש לשמור את היחידה הרחק ממקורות חום כדוגמת רדייטורים או תנורי בישול.
- אין להפעיל את היחידה.
- אין לאפשר צעוזע מכני או חבטה.
- יש לכבות את הטלפון בכל מקום שבו נדרש הדבר על-ידי תקנות מיוחדות. לדוגמה, אין להשתמש בטלפון בבתי חולים, שכן הפעלה עלולה להשפיע על פעולות מכשור רפואי רגיש.
- אין לאחז בטלפון בידיים רטובות בזמן הטענתו. אחיזה במצב צהה עלולה לגרום להתחشمויות ולהסב נזקכבד לטלפון.
- אין לטעון את הטלפון ליד חומר דליק, מכיוון שהמऋיר עלול להתחמס ולעלות באש.
- יש להשתמש במטלית יבשה לניקוי חלקו החיצוני של המऋיר (אין להשתמש בחומרים מסוכנים כגון בנץ, מדלול או אלכוהול).
- אין לטעון את הטלפון כאשר הוא נמצא על-גביו מצעים או ריפורד.
- יש לטעון את הטלפון באזור מאורר היבט.
- אין לחשוף יחידה זו לכמויות מוגזמות של עשן או אבק.

- אין להחזיק את הטלפון בסמוך לכרטיסי אשראי או כרטיסי נסיעה; הנתונים בפיהם המוגנטיים עלולים להיפגם.
- אין להקיש על המספר באמצעות חפצים חדים, שכן הדבר עלול לגרום לך טלפון.
- אין לחשוף את הטלפון לנוזלים או ללחות.
- יש לנתקו זהירות בשימוש באביזרים, כמו אוזניות. אין לגעת באנטנה שלו לצורך.
- אם זכוכית המכשיר שברורה או סודקה, אל תיגע בה או תנסה להסיר אותה ועל תשתמש במכשיר. האחריות אינה מכסה נזקים שנגרמו לתצוגת הזכוכית כתוצאה מגעה ושימוש לרעה.
- הטלפון שלך הוא מכשיר אלקטרוני המייצר חום במהלך הפעלה רגילה. בהיעדר אוורור העולם, מגע ישיר וממושך מאוד של העור עלול לגרום לא-נוחות או לכוויות קלות. לפיכך, יש לנתקו זהירות בהחזקת הטלפון במהלך הפעלה או מיד לאחריה.
- אם הטלפון גרבט, נתק אותו מיד והנח לו להתייבש לגמרי. אל תנסה להאיץ את תהיליך הייבוש בעזרת מקור חום חיצוני, כמו תנור, מיקרוגל או מייבש שיער.
- הנזילים שחדרו לטלפון ישנו את צבע תווית המוצר שבתוכו המכשיר. כתוב האחריות אינם מכוסה נזק למכשיר כתוצאה מחשיפה לנוזלים.

תפקיד ייעיל של הטלפון

מכשירים אלקטרוניים

כל הטלפונים החדשים עלולים לספג הפירות שישפיעו לרעה על ביצועיהם.

- אין לשתמש בטלפון הנייד בסמוך לציר רפואי ללא קבלת רשות. יש להימנע מהනחת הטלפון מעל לקוצב לב, למשל בכיס החזה.
- טלפונים ניידים עלולים להפריע לעזריו שימושה מסויימים.
- הפרעה שנייה עלולה להשפיע על מכשירי טלוייזיה, מכשירי רדיו, מחשבים וכוכלי.

- השתמש בטלפון שלך בטמפרטורות שבין 0°C ו-40°C, אם ניתן. חסיפת הטלפון לטמפרטורות נמוכות או גבוהות באופן קיצוני עלולה לגרום לנזק, לתקלות או אפילו לפיצוץ.

בטיחות בדרכים

בדוק את החוקים והתקנות הנוגעים לשימוש בטלפונים ניידים באזוריים שבהם אתה נוהג.

- אין להחזיק את הטלפון בידי בזמן נהיגה.
- יש להפנות את מלאו תשומת הלב לנרגאה.
- רד לשול הדרך וחנה לפני ביצוע שיחאה או מענה לשיחאה, בהתאם לתנאי הדרך.
- אנרגיית תדר רדיו עשויה להשפיע על מערכות אלקטרוניות מסוימות ברכב.
- כדוגמת מערכות טריאו וצדוד בטיחות.
- אם המכונית מצויה בכירית אויר מתנפחת, אין לחסום אותה על-ידי התקינה של ציוד אלחוטי נישא. הדבר עלול לגרום לכשל של הכירית או לפיצעה חמורה עקב ביצועים לא נאותים שלה.
- אם אתה מازין למוסיקה בעת תנועה, ודא שהעוצמה היא ברמה סבירה, כך שתתmeshir להיות מודע לסביבתך. הדבר חשוב במיוחד בקרבת כבישים.

מנעו נזק לשמיעתכם

כדי למנוע נזק אפשרי לשמיעה, אל תאזרן בעוצמות קול גבהות לאורך זמן.



חסיפה לעוצמות קול גבהות במשך פרקי זמן ארוכים עלולה להזיק לשמיעה. לכן אנו ממליצים שלא תדליק או תכבה את המכשיר סמוך לאוזן. מומלץ גם להגיד את עוצמת הקול של המוסיקה והשיחאה לרמה סבירה.

- כאשר אתה משתמש באוזניות, הנmr את עוצמת הקול אם אין מצליח לשמע את האנשים שבסביבתך מדברים, או אם האדם שלצדך יכול לשמעו את מה שאתה שומע באוזניות.

הערה: עצמת קול מופרצת מאוזניות פנימיות ואוזניות חיצונית עלולה לפגוע בשמיעה

חלק זכוכית

חלקים מסוימים של התקן הנייד עשויים מזכוכית. זכוכית זו עלולה להישבר אם המכשיר ייפול על משטח קשה או יקבל מכחה חזקה. אם הזכוכית נשברת, אל תנסה לגעת בה או להסיר אותה. יש להפסיק להשתמש בתקן הנייד עד להחלפת הזכוכית על ידי ספק שירות מורשה.

סביבה שבה מבוצעות עבודות עם חומר נפץ

אין להשתמש בטלפון באזורי שבהם מתבצעות פעולות פיצוץ. שים לב להגבלות שעמוד בכל התקנות או הכללים.

סביבה שבה קיימת סבירות לפיצוץ

- אין להשתמש בטלפון באזורי תדלוק.
- אין להשתמש בו בסמוך לדלק או לכימיקלים.
- אין להוביל או לאחסן גז דליק, נזליים דליקים או חומר נפץ בתא הרכב המכיל את הטלפון הנייד או את אביזריו.

כלי טיס

- התקנים אלחוטיים עלולים לגרום להפרעה במטוסים.
- יש לכבות את הטלפון הנייד לפני העלייה למטוס.
 - אין להשתמש בו על הקrukן ללא קבלת רשות מאנשי הציגות.

ילדים

יש לשמור על הטלפון במקום בטוח, מחוץ להישג ידם של ילדים קטנים. המכשיר כולל חלקים זעירים העולים להיות סכנת חנק אם ינותקו מהטלפון.

שיעורויות חירום

רק רשותות סולריות מסוימות מאפשרות לבצע שיעורויות חירום. לפיק', בשום מקרה אין לשמור רק על הטלפון לביצוע שיעורויות חירום. בדקו את הנושא עם חברת הסולולר המקומית.

מידע לגבי הסוללה והטיפול בה

- אין צורך לפרק את הסוללה במלואה לפני טעינה מחדש. בגיןוד למערכות סוללה אחרות, אין השפעת זיכרון שעוללה לפגום ביצועי הסוללה.
- יש להשתמש אך ורק בסוללות ובמטענים של LG. מטעני LG מיועדים להארכת חיים הסוללה.
- אין לפרק או לקצר את הסוללה.
- יש להחליף את הסוללה כאשר היא אינה מפיקה עוד רמת ביצועים סבירה. ניתן לטען מחדש את מאורת הסוללה מאות פעמים לפני שהיא צורך להחליפו.
- כדי להציג שימושים סוללה מרבית, יש לטען אותה מחדש אם לא הייתה בשימוש במשך זמן רב.
- אין לחסוף את מטען הסוללה לאור שמש ישיר או להשתמש בו בתנאי לחות גבוהה, כמו חדר אמבטיה.
- אין להשיר את הסוללה במקומות חמימים או קרירים, שכן הדבר עלול לפגום ביצועיה.
- קיים סכנת התפוצצות אם הסוללה הוחלפה בסוג סוללה שאינו מתאים.
- השלך סוללות משומשות על פי הוראות היצרן. יש למחרר, אם אפשר. אין להשליך אותן כאשפה ביתית.

- אם עליך להחליף סוללה, קח אותה למרוץ השירות המורשה הקרוב של LG Electronics או לספק לצורך לקבלת סיוע.
- יש לנתק תמיד את המתען מהשקע לאחר שהטלפון נתען במלואו כדי למנוע בזבוז מיותר של חשמל מצד המתען.
- אורך חי' הסוללה בפועל תלוי בתצורת הרשת, בהגדרות המוצר, באופי השימוש, בתנאי הסוללה ובתנאים הסביבתיים.
- הקפד שלא יוצר מגע בין הסוללה לבין פריטים חדים כגון שענים או ציפורניים של בעל חיים. מגע זהה עלול לגרום לשריפה.
- למען בטיחותך, אל תסיר את הסוללה המשולבת במוצר.

הצהרת תאימות

בזאת, **LG Electronics** מצהירה שהמוצר **LG-D802** תואם לדרישות היסודות ולתנאים הרלוונטיים الآخרים של הנחה **1999/5/EC**. ניתן למצוא עותק של הצהרת התאימות בכתבوبة <http://www.lg.com/global/support/cedoc/RetrieveProductCeDOC.jsp>

שים לב: תוכנת קוד פתוח

לקבלת קוד המקור המתאים במסגרת **LGPL**, **GPL**, **MPL** ורישונות קוד פתוח אחרים, בקר בכתבوبة <http://opensource.lge.com>
כל תנאי הרישיון, כתבי הוויתור והודעות המזכירים זמינים להורדה עם קוד המקור.

תקינה ובטיחות

עבור אל 'הגדרות מערכת' > **אודוט הטלפון** > **תקינה ובטיחות** לקלט מידע על תקינה ובטיחות

פרטי המשרד המטפל בתאימות מוצר זה:

LG Electronics Inc.
EU Representative, Krijgsman 1,
1186 DM Amstelveen, The Netherlands

אנא קרא מידע זה לפני תחילת השימוש בטלפון!

לפניהם תזקיח את הטלפון לנקודות שירות או שתתקשר לנציג שירות, בדוק אם חלק מהבאים שבנה נתקלה מהתוארות בסעיף זה.

1. זיכרון הטלפון

כאשר שטח הזיכרון הפנוי קטן מ-10%, הטלפון לא יוכל לקבל הודעות חדשות. עליך לבדוק את זיכרון הטלפון ולמחוק חלק מהנתונים, כגון יישומים או הודעות, כדי לפנות מקום זיכרון.

כדי להסיר התקינה של יישום:

- 1 הקש על  > הכרטיסייה "ישומים" >  הגדרות > הכרטיסייה כללית > יישומים.
- 2 לאחר שיופיעו כל היישומים, גלול ובחירה את היחסם שאת התקנתו ברצונך להסיר.
- 3 הקש על הסר התקינה.

2. מיטוב חי' הסוללה

הארך את חי' הסוללה על ידי כיבוי תכונות שאין צורך בפעולה רציפה שלhn ברקע. תוכל לפקח על המידה שבה יישומים ומশאי מערכות צריכים כוח סוללה.

הארכת חי' הסוללה של הטלפון:

- כבה תקשורת רדיו שאינה בשימוש. אם איןך משתמש ב-Wi-Fi, חיבור Bluetooth או GPS, כבה אותם.
- הפחית את הבחרות המשך וקבע פרק זמן קצר יותר לכיבוי אוטומטי של המספר.
- בטל את הסינכרון האוטומטי של Gmail, לוח השנה, אנשי הקשר ויישומים אחרים.
- יתכן שחלק מהיישומים שהורדת מפחיתים את כוח הסוללה.
- בזמן השימוש ביישומים שהורדו, בדוק את רמת הטעינה של הסוללה.

הערה: אם אתה מתקין בטענות על Power/Lock Key בזמן שההתקן נמצא בכיס שלך, המסת' יכבה באופן אוטומטי כדי להסוך באנרגיית הסוללה.

כדי לבדוק את רמת הכוח של הסוללה:

- הקש על > הcartisية "ישומים" > הגדרות הcartisיה > כללי > **אודות הטלפון** > סוללה.


מצב הסוללה (בטעינה או בפריקה) ורמת הסוללה (כחוז מהטעינה המלאה מוצגים בחלקן העליון של המסך).

כדי לשנות ולפקח על השימוש בכוח הסוללה:


- הקש על > הcartisיה "ישומים" > הגדרות > הcartisיה כללי > **אודות הטלפון** > סוללה > שימוש בסוללה.

זמן השימוש בסוללה מוצג במסך. הזמן המוצג מצין את משך הזמן שעבר מאז החיבור האחרון למקור מתח; לחולפון, אם הטלפון מחובר כעת, כמה זמן פעל הטלפון לאחרונה על כוח סוללה. במשך מוצגים היישומים או השירותים שצורכים כוח סוללה, והרשימה מסודרת לפי רמת הצריכה: מההגבוה ביותר לנמוכה ביותר.

3. לפני התקנת יישום או מערכת פעולה בקוד פתוח.



אם אתה מתקן או משתמש במערכת הפעלה שונה מזו שספק היצרן, הדבר עלול לגרום לתפקוד לקוי של הטלפון. לבסוף, האחריות על הטלפון תתבטל.



כדי להגן על הטלפון ועל הנתונים האישיים האישיים שלך, הורד יישומים מקוריים מהייננס בלבד, כגון Play Store. התקנה שגואה של יישומים בטלפון עלולה לגרום לטלפון לפעול בצורה לא תקינה או להתרחשויות שגיאיה חמורה. יש להסיר מהטלפון את היישומים הללו ואת כל ההגדרות והנתונים הקשורים אליהם.

4. שימוש בתבנית ביטול נעילה

הגדר תבנית ביטול נעילה להגנה על הטלפון. הקש על  >  הcartis'iyah יישומים > הגדרות > הcartis'iyah תצוגה > מסך נעילה > בחירות נעילת מסך > התבנית. פעולה זו פותחת מסך שינחה אותה כדי לשרטט התבנית ביטול נעילה של המסך. עליך ליצור קוד PIN לגיבוי באמצעות מקורה שתשחץ את התבנית ביטול הנעילה. זיהירות: צור חשבון Google לפני שתגדיר התבנית ביטול נעילה, וזכור את קוד ה-PIN לגיבוי שיצרת בזמן יצירת נעילת התבנית.

⚠️ אזהרה

אם מצביע זיהירות שיש לנ��וט בעת השימוש בענילת התבנית.

חשוב מאוד לציין את התבנית ביטול הנעילה שהוגדרה. אם תשתמש בתבנית שגוייה 5 פעמים, תאביד את הגישה לטלפון. לרשותך 5 ניסיונות להזין את התבנית ביטול הנעילה, קוד ה-PIN או הסיסמה. אם ניצלת את כל 5 הניסיונות, תוכל לנסות שוב לאחר 30 שניות.

אם שכחת את התבנית ביטול הנעילה, קוד ה-PIN או הסיסמה:
< אם שכחת את התבנית >

אם נכנסת לחשבון Google דרך הטלפון, אך לא הצליחה להזין את התבנית הנכונה 5 פעמים, הקש על הלוחץ **שכחת את התבנית?** בתחתית המסך. לאחר מכן תתקבקש להיכנס באמצעות חשבון Google, או שייהה עליך להזין קוד PIN לגיבוי, שאותו הזנת בעת יצירת נעילת התבנית.

אם לא נכנסת לחשבון Google בטלפון או שכחת את קוד ה-PIN לגיבוי, עליך לבצע איפוס קשיח.

< אם שכחת קוד PIN או סיסמה >

אם שכחת את קוד PIN או את הסיסמה, תצטרך לבצע איפוס קשיח. זיהירות: אם תבצע איפוס קשיח, כל יישומי המשמשו ונתוינו המשתמש יימחקו.

הערה: אם לא נכנסת לחשבון Google, ושכחת את התבנית ביטול הנעילה, תצטרך להזין קוד PIN לגיבוי.

5. שימוש באיפוס קשייח' (איפוס להגדרות היצן)

אם הטלפון אינו משבחר למצוב המוקורי, יש להשתמש באיפוס קשייח' (איפוס להגדרות היצן) כדי לאתחל אותו.

- 1 כבה את המכשיר.
- 2 לחץ לחיצה ארוכה על **מקש הדלק/געל + מקש הנמכת עוצמת הקול** בגב הטלפון.
- 3 שחרר את **מקש הדלק/געל** רק כאשר מוצג הסמל של LG, ולאחר מכן לחץ והחזק מיד את **מקש הדלק/געל** שוב.
- 4 שחרר את כל המקשיים כמשמעותם 'איפוס קשייח' להגדרות היצן'.
- 5 **הקש על מקש הדלק/געל** כדי להמשיך או על אחד משני **מקשי עוצמת הקול** לביטול.
- 6 **הקש על מקש הדלק/געל** פעם נוספת כדי לאשר או על אחד משני **מקשי עוצמת הקול** לביטול.



אם תבצע איפוס קשייח', כל "ישומי המשתמש", נתוני המשתמש ורישונות DRM ייהוקו. זכור לגבוט את כל הנתונים החשובים לפני ביצוע איפוס קשייח'.

6.פתיחה ישומים ומעבר ביניהם

כל לביצוע ריבוי-משימות ב-Android, ונitin להפעיל יותר מיישום אחד בו-זמנית. אין צורך לצאת מיישום לפני פתיחה של ישום אחר. ניתן להשתמש במקרה "ישומים פתוחים ומעבר ביניהם". מערכת Android מנהלת את היישומים, ועוצרת ומפעילה אותם בהתאם לצורך כדי להבטיח שישומים לא פעילים לא צריכים משאבים שלא לצורך.

- 1 **הקש והחזק את מקש הבית** תציג רשימה של ישומים שהיו בשימוש לאחרונה.
- 2 **הקש על היישום שאליו ברצונך ל抵达.** פעולה זו אינה מספיקה את פעולתו של היישום הקודם ברקע של הטלפון. הקפד להקיש על **מקש 'הקודם'** כדי לצאת מיישום לאחר השימוש בו.

- כדי לעזרך יישומים, הקש על **מנהל המשימות** מרשיימת היישומים שבו בשימוש לאחרונה, ולאחר מכן הקש על **עוזר או על עוזר הכל**.
- כדי להסיר יישום מרשיימת היישומים שבו בשימוש לאחרונה, החלק ימינה או שמאלה את התצוגה המקדימה של היישומים. כדי לנוקות את כל היישומים, הקש על **נקה הכל**.

7. העברת מוסיקה, תמונות וסרטוני וידאו באמצעות סינכרון מדיה (MTP)

- 1 הקש על > הcartisim יישומים > הגדרות > הcartisim כללי > **אחסון** כדי לבדוק את מדיית האחסון.
- 2 חיבר את הטלפון למחשב באמצעות כבל ה-USB.
- 3 בחר מצב חיבור USB יופיע במסך הטלפון, בחר באפשרות **סינכרון מדיה (MTP)**.
- 4 פתח את תיikit הזיכרון במחשב. באפשרות להציג את תוכן האחסון בනוף גדול במחשב ולהעביר את הקבצים מהמחשב לתיקית זיכרון ההתקן, או להיפר.
- 5 לאחר העברת קבצים, החלק מטה את שורת המצב, הקש על האפשרות **USB מחיבור** ובחר באפשרות טען את **מצשיר הטלפון** מתוך רשימה סוגית חיבור USB.

8. החזקת הטלפון באופן ניצב

החזק את הטלפון הסולרי במאונך, כפי שמחזקים טלפון רגיל. הטלפון שלך כולל אנטנה פנימית. היזהר שלא לשרטוט או לגרום נזק לחלק האחורי של הטלפון כדי לא לגרום לירידה בביצועים.

כשהתאiate יוזם/מקבל שירות או שולח/מקבל נתונים, הימנע מהחזקת הטלפון בחלק התחתון שלו, שבו נמצאת האנטנה. הדבר עשוי להשפיע על איכות השיחה.

9. כאשר המסך קופא

אם המסך קופא או שהטלפון אינו מגיב כשמנטים להפעיל אותו: לחץ לחיצה ארוכה על מקש הפעלה/געילה למשך 10 שניות כדי לנובות את הטלפון. אם הוא עדיין לא פועל, פנה למרכז השירות.

10. אל תחבר את הטלפון בעת הפעלה/כיבוי של המחשב

הקפד לנתק את הטלפון מהמחשב בעת הפעלה או כיבוי של המחשב, לאחר שאם הוא יהיה מחובר הדבר עלול לגרום לשגיאות מחשב.

11. מצב בקירה של מפתח חומרה


אם תציגת הטלפון פגומה או שבורה, תוכל להשיב לשיחת נוכנת, לסיים שיחה, או לכבות התראה באמצעות מפתחות החומרה.

- 1 כבה את הטלפון.
- 2 הקש והחזק את מקש הדלק/געול ואת מключи עוצמת הקול בו-זמןית למשך מילאה מ-6 שניות כדי להיכנס למצב בקירה של מפתח חומרה.
- 3 הקש על מключи עוצמת הקול כדי לגלוול אל האפשרות הרצiosa, ולאחר מכן הקש על מקלט הדלק/געול כדי לאשר.
- מענה לשיחה: הקש על מключи עוצמת הקול בו-זמןית.
- ניתוק שיחה: הקש על Power/Lock Key במהלך שיחה.
- הפסקת שעון מעורר: כאשר מצלול שעון מעורר, הקש והחזק את מקש הגברת עוצמת הקול או את מקש הנמכת עוצמת הקול כדי להפסיק את השעון המעורר.

הערה: אם אתה משתמש בטלפון שזכוכית התצוגה שלו שבורה, הטלפון עלול להישבר עוד יותר ואתה עלול להיפצע. הקפד לגשת למרכז השירות המורשה של LG כדי שהטלפון שלך יתוקן.

היכרות עם הטלפון שלכם

סקירה כללית של הטלפון




הערה: חישון קרובא

בעת קבלת שיחות וביצוע שייחות, חישון הקרובא מכבה אוטומטית את התאורה האחוריית ומעל את המסך כאשר הוא חש שהטלפון קרוב לאוזן. תכונה זו מאריכה את ח'י הסוללה ומנ�נעת את הפעלת מסך המגע שלא בכוונה במהלך השיחה.

⚠️ אזהרה

הנחת עצם כבד על הטלפון או ישיבה עליו עלולות לגרום לפגיעה בפונקציות של מסך המגע ומסך-h LCD של הטלפון. אין לכנות את חישון הקרובא של-h LCD ביציפוי מגן. הדבר עלול לגרום לתתקלה בחישון.



! אזהרה

- חלק זה סגור את תא הסוללה. אין לפתוח את המכסה האחורי.
- הקפד לא לפגוע בנקודת המגע של NFC בטלפון, מהוות חלק מאנטנת NFC.

התקנת כרטיס ה-Micro-USIM

לפני שתתחל ל לחבר את הטלפון החדש שלך, כדאי להכניס את כרטיס ה-Micro-USIM.

לחצן השיליפה הוא פתח עגול קטן ממש מעלה לדלת המגש. כדי להתקין כרטיס Micro-USIM חדש:

- 1 הכנס את הכליל לשילוף Micro-USIM שהגיע עם הטלפון (או סיכה דקה) לפתח לחצן השיליפה, ולחץ בעדינותות אך ביציבות עד שהמגש י קופוץ החוצה.
- 2 הוציא את המגש ומוקם את כרטיס ה-Micro-USIM בתוכו, כאשר המגעים פונים החוצה והפינה בעלת החווית נמצאת מימין. יש רק דרך אפשרית אחת להכניס בכוונה את הכרטיס למגש.
- 3 מוקם מחדש בזיהירות את המגש בחירץ, ודחף אותו בעדינות בזרירה לטלפון.

הערה: ודא שאזורי מגע הזהב בכרטיס פונה מטה.




טעינה הטלפון

טען את הסוללה לפני השימוש הראשוני. השתמש במתען כדי לטעון את הסוללה. ניתן גם להשתמש במחשב כדי לטעון את המכשיר, על-ידי חיבורם באמצעות כבל USB.

אזהרה

השתמש אך ורק במתעניים, סוללות וכבלים המאושרים על-ידי LG. אם אתה משתמש במटעניים, סוללות או כבלים שלא אושר, הדבר עלול לגרום לעיכוב בטיענת הסוללה או להופעת הודעה לגבי טעינה איטית, או שהדבר עלול לגרום פיצוץ בסוללה או מזק בהתקן. והאחריות אינה מכסה אותך.

מחבר המתען נמצא בחלק התיכון של הטלפון. הכנס את המתען, ו לחבר אותו לשקע חשמל.



הערה:

- הסוללה חייבת להיות טעונה במלואה מההתחלה כדי לשפר את אורך חייה.
- אל תפתח את המכסה האחורי במהלך טיענת הטלפון.

נעילת המסר וביטול הנעילה

אם לא תשתמש בטלפון למשך זמן מה, המסר יכבה וינעל באופן אוטומטי. כך נמנעות הקשות בשוגג ונוחך הספק הסוללה.

כשאין משתמש בטלפון, הקש על **מקס הדלק/נעיל** כדי לנעל את הטלפון. אם יש תוכניות פועלות כאשרהו נועל את המסר, הן עשויות להמשיך לפעול במצב נעילה. מומלץ לצאת מכל התוכניות לפני הכניסה למצב 'נעילה' כדי להימנע מחויבים מיוחדים (כגון שיחות טלפון, גישה לאינטרנט ותקשרות נתוניים).

כדי להעיר את הטלפון, הקש על **מקס הדלק/נעיל**. מסר הנעילה יופיע. גע במסר הנעילה והחלה אותו בכיוון לצדתו כדי לבטל את נעילת המסר הראשי. המסר الآخرן שהוזג יפתח.

הפעל מסר

המשתמש יכול לנעל את המסר או לבטל את הנעילה פשוט על ידי הקשה כפולה. כדי להפעיל את התוכנה '**הפעל מסר**'

1 הקש על <>  הגדרות > הרטיסייה כללי > מחוות.

2 הוסיף סימן ביקורת לצד האפשרות **אשר המסר דולק/כבוי**.

הקש פעמיים על התצוגה המרכזית כדי לבטל במהירות את נעילת התצוגה. כדי לכפות נעילה, הקש פעמיים על שורת המצב בתצוגה לצדתו (למעט בתצוגה המקדימה של המצלמה) או באזורי ריק במסר הראשי.

הערה: בעת הדלקת המסר, הקפד שלא לכוסות את חישון הקברבה. פעליה זו תביא לכיבוי מיידי של המסר לאחר הדלקתו כדי למנוע הפעלה לא רגילה בכיס או בתיק.


אוזניות סטריאו עם מיקרופון

כאשר האוזניות מחוברות, תוכל ליהנות ממוסיקה או יידאו עם צליל סטריאו, ולבור במחיאות מהמוסיקה/ידאו למענה על שיחות ולניתוק שיחות.

< חzikת >

לחצני הגברת עוצמה/הפחחת עוצמה

לחצן שיחה/ניתוק




- עברו שיחה נכנסת, לחץ כדי לקבל או לנתק שיחה.
- כאשר אתה מסازן למוסיקה, הקש כדי לעזור את הפעלה או מחדש אותה. לחץ פעמיים כדי להפעיל את הרצועה הבאה.

< גב >

מיקרופון



1. חיבור האוזניות כפי שמוצג באירור הבא.



היכרות עם הטלפון שלכם

2 לוח היישומים מוצג ותאך יכול לבחור יישום להפעלה.

הערה: ניתן לעורר את היישומים כך שיוצגו בלוח או להציג אותם כך שלא יוצגו בלוח היישומים. ראה <אביר>.

3 אם יש שיחה נכנסת כאשר האוזניות מחוברות לטלפון, לחץ על  כדי לענות לשיחה.

4 כדי לנטק את השיחה, לחץ על  שוב.

Plug & Pop

Plug & Pop מאפשר לך לבחור במהירות יישומים לשימוש בעת חיבור אוזנית או התקן On-the-Go, כגון עכבר או מקלדת.

1 לחבר אוזנית או התקן OTG (On-the-Go) (לדוגמה, עכבר, מקלדת, וכדו').

2 לוח היישומים יוצג ותאך יכול לבחור יישום להפעלה.

הערה: ניתן לעורר את היישומים כך שיוצגו בלוח או להציג אותם כך שלא יוצגו בלוח היישומים.

◀ הקש על  הגדרות > הcartיסייה כללי > אביר > אמצעי אחסון מסוג **USB** או אוזניות.

עצות בוגר למשך המגע

להלן מספר עצות בנושא ניוט בטלפון.

הקש או גע – הקשה באצבע ימינה בוחרת פריטים, קישורים, קיזורי דרך ואוותיות במקלחת שעל המסך.

גע והחזק – גע והחזק בפרט בתצוגה על-ידי הקשה עליון ואי-הרמה של האצבע עד שתתרחש פעולה. לדוגמה, כדי לפתוח אפשרות זמינות של איש קשר, גע והחזק את איש הקשר בראשימה 'אנשי קשר' עד שיופיע תפריט ההקשר.

גורו – גע והחזק בפרט לרגע ולאחר מכן, מבלי להרים את האצבע, הזו את האצבע על המסך עד שתציגו למיקום היעד. ניתן לגורר פריטים במסך הראשי כדי לשנות את מיקומם.

החלוקת רגילה או חילקה מהירה – כדי לבצע חילקה רגילה או חילקה מהירה, הזו את האצבע במהירות על-גביו שטח המסך, מבלי להשווות את האצבע כשאתה מ קיש על המסך לראשונה (כדי לא לגרום פריט בטעות). לדוגמה, באפשרות להחלק את המסך כלפי מעלה אומטה כדי לגלול רשימה, או לדפדף בין המomics הראשיים השונים על-ידי החילקה משמאלי לימין (ולהיפך).

הקשה כפולה – הקש פעמיים כדי להגדיל דף אינטראקטן או מפה. לדוגמה, הקש פעמיים במהירות על מקטע בדף אינטראקטן כדי להתאים אותו לרוחב המסך. תוכל גם להקיש פעמיים כדי לבצע הגדלה/הקטנה בזמן שאתה מציג את התמונה.

צבוט כדי לשנות את גודל התצוגה – השתמש באצבע המורה ובאגודל בתנועת צביטה או פריסה כדי להקטין או להגדיל את התצוגה כשאתה משתמש בדף דין או במפות, או כשאתה מדפסת בתמונות.

סובב את המסך – בישומים ותפריטים רבים, כיוון המסך מתאים他自己 לעצמו לכיוון הפיזי של המקשר.

הערה:

- כדי לבחור פריט, הקש על מרכז הסמל.
- אין צורך לחוץ חזק מדי, מסך המגע רגיש די כדי לחוש במגע קל אך החלטי.
- השתמש בקצה האצבע כדי להקש על האפשרות הרצואה. היזהר שלא להקש על אף מקש אחר.

המסך הראשי

המסך הראשי הוא נקודת ההתחלה לפונקציות ולישומים רבים, והוא מאפשר לך להוסיף פריטים כגון קיצורי דרך לשימושים או ידgelטים של Google כדי לקבל גישה מיידית למידע ולישומים. זהו לוח בירורת המandal והוא נגיש מכל תפריט עליידי.



הקשה על

שורת המצב

מציגה את מידע המצב של הטלפון כולל השעה, עצמתה האות, מצב הסוללה וסמלית התאראות.

וידג'ט

וידgelטים הם ישומים עצמאיים שנייתם לגשת אליהם מסך היזומים או מסך הראשי או מסך ראש מוחרב. בינויגן לקיצור דרך, הוודג'ט מופיע כישום במסך.

סמלית ישומים

הקש על סמל (ישום, תיקייה וכו') כדי לפתוח אותו ולהשתמש בו.

מצין מיקום

מצין איזה לוח של מסך הראשי אתה מציג.

אזור מקשיים מהירים

מספק גישה בנגיעה אחת לפונקציה בכל לוח של מסך הראשי.

לחצני מגע קדמים



מסך הראשי מורחב

מערכת הפעלה מספקת לוחות מרובים של מסך הראשי כדי לאפשר עוד שטח להוספת סמלים, וידgelטים ועוד.

◀ החלק את האצבע שמאליה או ימינה על פני המסך הראשי.

התאמת אישית של המסר הראשי

באפשרות להתאים אישית את המסר הראשי על-ידי הוספת יישומים, וידג'טים או על-ידי שינוי טפטים.

כדי להוסיף פרטיים למסר הראשי

1 לחץ לחיצה ארוכה בנקודה הריקה במסר הראשי.

2 בתפריט 'מצב הוספה',בחר את הפרט שברצונך להוסיף. הפרט שהוספה יופיע במסר הראשי.

3 גורר אותו למיקום הרצוי והרמת האצבע.

עצה! כדי להוסיף סמל יישום למסר הראשי, בתפריט 'ישומים', גע והחזק את היישום שברצונך להוסיף.

כדי להסיר פריט מהמסר הראשי

◀ מסר הראשי > גע ברציפות בסמל שברצונך להסיר > גורר אותו אל .

כדי להוסיף יישום כמקש מהיר

◀ מהתפריט 'ישומים' או במסר הראשי, הקש והחזק סמל יישום, וגורר אותו לאזור המקשים המהירים. ניתן להוסיף עד 7 יישומים.

כדי להסיר יישום מאזור המקשים המהירים

◀ גע והחזק את המקש המהיר הרצוי, וגורר אותו אל .

הערה:  המקש יישומים אינו ניתן להסרה.

כדי להתאים אישית סמל יישומים במסר הראשי

1 גע והקש על סמל יישום עד שנעלמו מהמייקום הנוכחי ובוטל. לאחר מכן שחרר אותו במסר. סמל העריכה יופיע בפינה הימנית העליונה של היישום.

2 הקש על  סמל היישוםשוב ובחר בעיצוב ובגודל הרצויים עבור הסמל.

3 הקש על אישור כדי לשמר את השינוי.


חזרה לישומים שהיו בשימוש לאחרונה

- 1 גע ווחזק את . במסך יופיע חלון מוקפץ ובו סמלים היישומים שבhem השתמשת לאחרונה.
- 2 הקש על סמל כדי לפתוח את היישום שלו. לחלוfin, הקש על  כדי לחזור למסך הקודם.

לוח התראות

התראות מדוחחות לר' על הגעת הודעות חדשות, אירועים בלוח השנה ומצבי חירום, וכן על אירועים מתחמכים, לדוגמה, כאשר אתה בשיחה. כשמגיעה התראה, הסמל שלה מופיע בחלק העליון של המסך. סמלים של התראות מסוימות מופיעים משמאלי, וסמלים אחרים, כגון Wi-Fi או עצמת סוללה, מופיעים מימין.

הערה: האפשרויות הזמניות משתנות בהתאם לאזרור או לספק השירות.



פתיחת לוח התראות

החלק כלפי מטה משורת המצב כדי לפתוח את חלונית התראות.

אזור החלפה המהירה

הקש על כל מקש החלפה מהירה כדי להפעיל/לכבות אותו. גע ווחזק את המקש כדי לגשת לתפריט ההגדרות של הפונקציה. להציג מקשי החלפה נוספים, החלק שמאלה או ימינה. הקש על כדי להסיר, להוסיף או לשנות את הסדר של מקשי החלפה.

ישומי QSlide

הקש על יישום QSlide כדי לפתוח אותו כחלון קטן בمسך. הקש על כדי להסיר, להוסיף או לשנות את הסדר של יישומי QSlide.

הקש כדי לנוקוט את כל התראות.

התראות

התראות הנוכחיות מפורטוות, כל אחת עם תיאור קצר. הקש על התראה כדי להציג אותה.

כדי לסגור את לוח התראות, גע וגורור את הלשונית אל עבר הקצה העליון של המסך.



סמלים מחוונים בשורת המצב

סמלים מחוונים מופיעים בשורת המצב בחלקן העליון של המסך כדי לדוח על שיחות שלא נענו, הודעות חדשות, אירועים בלוח השנה, סטטוס המכשיר ועוד.



הסמלים המוצגים בחלקן העליון של המסך מספקים מידע על סטטוס המכשיר.
הטבלה שלහן מציגה אחדים מהסמלים הנפוצים ביותר.

סמל	תיאור	סמל	תיאור
	הצלול מושתק		לא הוכנס כרטיס SIM
	מצב רטט מופעל		אין אות רשות זמיין
	הסוללה טעונה במלואה		מצב טישה מופעל
	הסוללה נטענת		מחובר לרשת Wi-Fi
	הטלפון מחובר למחשב באמצעות כבל USB		האזניות הקוויות מחוברות
	הורדת נתונים		מתבצעת שיחה
	העלאת נתונים		שיחה שלא נעננה
	GPS פועל		Bluetooth מופעל
	נתוני מיקום מתקובלים GPS-מ-GPS		NFC פועל
	הנתונים מסתנכרנים		התראת מערכת
	קיימת הודעה חדשה ב-Email		הוגדרה התראה
	קיימת הודעה חדשה Hangouts		קיימת הודעה קולית חדשה
	בחר שיטת קלט		קיימת הודעה טקסט או מולטימדיה חדשה

DLNA המודול המוסיקה המתווגנת		שיר מושמע בicut	
---------------------------------	--	-----------------	--

הערה: מיקום הסמלים בשורת המ Zub เปssiי לשתנות בהתאם לפונקציה או לשירות.

מקלדת וירטואלית

ניתן להזין טקסט גם באמצעות המקלדת הוירטואלית. המקלדת מוצגת על המסך אוטומטית כשלעצמה להזין טקסט. כדי להציג ידנית את המקלדת, פשוט הקש על שדה טקסט שבו תרצה להזין טקסט.

שימוש בלווח המקשים והזנת טקסט

הקש פעם אחת כדי להפוך את האות הבאה שתתקליד לאות רישית. הקישו פעמים כדי שכל האותיות יהיו רישיות.

הקש כדי לעבור למקלדת של מספרים וסמלים.

הקש כדי לעבור למצב כתוב ידי.

הקש כדי להזין רווח.

הקש כדי ליצור שורה חדשה.

הקש כדי למחוק את התו הקודם.

הזנת אותיות עם סימני הטעמה

כאשר אתה בוחר ב'צרפתי' או 'ספרדי' כשותת הזנת טקסט, אפשרות להזין תווים מיוחדים הקיימים בצרפתית או בספרדית (למשל "á").

לדוגמה, כדי להזין "á", גע ברציפות במקש "a" עד שמקש ההגדלה יגדל ויצא תווים של שפות שונות.

לאחר מכן בחר את התו המיוחד הרצוי.

כשאתה מפעיל את הטלפון בפעם הראשונה, יש לך הזדמנות להפעיל את הרשות, להיכנס לחשבון Google שלך ולבחור כיצד ברצונך להשתמש בשירותי Google מסויימים.

כדי להגדיר את חשבון Google שלך:

- היכנס לחשבון Google ממסך הначיות הרתקינה.
או
- הקש על  > הלקוחיסיה **"ישומים"** >בחר "ישום של Google", כגון **Gmail** > בחר באפשרות **חדש** כדי ליצור חשבון חדש.
אם יש לך חשבון Google, הקש על האפשרות **קיים**, הזן את כתובת הדואר האלקטרוני ואת הסיסמה שלך, ולאחר מכן הקש על .
- לאחר שהגדרת את חשבון Google שלך בטלפון, הטלפון יסתנכרן באופן אוטומטי עם חשבון Google באינטרנט.
- אנשי הקשר, ההודעות ב-Gmail, האירועים בלוח השנה ופרטים נוספים מיישומים ושירותים אלה באינטרנט יסתנכרנו עם הטלפון שלך. (הדבר תלוי בהגדרות הסנכרון שלך).
- לאחר הכניסה תוכל להשתמש ב-Gmail ובסירותי Google דרך הטלפון.

Wi-Fi

עם Wi-Fi אפשרו לשתף במכשיר לאינטרנט מהיר בטוח כיסוי נקודת הגישה (AP) האלחוטית. תוכל ליהנות מਆינטרנט אלחוטי באמצעות Wi-Fi, ללא תשלום נוספת.

התחברות לרשתות Wi-Fi

כדי להשתמש ב-Wi-Fi בטלפון, עליך לגשת לנקודת הגישה האלחוטית, או 'נקודת חמה'. חלק מנקודות הגישה הן פתוחות, ופשוט ניתן להתחבר אליהן. אחרת נסתרות או שחולות בין תכונות אבטחה אחרות, ולכן נדרש להגדיר את הטלפון כך שיאכל להתחבר אליהן. כאשר איןך משתמש ב-Wi-Fi, כבاه אפשרות זו כדי להאריך את חיי הסוללה.

הערה: אם איןך בתוך אזור Wi-Fi או שהגדרת את Wi-Fi ככבי, יתכן שספק השירות יחיל חיבורים נוספים עבור שימוש בתנאים סולריים.

הפעלת Wi-Fi והתחברות לרשת Wi-Fi

1 הקש על  > הcrcטיסיה יישומיים >  הגדרות > crcטיסיה רשתות > Wi-Fi.

2 הגדר את Wi-Fi לפועל כדי להפעיל אותו והתחיל בسؤالה לאיתור רשתות Wi-Fi זמיןות.

3 הקש על התפריט 'ו-Wi' פעם נוספת כדי להציג רשימה של רשתות Wi-Fi פעילות הנמצאות בטוחה.

. הרשות המאוובתות מסומנות בסמל של מנעול.

4 הקש על רשת כדי להתחבר אליה.

. אם הרשות מאובטחת, תונחה להזין סיסמה או הרשותות אחרות. (פנה אל מנהל המערכת לקבלת פרטיים)

5 שורת המציג מציגה סמלים המצביעים את מצב Wi-Fi.

Bluetooth

ניתן לשלווח נתונים באמצעות Bluetooth על-ידי הפעלת יישום מתאים, אך לא דרך תפריט Bluetooth כמו במרבית הטלפונים הניידים.

הערה:

- LG אינה אחראית לאובדן, יירוט או שימוש לרעה של נתונים שנשלחו או נקלטו דרך תכונת Bluetooth אלחוטי.
- וDAO תמיד שאותם משתמשים ומקבלים נתונים ממכשירים מהימנים המאוביוחים כיואט.
- מכשולים בין המכשירים עלולים להקטין את מרחק הקליטה.
- חלק מהמכשירים, ובמיוחד אלה שלא בדקנו ואושרו על-ידי SIG, עלולים Bluetooth SIG לא להתאים למכשירים שלך.

הפעלת Bluetooth ושיוור הטלפון שלך עם מכשיר Bluetooth

עליך לשער את המכשיר שלך למכשיר אחר לפני שתת לחבר אליו.

1 **הקש על**  **> הרכטיםיה ישומים >**  **הגדרות > הרכטיםיה רשותות > הגדר את Bluetooth למופעל.**

2 **הקש על תפריט Bluetooth** שוב. תראה אפשרות להפוך את הטלפון שלך לגליי ואפשרות לחפש מכשירים. כעת הקש על חפש מכשירים כדי להציג את המכשירים שנמצאים באותו מקום Bluetooth.

3 **בחר מהרשימה את המכשיר שאליו ברצונך לשער את הטלפון שלך.** לאחר שהשיור יסתים בהצלחה, המכשיר שלך יתחבר למכשיר האחד.

הערה: יתכן שבמכשירים מסוימים, במילוי אוזניות או דיבוריות לרכב, יהיה קוד PIN קבוע-ל-Bluetooth, לדוגמה 0000. אם למכשיר האחר יש קוד PIN, תתבקש להזין אותו.

שליחת נתונים באמצעות התכונה Bluetooth אלחוטי

1 **בחר קובץ או פריט, כגון איש קשר, אירוע בלוח השנה או קובץ מדיה, מתוך יישום מתאים או מתוך הורדות.**

2 **בחר באפשרות שליחת נתונים דרך Bluetooth.**

הערה: יתכן שהשיטה לבחירת אפשרות תהיה שונה בהתאם לסוג הנתונים.

3 חיפוש מכשיר המותאם לשימוש Bluetooth ושינוע אליו.

渴求 נתונים באמצעות התוכנה **Bluetooth אלחוטי**.

1 הקש על  > הcartיסיה יישומים >  הגדרות > הcartיסיה רשות > הגדר את **Bluetooth** למופעל.

2 הקש על התפריט **Bluetooth** שב והוסף סימן ביקורת בתיבת הסימון שבראש המספר כדי שייהי גלוי במכשירים אחרים.

הערה: כדי לבחור את מועד הזמן שהמכשיר יהיה גלוי, הקש על  מועד זמן נראות.

3 בחר באפשרות **קבל** כדי לאשר שאתה מוקן לקבל נתונים מהמכשיר.

יתוף החיבור של נתוני הטלפון

חיבור כמודם סולרי USB ונקודה חמה ניידת ב-Wi-Fi הן תוכנות נהדרות כשיין חיבורם אלחוטיים זמינים. באפשרותך לשתף את חיבור הנתונים הנידי של הטלפון עם מחשב אחד, דרך כבל USB (חיבור כמודם USB). תוכל גם לשתף את חיבור הנתונים של הטלפון עם יותר ממכשיר אחד בו-זמנית, על ידי הפיכת הטלפון לנקודה חמה ניידת של Wi-Fi.

כאשר הטלפון משתף את חיבור הנתונים שלך, מופיעים סמל בשורת המצב והתראה מתמשכת במנגנון ההתראות. לקבלת המידע העדכני ביותר על האזמנת התקנים ונקודות חממות ניידות, לרבות מערכות הפעלה נתמכות ופרטים נוספים, בקר בכתובת <http://www.android.com/tether>.

כדי לשתף את חיבור הנתונים של הטלפון כנקודה חמה ניידת של Wi-Fi

1 הקש על  > הcartיסיה יישומים >  הגדרות > הcartיסיה רשות > רשות ושיתוף אינטרנט > המתג נקודה חמה ניידת ב-Wi-Fi להפעלה.

2 הzin סיסמה והקש על שמו.

עזה! אם במחשב שלך פועל Windows 7 או מהדרה עדכנית של סוגים מסוימים של Linux (כגון Ubuntu), בדרך כלל אין צורך להכין את המחשב לחברו כמודם USB. לעומת זאת, אם במחשב פועלת גרסה מודקמת יותר של Windows יתיר לך להקם חיבור לרשת דרך USB. אחרת, ניתן שהייה עלייך להכין את המחשב כדי להקם חיבור לרשת דרך USB. לקבלת המידע העדכני ביחס על מערכות הפעלה שתומכות בשיתוף באמצעות USB וכיידך להגדיר אותן, בקר בכתובת <http://www.android.com/tether>.

כדי לשנות את שמה של נקודת החמה הנידית או לאבטח אותה באפשרות לשנות את השם של רשת Wi-Fi של הטלפון (SSID) ולאבטח את רשת Wi-Fi שלו.

1 הקש על  > הכרטיסיה ישומים >  הגדרות > הכרטיסיה רשות > ושיטוף אינטראקט > נקודת חמה נידית Wi-Fi.

2 הקש על האפשרות הגדר נקודת חמה של Wi-Fi.

- תיבת הדוא-שייח הגדר נקודת חמה של Wi-Fi תיפתח.
- באפשרות לשנות את ה-SSID של הרשת (השם) אשר התקנים אחרים רואים בעת סריקה לאיתור רשות Wi-Fi.
- תוכל גם להקיש על התפריט **אבטחה** כדי לקבוע את תוכנת הרשת עם אבטחה מסוג 2 Wi-Fi Protected Access 2 (WPA2) המבוססת על מפתח שותף מראש (PSK).

גיעה באפשרות האבטחה **PSK WPA2** תגרום להוספה שדה סיסמה לתיבת הדוא-שייח הגדר נקודת חמה של Wi-Fi. אם תזין סיסמה, יהיה עלייך להזין סיסמה זו בעת התחברות לנקודת החמה של הטלפון בעזרת מחשב או התקן אחר. לחילופין, באפשרות להגדיר את **פתח בתפריט אבטחה** כדי לבטל את האבטחה של רשת Wi-Fi.

3 הקש על שמו.

שים לב! אם תaddir את אפשרות האבטחה 'פתוח', לא תוכל למנוע שימוש בלתי מורשה בשירותים מקוונים על-ידי אנשים אחרים, ויתכן שתתברר חיבורים נוספים. כדי למנוע שימוש בלתי מורשה, מומלץ לדאוג שאפשרות האבטחה תהיה פעילה.

Wi-Fi Direct

Wi-Fi Direct תומך בחיבור ישיר בין התקנים מאופשי Wi-Fi ללא נקודת גישה. עקב ניצול הסוללה הגבוהה ב-Wi-Fi Direct, מומלץ לחבר את הטלפון לשקע חשמל בעת השימוש בתוכנה Wi-Fi Direct-i. בדוק את רשות Wi-Fi Direct ו-Wi-Fi Directed מראש, וודא שהמשתמשים מחוברים לאותה הרשת.

כדי להפעיל את Wi-Fi Direct:

1. הקש על  **מקש התפריט** < הגדרות מערכת > 
2. הקש על  Wi-Fi Direct בתחתית המסך.
3. בחר מכשיר כדי להתחבר אליו מתוך רשימת המכשירים שנדרקו.


שימוש ב-SmartShare

SmartShare עשויה שימוש בטכנולוגיית DLNA (Digital Living Network) לשיתוף תוכן דיגיטלי דרך רשת אלחוטית. שני המכשירים חיברים לשאת אישור DLNA כדי לתמוך בתוכנה זו. תאפשר להנחות מהתוכנה SmartShare Polaris Office, 'מוסיקה', 'ויאדו' ו-'Polaris Office'.

1. בתוכון שברצונך להפעיל או לשדר, הקש על .
2. הקש על **הפעל** או **Beam** בתיבת הדו-שיח.
- **הפעל:** באפשרות להזרים את התוכן שלך דרך טלוויזיה, רמקול Bluetooth וכו'.
- **Beam:** באפשרות לשЛОח את התוכן שלך להתקני Bluetooth או לטלפונים או טבלטים של LG הנתמכים על-ידי SmartShare Beam*. Wi-Fi Direct דרך SmartShare Beam*.

התחברות לרשתות ולמכשירים

- 3 הקש על המכשיר ברשימת כדי להפעיל או לקלֶב.
- אם המכשיר אינו ברשימה, ודא במכשיר שchip'ר Wi-Fi או Wi-Fi Direct מופעל. לאחר מכן הקש על **סrox Bluetooth**.
- 4 הקש על **שלוח**.
- כדי להנות מתוכן ממכשירים סמוכים, כגון מחשב או התקן נייד, טלפון
- 1 כדי לחבר את המכשירים הסמוכים לטלפון, הקש על **מכשירים סמוכים** בישום גלריה, מוסיקה או וידאו כמפורט להלן.



- ודא שהטלפון והמכשירים הסמוכים מחוברים לאותה רשת Wi-Fi.
 - ודא שהתקינה DLNA במכשיר הסמור מופעלת.
- 2 הקש על המכשיר להתחברות.
- אם המכשיר אינו מופיע ברשימה, הקש על **חפש מכשירים סמוכים**.
לאחר ההתחברות, תוכל להנות בטלפון שלך מהמכשיר הסמור.

חיבורם למחשב עם כבל USB

- למד ל לחבר את המකשיר שלך למחשב באמצעות כבל USB במצבי חיבור USB.
- העברת מוסיקה, תמונות וסרטוני יידאו באמצעות מצלב אחסון בנפח גדול ב-USB**
- 1 חבר את הטלפון שלך למחשב באמצעות כבל USB.
 - 2 אם לא התקנתה במחשב את **Android Platform Driver**, תציגך לשנות את ההגדירות באופן ידני. בחוץ בהגדירות **מערכת > כללי > חיבור PC** > בחור **שיטת חיבור USB** ולאחר מכן בחור באפשרות **סינכרון מדיה (MTP)**.
 - 3 בעת אפשרות להציג את תוכן האחסון בנפח גדול במחשב ולהעביר את הקבצים.

סינכרון עם Windows Media Player

- ואו ש-Windows Media Player מותקן במחשב שלך.
- 1** השתמש בכבל ה-USB כדי לחבר את הטלפון למחשב שבו מותקן Windows Media Player.
- 2** לחבר באפשרות **סינכרון מדיה (MTP)**. כאשר המකשיר מחובר, יופיע במחשב חלון מוקף.
- 3** פתח את Windows Media Player כדי לסינכרן קובצי מוסיקה.
- 4** עורך או הזין את שם המකשיר בחלון המוקף (במקרה הצורר).
- 5** בחור את קובצי המוסיקה הרצויים וגורור אותם לרישימת הסינכרון.
- 6** התחלה את הסינכרון.
- יש למלא את הדרישות הבאות כדי לבצע סינכרון עם Windows Media Player

דרישה	פריטים
Vista ,Microsoft Windows XP SP2 או גרסה מתקדמת יותר	מערכת הפעלה
Windows Media Player 10	גרסת Window Media Player ומעלה

- אם הגרסה של Windows Media Player נמוכה מ-10, התקן את גרסה 10 או גרסה מתקדמת יותר.

ביצוע שייחה

- 1 הקש על כדי לפתחו את לוח המקשימים.
- 2 הzan את המספר בלוח המקשימים. כדי למחוק ספרה, הקש על הסמל .
- 3 הקש על כדי לבצע שייחה.
- 4 כדי לסיים שייחה, הקש על הסמל סיום.

עצה! כדי להזין "+" לביצוע שייחות בינלאומיות, לחץ לחיצה ממושכת על הסמל [0].

 התקשרות לאנשי הקשר

- 1 הקש על כדי לפתחו את אנשי הקשר.
- 2 גלול ברשימה אנשי הקשר או הzan את האותיות הראשונות של שם איש הקשר המבוקש על-ידי הקשה על חפש אנשי קשר.
- 3 ברשימה, הקש על שאליו ברצונך להתקשרות.

מענה לשיחת ודחיתת שייחה

כשאתה מקבל שייחה במצב נעליה, החלק את בכיוון כלשהו כדי לענות לשיחת הנכנסת.

החלק את בכיוון כלשהו כדי לסרוב לשיחת נכנסת.

החלק את הסמל דחה שייחה ושליח הודעה מהחלון התחתון אם ברצונך לשלוח הודעה.

עצה! דחה שייחה ושליח הודעה באמצעות פונקציה זו ניתן לשולח הודעה במהירות. אפשרות זו שימושית כאשר אתה מדרש לדוחות שייחה במהלך פגשך.

התאמת עוצמת הקול בשיחה

כדי להתאים את עוצמת הקול במהלך שיחה, השתמשו במקשי הגברת והחלשת עוצמת הקול שבצד הימני של הטלפון.

ביצוע שיחה נוספת

- 1 במהלך השיחה הראשונה שלך, הקש על **מקש התפריט**  **<+** **הוסף** שיחה וחיג את המספר. באפשרות גם לעבור לרשימת המספרים שהויגו לאחרונה על-ידי הקשה על  **5**, או לחפש אנשי קשר על-ידי הקשה על  **2** ובחירה איש הקשר שאלוי ברצונך להתקשר.
- 2 הקש על  **3** כדי לבצע את השיחה.
- 3 שתי השיחות יוצגו במסך השיחות. השיחה הראשונה שלך תינעל ותועבר למסך המתנה.
- 4 כדי לעبور בין שיחות, הקש על המספר המוצג. לחופין, הקש על האפשרות  **4** **מייזוג** **שיחות** כדי להתחיל שיחת עידיה.
- 5 כדי לסיים שיחות פעילות, הקש על **ניטוק** או הקש על  **6**, החליק מטה את שורת ההתראות ובחר בסמל **סיום**  **7**.

הערה: תחביב עبور כל שיחה שתבוצע.

צפיה ביוםני השיחות

במסך הראשי, הקש על  **8** ובחר בכרטיסיה **יוםני** **שיחות**  **5**.
הציג רשימה מלאה של כל השיחות שהויגו, שהתקבלו ושלא נענו.

עזה!

- הקש על כל אחד מהפריטים ביוםן השיחות כדי להציג את התאריך, השעה ומשך השיחה.
- הקש על **מקסם התפריט** , ולאחר מכן הקש על האפשרות **מחק הכל** כדי למחוק את כל הפריטים המוקלטים.

הגדרות שיחה

באפשרותך לקבוע את התצורה של הגדרות שיחת טלפון, כגון הפניות שיחה, וכן תוכנות מיוחדות אחרות שספק השירות שלך מציע.

- 1** במסך הראשי, הקש על .
- 2** הקש על .
- 3** הקש על **הגדרות שיחה** ובחר את האפשרויות שברצונך לשנות.

הוסף אנשי קשר לטלפון וסנכרן אותם עם אנשי הקשר בחשבון Google שלך או בחשבונות אחרים שתומכים בסנכרון אנשי קשר.

חיפוש איש קשר

במסך הראשי

- 1 **הקש על  כדי לפתחו את אנשי הקשר.**
- 2 **הקש על  חפש אנשי קשר והזן את שם איש הקשר באמצעות המקלדת.**

הוספה איש קשר חדש

- 1 **הקש על  הzin את המספר של איש הקשר החדש ולאחר מכן הקש על  התפריט .** הקש על **הוסף לאנשי קשר > איש קשר חדש**.
- 2 **אם ברצונכם להוסיף תמונה לאיש הקשר החדש, געו באזור התמונה.**
בחר מ בין האפשרויות **צלם** או **בחר מהגלארייה**.
- 3 **בחר את סוג איש הקשר על-ידי הקשה על .**
- 4 **הקש על **קטגורית פרט** איש קשר והזן את פרטיו.**
- 5 **הקש על **שמור**.**

אנשי קשר מועדפים

באפשרות לסוג אנשי קשר שאליים אתה מתקשר לעתים קרובות כמועדפים.

הוספה איש קשר למועדפים

- 1 **הקש על  כדי לפתחו את אנשי הקשר.**
- 2 **הקש על איש קשר כדי להציג את פרטיו.**
- 3 **הקש על **כוכב** בפינה הימנית של שם איש הקשר. הכוכב ישנה את צבעו לצהוב.**

הסרת איש קשר מרשימה המועדים

- 1 הקש על  כדי לפתח את אנשי הקשר.
- 2 הקש על הלקוחיסיה  ובחר איש קשר כדי להציג את פרטיו.
- 3 הקש על הכוכב בצד שמאל בפינה הימנית של שם איש הקשר. הכוכב ישנה את צבעו לאפור ואיש הקשר יוסר מהמועדפים שלו.

יצירת קבוצה

- 1 הקש על  כדי לפתח את אנשי הקשר.
- 2 הקש על **קבוצות** והקש על **מქש התפריט** . בחר **קבוצה חדשה**.
- 3 הzin שם למועדון החדש. תוכל גם להגיד צלצל עבור הקבוצה שזה עתה נוצרה.
- 4 הקש על **שמור** כדי לשמר את הקבוצה.

הערה: אם תמחקו קבוצה, אנשי הקשר שהוקצו למועדון זו לא ילווה לאיבוד. הם ישארו ברשימהת אנשי הקשר שלכם.

טלפון שלך משלב הודעות SMS ו-MMS בתפריט יחיד, אינטואיטיבי וקל לשימוש.

שליחת הודעה

- 1 **הקש על**  **במסך הראשי**, והקש על  **כדי לפתח הודעה ריקה**.
- 2 **הן שם** של איש קשר או מספר להתקשרות בשדה **אל**. **טור** כדי **הזנת** שם איש **קשר** יופיעו אנשי קשר מתאימים. תוכל להקש על נמען מוצע. **ניתן להוסיף** יותר איש קשר אחד.

הערה: תחביב בתשלום על הודעה טקסט עبور כל אדם שאליו תשליח את ההודעה.

- 3 **הקש על השדה **הן הודעה** והתחל לחבר את ההודעה.**
- 4 **הקש על**  **כדי לפתח את התפריט 'אפשרויות'**. בחר מבין האפשרויות **הודעה מהירה, הוסף סמייל, לוח זמנים נשלח, הוסף נושא וביטול**.

עזה! אפשרותך להקש על הסמל  **כדי לצרף הודעה את הקובץ שברצונך לשתף**.

- 5 **הקש על **שלח** כדי לשלוח את ההודעה.**
- 6 **התשובות יופיעו** במסך. כאשר תציג ותשליח הודעות נוספות נספנות, ייווצר רצף **הודעות**.

⚠️ **אזהרה:**

- מגבלת 160 התווים עשויה להשנות ממדינה למדינה, בהתאם לשפה ולצורת הקידוד של הודעות SMS.
- בהוספת תמונה, סרטון וידאו או קובץ שמע להודעת SMS, הפריט יעבור המרה אוטומטית להודעת MMS ואתם תחויבו בהתאם.

תיבה ברצף

ניתן להציג הודעות (SMS, MMS) שהוחלפו עם אחרים בסדר כרונולוגי, כך שניתן לראות בקלות מעין סקירה כללית של שיחתך.

שינוי הגדרות ההודעה

הגדרות ההודעות בטלפון שלך נקבעו מראש, כדי שתוכל לשЛОח הודעות מייד.

באפשרותך לשנות את הגדרות לפי העדפותיך.

- הקש על הסמל **הודעות** במסר הראשי, הקש על  ולאחר מכן הקש על **הגדרות**.

ניתן להשתמש בישום הדוא"ל כדי לקרוא הודעות דוא"ל משלוחים כגון Gmail. ישום הדוא"ל תומך בסוגי החשבונות הבאים: POP3, IMAP ו-e-Exchange. השירות או מנהל המערכת שלר יכולם לספק לך את הגדרות החשבון הדרושים.

ניהול חשבון דוא"ל

בפעם הראשונה שתפתח את יישום הדוא"ל, יפתח אשי' התקינה שיעזר לך להציג חשבון דוא"ל.

לאחר ההגדרה הראשונית, יישום הדוא"ל יציג את תוכן תיקת הדואר הנכנס שלך. כדי להוסיף חשבון דוא"ל:

- הקש על > הרטיסייה "ישומים" > דוא"ל > הקש על > הגדרות

כדי לשנות את ההגדרות של חשבון דוא"ל:

- הקש על > הרטיסייה "ישומים" > דוא"ל > הקש על > הגדרות > הגדרות כלליות.

כדי למחוק חשבון דוא"ל:

- הקש על > הרטיסייה "ישומים" > דוא"ל > הקש על > הגדרות > הקש על > הסר חשבון > בחר את החשבון למחיקה > הסר > בחר ב'כן'.

עבודה עם תיקיות החשבון

הקש על > הרטיסייה "ישומים" > דוא"ל > הקש על ובחר באפשרות **תיקיות**.

לכל חשבון ישנן תיקיות דואר נכנס, דואר יוצא, פרטיים שנשלחו וטיוטות. בהתאם לתוכנות שבahn תומך ספק השירות של החשבון, יתכן שהיו לך תיקיות נוספות.

chipur shel shilcha shel doar

כדי לחבר ולשלוח הודעה

- 1 בישום דוא"ל, הקש על .

הזה כתובות עברו הנמען המיועד של הודעה. תוך כדי הזנת הטקסט יוצאו כתובות תואמות מרשימה אנשי הקשר שלך. הפרד בין כתובות רבות בamusot tivo נקודת-פ洋洋ק.

- 2 3 הקש על  כדי להוסיף עותק/עותק מוסתר והקש על  כדי לצלף קבצים, במקרה הצורך.

הזה את טקסט הודעה.


- 4 5 הקש על .

עצה! כשהודעת דוא"ל חדשה מגיעה לתיבת הדואר הנכון, תקבל התראה על קר באמצעות ציליל או רטט.

ששצלמת ה-OIS (Optical Image Stabilizer) בטלפון, תוכל לצלם תמונת ברורה יותר על-ידי מניעת רעדת פיזית. התוכנה Multi Point AF (מייקוד אוטומטי מרובה נקודות) מאפשרת לך לקבל תמונת ברורה יותר וטבעית גם אם האובייקטיבים אינם במרכז.

כדי לפתוח את יישום המצלמה, הקש על **מצלמה** במסך הראשי.

הקרת התצוגה המקדימה



- ❶ **הבדיקה** – בחר מבין האפשרויות **כבי** ④, **מופעל** ③, **אוטומטי** ⑤.
- ❷ **החלף מצלמה** – למעבר בין המצלמה האחראית לבין המצלמה הקדמית.
- ❸ **מצב צילום** – בחר מבין האפשרויות **רגיל**, **צלם ונקה**, **צליל>Dינמי** (HDR), **פונרומה**, **פונרומה VR**, **צלום רציף**, **צלום יופי**, **מצלמה כפולה**, **צלום לכידת זמן**, **צלום חכם**, **ספורט או לילה**.
- ❹ **הגדירות** – הקש על סמל זה כדי לפתוח את תפריט ההגדירות.
- ❺ **מצב וידאו** – הקש והחלהק סמל זה למטה כדי לעבור למצב וידאו.
- ❻ **לחצן הצמצם**
- ❼ **галריה** – הקש כדי להציג את התמונה الأخيرة שצילמת. כך ניתן להיכנס לגלריה ולצפות בתמונות השמורות כשאתה נמצא במצב מצלמה.

הערה: יש לוודא שעדשת המצלמה נקייה לפני הצלום.

שימוש בהגדרות המתקדמיות

ב>Showcase המקדימה, הקש על  כדי לפתח את האפשרויות המתקדמיות. ניתן לשנות את הגדרות המצלמה עלי ידי גלילה בראשינה. לאחר בחירה באפשרות, הקש על .

 כדי לצלם תמונה, אמרו אחת מהמילים הבאים: Smile, Cheese, Kimchi או LG Whisky.

 מגדיר וקובע את כמות אור השימוש הנכונות לתמונה.

 הקש כדי לבחור את מצב המיקוד.

 בוחר את רזולוציית התמונה. אם תבחר רזולוציה גבוהה, גודל הקובץ יגדל, והמשמעות היא שתוכל לאחסן בזיכרון פחות תמונות.

 דירוג ה-ISO קובע את רגישות חיישן האור של המצלמה. ככל שעריך ה-ISO גבוהה יותר, כך המצלמה רגישה יותר. הדבר מועיל בתנאי תאורה חשוכים כאשר לא ניתן להשתמש במצלק.

 משפר את איזוט הצבע בתנאי תאורה שונים.

 מוסיף אפקטים אמנותיים לתמונות.

 מגדיר השהיה לאחר לחיצה על לחץ הצילום. מצב זה אידיאלי במקרה שתרצה להיות בתמונה עצמן.

 הפעל כדי להשתמש בשירותים מבוססי-המיקום של הטלפון. צלים תמונות בכל מקום שבו אתה נמצא ותיג אותן עם המיקום המתאים. אם תעלה תמונות מתוצאות לבלוג התומך בתיאוג מיקום, תוכל לראות את התמונות מוצגות על גבי מפה.

הערה: פונקציה זו זמינה רק כאשר פונקציית GPS פעילה.

בוחר צליל צמצם.

הגדיר את מקש עוצמת הקול כדי לבחור אם להשתמש בצלום או בהגדלה.	
פותח את מדריך העזרה כדי לדעת כיצד פועלת פונקציה.	
משחזר את כל ההוראות ברירת המחדל של המצלמה.	

עצה!

- כשתצא מפונקציית המצלמה, חלק מההוראות יוחזרו לערכיו ברירת המחדל שלון.
- לדוגמא איזון לבן, אפקט צבע, טיימר ומצב צילום. בדוק אותן לפני הצלום הבא שלך.
- תפריט ההוראות מופיע מעל התצוגה המקדימה, כך שאם תנסה רכיב צבע או אינט'
- בתמונה, תראה תצוגה מקדימה של התמונה עם השינויים מאחרו התפריט 'הוראות'.

צלום מהיר

- 1 פותח את היישום **צלמה** וכוכן את העדשה לעבר הנושא שברצונך לצלם.
- 2 תיבות פוקוס יופיעו במרכז מסך התצוגה המקדימה. ניתן גם להקייש במקום קלשו במסך כדי להציב את הפוקוס בנקודה זו.
- 3 כשתיבת המיקוד הופכת לירוקה, זה סימן שהצלמה התחמכה בנושא הצלום.
- 4 הקש על כדי ללכוד את התמונה.

שימוש במצב 'צלם ונקה'

תוכנה זו מאפשרת לצלמה לזרות אובייקטים שייתכן שאין מעוניין בהם בתצלום. לאחר צילום התצלום, הקש על אובייקט בעל קו מתאר* כדי להסיר אותו, ולאחר מכן לשמור את התצלום.

- 1 פותח את יישום המצלמה.
- 2 הקש על > **צלם ונקה**.
- 3 הקש על כדי לצלם תמונה.

- 4** הקש על אחד מהאובייקטים בעלי קו המתאר כדי להסיר אותם מהתצלום, ולאחר מכן הקש על .

* בעת צילום תמונה, אובייקטים נעים מוצגים כקווים מוקווים.

הערות

- צלם תמונה לאחר תיקון המצלמה במקום אחד.
- אם הצביע של נושא זהה לרקע, ניתן יהיה ללחות רק חלקו, או שהדבר יהיה קשה לਮחיקה.
- אם נושא נוע הוא קטן או גדול מדי, יתכן שהוא יהיה קשה למחיקה.
- אם הנושא נוע באופן חסר חשיבות, יתכן שהוא לא יזווה.

שימוש במצב מצלמה כפולה

מאפשר לך לצלם תמונה עם המצלמות הקדמית וה האחורי ב-זמןית, במשולב בתמונה אחת.

- 1** פתח את יישום המצלמה.
- 2** הקש על  **מצלמה כפולה**.
- 3** תיבת קטנה של התצוגה המקדימה מופיעה במסך הראשי של התצוגה המקדימה. הגדר את הצלום.
- גורר את התצוגה המקדימה הקטנה כדי להעביר אותה למיקום שבו אתה מעוניין בה בתצלום.
- הקש ווחזק את התצוגה המקדימה הקטנה כדי לשנות את גודלה, במקרה הצורך.
- הקש על התצוגה המקדימה הקטנה כדי להחליף את העדשה בין התצוגה המקדימה הראשית והתצוגה המקדימה הקטנה.
- 4** הקש על  כדי לצלם תמונה משולבת.

שימוש במצב צילום לצד זמן

- מaddir את המצלמה לכלוד רגעים חסרים על-ידי צילום חמץ תמונות רצופות לפני הkey על .
- 1 פתח את יישום המצלמה.
 - 2 הקש על  <  צילום לצד זמן.
 - 3 הקש על  כדי לצלם תמונה.
 - 4 כדי להציג את הרגעים ממש לפני שהתמונה צולמה, הקש על התמונה הממוזערת של התמונה בתחתית מסך המצלמה.
 - 5 בחר את התמונות שברצונך להشير, ולאחר מכן הקש על  בראש המסך.

לאחר צילמת תמונה

Tap the image thumbnail at the bottom of the Camera screen to view the last photo you took

הקש כדי לשთף את התמונה שלך באמצעות הפונקציה SmartShare .	
הקש כדי לצלם תמונה נוספת מיד.	
הקש כדי לשלוח את התמונה אחרים או לשתף אותה בשירותי רשות חברות.	
הקש כדי למחוק את התצלום.	

עצה! אם יש לך חשבון SNS והגדרת אותו בטלפון, אפשרות לשთף את התמונה שלך עם קהילת SNS.

הערה: אם אתה מוריד הודעות MMS תוך כדי נדייה, "יתכן שיחולו חיבורים נוספים".

הקש על מקש התפריט  כדי לפתח את כל האפשרויות המתקדמיות. הגדר תמונה בתור – הקש כדי להשתמש בתצלום כתמונה של איש קשר, טפט המסך הראשי או טפט מסך געילה.

העבר – הקש כדי להעביר את התמונה למקום אחר.

העתק – הקש כדי להעתיק את התמונה הנבחרת ולשמור אותה באלבום אחר.

העתק אל מגש הגזרים – הקש כדי להעתיק את התמונה ולאחסן אותה ב'מגש הגזרים'.

שנה שם – הקש כדי לעורר את שם התמונה הנבחרת.

סובב שמאליה/ימינה – כדי לסובב שמאליה או ימינה.

חתור – חתור את התמונה. העבר את אצבעו לרווח המסך כדי לבחור את האזור המועד לחיתוך.

ערוך – הציג וערוך את התמונה.

הציג שkopיות – מראה לך את התמונות בתיקייה הנוכחיות בזו אחר זו באופן אוטומטי.

הוספה מיקום – כדי להוסיף את מידע המיקום.


פרטים – קיבל מידע נוסף אודות הקובץ.

מתוך הгалריה

הקש על  גלריה ובחר באפשרות **מצלמה**.

- להציג תמונות נוספות, כולל ימינה או שמאליה.
- כדי להגדיל או להקטין את המרחק מההתצוגה, הקש פעמיים על המסך או מ呷 שתי אצבעות והפרד אותן (קרב את האצבעות כדי להגדיל את המרחק מההתצוגה).

הCRT התצוגה המקדימה



- ❶ הבדיקה – בחר מבין האפשרויות כבוי ③, מופעל ⚡, אוטומטי ⚡.
- ❷ החלף מצלמה – למעבר בין המצלמה האחראית לבין המצלמה הקדמית.
- ❸ מצב הקלטה – בחר מבין האפשרויות רגיל, אפקט חי, הקלטה כפולה, או זום מעקב.
- ❹ הגדרות – הקש על סמל זה כדי לפתוח את תפריט ההגדרות.
- ❺ מצב מצלמה – הקש והחלק סמל זה כלפי מעלה כדי לעבור במצב מצלמה.
- ❻ התחול הקלטה
- ❼ גליה – הקש כדי להציג את סרטון הוידאו האחרון שהקלטה. כך ניתן להיכנו לגלריה ולצפות בסרטוני הוידאו השמורים כשאתה נמצא במצב וידאו.

עצה!

כשהתא מקליט וידאו, הצב שתי אצבעות על המסך וצבות כדי להשתמש בפונקציית שינוי גודל התצוגה.

שימוש בהגדרות המתקדמות

ב>Showcase המקדימה, הקש על כדי לפתוח את כל האפשרויות המתקדמות.

הקש כדי להפעיל את התוכנה 'זום שמע'. תוכל להקליט אך ורק את הצליל הרצוי בצורה ברורה וחזקת. לאחר הפעלת תוכנה זו, מתקד את הנושא שברצונך לבצע עבורה זום, בתוך העיגול הכחול. כדי לבצע זום הן על ציללים והן על מראה, צבוט כלפי פנים.



הערות

- זמן ב>Showcase לרוחב בלבד.
- אל תכסה את המיקרופונים בשני הצדדים.



הקש כדי להציג את הגודל (בפיוקלים) של סרטון הוידאו שאתה מקליט.



מגדר וקובע את כמות אור השימוש הנכונות לעדשה. החלק את מחוון הבניהות לאורך הפס, לכיוון הסימן "-" להפחית בהירות הוידאו או לכיוון "+" להגברת בהירות הוידאו.



משפר את איכות הצלב בתנאי תאורה שונים.



בחר גוון צבע לשימוש ב>Showcase החדשה.



הפעל כדי להשתמש בשירותים מבוססי-המיקום של הטלפון.



הגדר את מקש עצמת הקול כדי לבחור אם להשתמש בהקלטה או בהגדלה.



פותח את מדריך העזרה כדי לדעת כיצד פועלת פונקציה.



משחזר את כל הגדרות ברירת המחדל של המצלמה.

הקלטת סרטון וידאו מהיר

- 1فتح את היישום מצלמה והחלק את הלחצן מצב וידאו.
- 2כעת תופיע התצוגה המקדימה של מצלמת הוויידאו על המסך.
- 3החזק את הטלפון וכוון את העדשה אל הנושא שברצונך לצלם בסרטון הוויידאו.
- 4הקש על פעם אחת כדי להתחיל בהקלטה.
- 5נקודה אדומה תופיע בפינה השמאלית העליונה של התצוגה המקדימה יחד עם קוצב זמן שיציג את אורך הסרטון.
- 6הקש על  במסך כדי להפסיק את ההקלטה.

עה!

-  – הקש כדי לצלם תמונה בעת הקלטת סרטון וידאו.
-  – הקש כדי להשנות בעת הקלטת סרטון וידאו.

לאחר הקלטת וידאו

In the viewfinder, tap the video thumbnail at the bottom of the screen .to view the last video you took

הקש כדי לשთף את התמונה שלך באמצעות הפונקציה SmartShare .	
הקש כדי להקליט עוד סרטון וידאו מייד.	
הקש כדי לשלוח את התמונה לאחרים או לשתף אותה בשירותי רשות חברותיות.	
הקש כדי למחוק את הוויידאו.	

הערה: אם אתה מוריד הודעות MMS תוקן כדי נדייה, יתכן שיחולו חיבורים נוספים.

מtower הגלריה

הקש על גלריה ובחר באפשרות **מצלמה**. הקש על סמל הפעלת הווידאו כדי להפעיל את הווידאו.

כונון העוצמה בעט צפיה בסרטוני וידאו

לכונן עוצמת הקול של סרטון וידאו בעט הפעלהו, השתמש במקשי עוצמת הקול בצד שמאל של הטלפון.

שימוש בזום שמע

ממוקד את הקלטת השמע באזור מסוים לפי בחירתך; זה יביא להגברת הרגשות של המיקרופון ויפחית רעש רקע.

- 1** פתח את היישום **מצלמה** ושנה למסך וידאו.
- 2** הקש על **זום שמע** ובחר באפשרות **מופעל**.
- 3** הקש על שטח ריק בתצוגה המקדימה כדי לסגור את החלון הקופץ 'הגדרה'.
- 4** החזק את הטלפון בצוואר אופקי והקש על כדי להתחיל בהקלטה.
- 5** התמקד בנושא שברצונך להגדיל בטור העיגול הכחול. לאחר מכן, צבוט כדי להגדיל, על מנת להפחית את רגישות הציליל ואת הרעש.
- 6** הקש על כדי לעצור את ההקלטה.

הערות

- אל תכסה את המיקרופונים הצדדים בעט השימוש בתוכונה זו.
- עליך להקליט בכוון לרוחב על מנת להשתמש בפונקציה זו.

שימוש במצב הקלטה כפולה

מאפשר לך להקליט סרטוני וידאו עם המצלמות הקדמיות והאחוריות בו-זמןית, במשולב בהקלטה אחת.

- 1 פתח את היישום **צלמה** ושנה למסך יידאו.
- 2 הקש על < **הקלטה כפולה**.
- 3 תיבת הקטנה של תצוגה מקדימה מופיעה במסך הראשי של התצוגה המקדימה. הגדר את הצלום.
- גורר את התצוגה המקדימה הקטנה כדי להעביר אותה למיקום שבו אתה מעוניין בה בתצלום.
- הקש והחזק את התצוגה המקדימה הקטנה כדי לשנות את גודלה, במקורה הצורך.
- הקש על התצוגה המקדימה הקטנה כדי להחליף את העדשה בין התצוגה הראשית והתצוגה המקדימה הקטנה.
- 4 הקש על כדי להפעיל הקלטה כפולה.
- 5 הקש על כדי לעזרה הקלטה כפולה.

שימוש בזום מעקב

מאפשר לך להגדיר אזור שבו תוכל להתמוך בהקלטה על מנת להגדיל אותו. אפשרותך להגדיר את האזור לפני הקלטה, ולאחר מכן להעביר אותו בהתאם לצורך במהלך הפעלה.

- 1 פתח את היישום **צלמה** ושנה למסך יידאו.
- 2 הקש על < **זום מעקב**.
- 3 גורר את הzdcochtit המגדלת לאזור שאתה מעוניין להגדיל. המסך הקטן מציג את המיקוד שהוגדר בתצוגה גדולה.
- 4 הקש על כדי להתחיל בהקלטה.
- בזמן הקלטה, אפשרותך להציג את המסך הקטן. גע בו וגורר אותו למיקום הרצוי.
- 5 הקש על כדי לעזרה את הקלטה.


QuickMemo

QuickMemo מאפשר לך ליצור תזכורות ולכלוך צילומי מסך. לכוד מסכים, צייר עליהם ושתף אותם עם בני משפחה וחברים באמצעות הקול.


- 1 (בזמן שהמסך כבוי) הקש והחזק את מיקש הגברת עוצמת הקול.

או


גע והחלק את שורת המצב כלפי מטה והקש על .




או



- 2 בחר באפשרות התפריט הרצiosa מבין סוג עט, צבע, מחק וצור תזכיר.



3 הקש על  בתפריט 'ערוך' כדי לשמר את התזכורת עם המסר הנוכחי. כדי לצאת מ-QuickMemo בכל עת, הקש על .



הערה: השתמש בקצת האצבע בזמן השימוש ב-QuickMemo. אל תשתמש בzip/oracle.

שימוש באפשרויות QuickMemo

ניתן להשתמש בקלות באפשרויות נענבות QuickMenu בעת שימוש ב-QuickMemo.

הקש כדי להשאיר את QuickMemo הנוכחי כשכבה-על של טקסט במסך, ומהר לשימוש בטלפון.



בחירה אם להשתמש במסך הרקע או לא.



בטל או בצע שוב.



בחירה את סוג העט ואת הצבע.



מוחק את התזכורת שיצרה.



הקש כדי לשחרר את התזכורת עם אחרים דרך כל אחד מהפתרונות הבאים.



ישומים.

שומר את התזכורת עם המסר הנוכחי בגלריה או במחברת.




הציג ה-QuickMemo שנשמר.
הקש על **מחברת/галריה** ובחירה באלבום QuickMemo.

QuickTranslator

פשוט כoon את המצלמה של הטלפון החכם שלך אל משפט בשפה זרה שברצונך להבini. אפשרותך לקבל תרגום בזמן אמת בכל מקום ובכל זמן. ניתן לרכוש מילוניים נוספים לתרגום לא מקוון מ-Google Play Store.

- ❶ שפת הבית.
- ❷ שפת היעד.
- ❸ תרגום של מילה.
- ❹ תרגום של משפט.
- ❺ תרגום של קטע.
- ❻ מבזק.



- ❶ הקש על > הcranטייסיה **ישומים** <
- ❷ הקש על האפשרויות **מילה**, **שרה** או **קטע**.
- ❸ הקש ובחר את השפה הרצויה.
- ❹ החזק את הטלפון לכיוון הנושא שברצונך לתרגם למשר שניות אחדות.

הערה: רק מילון אחד ניתן ללא תשלום. אם אתה מעוניין במלוניים נוספים עליך לרכוש אותם. בחר מתוך הרשימה שהלן את המילון שברצונך להתקין ללא תשלום.

הערה: עשוי להיות הבדל בקצב הדיזיין בהתאם לגודל, לגוף, לצבע, להירות ולזווית האותיות שיש לתרגם.

QSlide

מכל מסך שהוא, העלה פנקס רשימות, לוח שנה ועוד כחלון בתוך המסך.

הקש כדי לצאת מ-QSlide
ולחזרו לחילון מלא.



1

הקש כדי לכוון את השקיפות.
הקש כדי לנתק את QSlide.



2


הקש כדי להתאים את הגודל.



3



4



1 גע ווחילק את שורת המציג כלפי מטה > הקש על יישומי QSlide או במהלן שימוש ביישומים התומכים ב-QSlide, הקש על . הפענקציה תוצג באופן רציף כחלון קטן על המסך.


2 באפשרותך לבצע שיחה, לאLOS באינטרנט או לבחור אפשרויות אחרות בטלפון. באפשרותך גם להשתמש ולהקיש על המסך תחת החלונות הקטנים כסדרgal השקיפות אינם מלא.

הערה: QSlide יכול לתמוך בשני חלונות לכל היוטר בו-זמןית.

QuickRemote

הופך את הטלפון לשולט רחוק אוניברסלי עבור הטלוויזיה הביתית, הממיר, מערכת השמע, נגן DVD/Blu-ray, מיזוג האודיו והמקון.

1 גע בשורת המצב ו לחלק אותה מטה ו הקש על < הוסף שולט רחוק.



אנו
הקש על < < הרכטים<
ישומים < QuickRemote <
הקש על .

2 בחר את הסוג ומותג התקן, ולאחר מכן פועל בהתאם להוראות המופיעות במסך כדי להגדיר את תצורת התקנים.



3 גע בשורת המצב ו לחלק אותה מטה, והשתמש בפונקציות QuickRemote.



הקש על כדי לבחור מבין האפשרויות הגדרת Magic Remote, ערוך שם מרוחק, למד מושך שלט, העבר שלט, מחק שלט מרוחק, ערכת חדר, הגדרות ועוד.

הערה: QuickRemote פועל באופן זהה לאוטות אינפרא-אדום (IR) רגילים בשלט רחוק. הקפד לא לכוסות את חישון האינפרא-אדום בחולק העליון של הטלפון כאשר אתה משתמש בפונקציה זו. יתכן שלא תהיה תמייה בפונקציה זו - הדבר תליי בדגם, ביצור או בחברה המפעילה את השירות.

מייקוד אל רצעה

כאשר אתה מפעיל וידאו, אפשרותך להגדיל אובייקט בזמן שאתה עוקב אחריו.

- 1 כאשר אתה מפעיל וידאו, הקש על 
- 2agu בזcocית המגדלת וגורור אותה אל האובייקט שברצונך לעקב אחריו.



הערה:

- בזמן שפועלו וידאו, החלק את המסר מעלה או מטה כדי ליצור את בהירות המסר.
- בעת הפעלתו וידאו, החלק את המסר שמאליה או ימינה כדי להריץ אחרת או להריץ קידמה.
- אל תלחץ חזק מדי, מסך המגע רגיש די כדי לחש בהקשה קלה אך החלטית.
- יתכן שהתוכנה 'מייקוד לצורך מעקב' לא תהיה זמינים אם האובייקט נע מהר מדי או שהוא יוצא מהמסך.

VuTalk

בעזרת התוכנה VuTalk, המשתמש יכול ליצור הערות אינטראקטיביות ויתר יצירתיות עם הצד השני. תקשורת חזותית היא אפשרית בעת שיתוף צלום, מפה או תצוגה מקדימה של מצלמה.

הערה:

- זמן ארך ורק עם טלפון התומך גם בתוכנה זו.
- ניתן להשתמש בתוכנה VuTalk גם במהלךשיחת וידאו.
- המסר ינעל אם אין קלט.
- מחיב חיבור נתונים. חיבור נתונים עשוי לחול על שני הטלפונים.

הרשמה ל-VuTalk לפני השימוש

1    **אנשי קשר >**

באפשרותך גם להירשם לשירות VuTalk בזמן שאתה בשיחה.

2 קרא את תנאי השימוש ואת מדיניות הפרטויות של LG. אם אתה מסכים, הקש על תיבות הסימון ולאחר מכן הקש על **קביל**.

הגדרות VuTalk

- 1 הקש על ->  **אנשי קשר** <  **הגדרות VuTalk**.
- 2 הגדר את האפשרויות הבאות כהעדפותיך.
- 3 **צליל התראה:** בחר בצליל התראה הרצוי.
- 4 **רטט:** בחר בסוג הרטט הרצוי.
- 5 **הציג בקשה מוקפצת:** סמן אפשרות זו בסימן ביקורת כדי להציג חלון מוקפץ כאשר מתאפשרת בקשה VuTalk.
- 6 **סינכרון ANSI קשר:** סמן אפשרות זו בסימן ביקורת כדי לסונכרן ANSI קשר.

קיים תקשורת חזותית עם VuTalk

- 1 הקש על ->  **אנשי קשר** <  רק ANSI קשר המשתמשים בתוכנה VuTalk יוצג.
- 2 הקש על איש קשר כדי להתחיל עמו ב-VuTalk.
- 3 במסך הפורטים של איש הקשר, הקש על  . לאחר שהצד השני מקבל את בקשתך ל-VuTalk, תוכל להתחיל ב-VuTalk אליו/איתה.
- 4 השתמש במסך VuTalk כדי לשוחח ולקיים תקשורת חזותית עם חברך.
- 5 הקש על  כדי לצרף צלום, לצלם צלום חדש, תציגו מפה או מדבקה.
- 6 הקש על סמל העט  ועל סמל המחק  כדי לכתוב על התמונות שצירפת.
- 7 עם סיום השימוש ב-VuTalk, הקש על  כדי לצאת מהתוכנה VuTalk.
- 8 מסך VuTalk שנוצר מאוחסן ביישום לחברת.

הערה: אם המשתמש מקיש על  וחוזר למסך הבית, התוכנה VuTalk עדין תפעל ברקע.

Voice Mate

Voice Mate מאפשר לך להשתמש בתפקידים באמצעות דיבורית. תוכל לבקש Voice Mate לבצע פונקציות טלפוןיות באמצעות קולך, כגון חיבור לאיש קשר מהדרת התראות או חיפוש באינטרנט. כאשר משתמש ניגש לתוכנה זו בפעם הראשונה, היא מציגה מידע עזרה כדי לסייע לך ללמוד כיצד להשתמש בפונקציה זו.

הערה:

- תוכל להשתמש ב-Voice Mate לאחר שתקבל את התנאים של הסכם הרישוי למשתמש קצה ואת מדיניות הפרטיות.
- ניתן להציג דוגמאות של פקודות שונות על-ידי החלקת המסך הראשי של Voice Mate שמאליה.
- ניתן גם להפעיל את Voice Mate באמצעות התוכנה 'גישה מהירה'.

שימוש ב-Voice Mate

1 הקש על < Voice Mate .

2 הקש על כדי להפעיל אותו. אמרור מה ברצונך שהוא יבצע עבורך.

ឧחה! השימוש ב-Voice Mate בסביבה שקטה, כך שהוא יוכל לזהות במדויק את הפקודות שלך.

הגדרות Voice Mate

1 הקש על < < Voice Mate .

2 הקש על < הגדרות כדי לקבוע את תצורת הגדרות הסביבה.

LG SmartWorld

LG SmartWorld מציע מגוון של סוגי תוכן מרתוקים - משחקים, יישומים, טפסים וצלולים - ומעניק למשתמשי הטלפונים של LG הזדמנות ליהנות מחווית טלפון נייד עשויה יותר.

גישה ל-LG SmartWorld מהטלפון

- 1 הקש על < הכרטיסיה יישומים > הקש על סמל כדי לגשת אל **LG SmartWorld**.
- 2 הקש על 'כניסה למערכת' והזן שם משתמש וסיסמה ל-LG SmartWorld. אם עדין לא נרשם, הקש על 'הירשם' כדי לקבל חברות ב-**LG SmartWorld**.
- 3 הורד את התוכן הרצוי.

עזרה: מה לעשות אם אין סמל ?

- 1 באמצעות דפדפן אינטרנט של מכשיר נייד, גש ל-**LG SmartWorld** (www.lgworld.com) ובחר את מדינתר.
- 2 הורד את "שם" (www.lgworld.com).
- 3 הפעיל והתקן את הקובץ שהורדת.
- 4 גש אל **LG SmartWorld** על-ידי הקשה על הסמל .

אופן השימוש ב-LG SmartWorld

- . השתתף במכעים החדשניים של **LG SmartWorld**.

חפש תוכן.	
חפש תוכן לפי קטgorיה (למשל משחקים, חינוך, בידור וכן הלאה).	
רשימת תוכן שהורדת/מיועד לעדכו.	

- נסה את לחצני ה"פריט" הנוחים כדי למצוא במהירות את הפריט המבוקש.
- **ישומים עבורי** – פריטי תוכן מומלצים על בסיס הבחירה הקודמות שלך.
- **הגדירות** – הגדרת פרופיל ותצוגה.
- **כניסה למערכת** – הגדרת שם משתמש וסיסמה.
- נסה פונקציות שימושיות נוספות. (מסמך 'פריטי תוכן')

הערה: יתכן ש-Id-P LG SmartWorld לא יהיה זמין בכל המדינות ואצל כל המפעילים.

On-Screen Phone

On-Screen Phone מאפשר לך להציג את מסך הטלפון הנייד שלך מחשב דרך חיבור USB או חיבור Wi-Fi. ניתן לשלוט בטלפון הנייד גם מהמחשב, באמצעות עכבר או מקלדת.

סמלים טלפון במסך המחשב

לחיבור הטלפון הנייד למחשב וניתוקו.	
שנה את העדפות הטלפון במסך המחשב.	
lez'iaah matocnit 'telefon b'mascer ha'machshab.	
הגדלה מרבית של חלון הטלפון במסך המחשב.	
מצער של חלון הטלפון במסך המחשב.	

תוכנות הטלפון במכשיר המחשב

- העברה ושליטה בזמן אמיתי: הציגה של מסך הטלפון הנייד ושליטה עליו בעת החיבור למכשיר.
- שליטה בעבר: אפשרות לשלוט בטלפון הנייד על-ידי לחיצה וגרירה באמצעות העבר במכשיר המחשב.
- הציגת טקסט באמצעות מקלדת: אפשרות לחבר הודעה טקסט או הערה באמצעות מקלדת המחשב.
- העברת קבצים (טלפון נייד למכשיר): שליחת קבצים מהטלפון הנייד (לדוגמה, תמונות, סרטיוני וידאו, מוסיקה וקובץ Polaris Office) למכשיר. לחץ באמצעות לחץ העבר הימני על הקובץ שברצונך לשולח למכשיר ולהזע על 'שמור במכשיר'.
- העברת קבצים (מהמכשיר לטלפון הנייד): שליחת קבצים מהמכשיר לטלפון הנייד. בחר את הקבצים שברצונך להעביר כדי לגזרו אותן אל חלון 'טלפון במכשיר המחשב' ולשחררם שם. הקבצים שנשלחו מאוחסנים בכרטיס SD פנימי.
- התראות אירופים בזמן אמיתי: מופיע חלון מוקף הכלול הודעה על שייחות כניסה או על הודעות טקסט/ מולטימדיה.

כיצד להתקין On-Screen Phone במכשיר

- 1 בקר באתר LG Home (WWW.LG-MOBILE.CO.IL) ובחר מדינה.
- 2 עבור אל **תמיכה > תמיכה בטלפון נייד** < בחר את הדגם (LG-D802) < לחץ על **OSP** (On-Screen Phone) להורדה. ניתן להתקין את יישום 'טלפון במכשיר האיש' (On-Screen Phone) במכשיר האיש.

галריה

פתח את היישום גלריה כדי להציג אלבומים של התמונות וסרטוני הוידאו שלך.

- 1 הקש על > הכרטיסיה "ישומים" > גלריה.
אפשרותך לנתח ולשתף את כל קובצי התמונות וסרטוני הוידאו שלך באמצעות הגלריה.

הערה:

- תבניות קבועים מסוימות אין נטרכות, בהתאם לתוכנה המותקנת במכשיר.
- יתכן שקבצים מסוימים לא יופעלו באופן תקין, בהתאם לקיוד שלהם.

הציג תמונות

הפעלת הגלריה מציגה את התקיות הזמיןות שלך. כשי>Show אחר, כגון דוא"ל, שומר תמונה, תיקייה הורדנה נוצרת באופן אוטומטי כדי להכיל את התמונה. בדומה לכך, לכידת צילום מסך יוצרת באופן אוטומטי את תיקיית צילומי המסך. בחר תיקייה כדי לפתח אותה.

התמונות מוצגות בתיקייה לפי תאריך יצירה. בחר תמונה כדי להציג אותה במסך מלא. כולל שמאליה או ימינה כדי להציג את התמונה הבאה או הקודמת.

הגדלה או הקטנה של התצוגה

השתמש באחת השיטות הבאות כדי להגדיל/הקטין תמונה:

- הקש פעמיים בנקודה כלשהי כדי להגדיל את התצוגה.
 - הzz שטי' אצבעות בתנועת פריסה בנקודה כלשהי כדי להגדיל את התצוגה.
- צבות כדי להקטין את התצוגה, או הקש פעמיים כדי לחזור.

הפעלת סרטוני וידאו

בקובי וידאו מופיע סמל בתצוגה המקדימה. בחר סרטון וידאו כדי לצפות בו והקש על . "ישום סרטוני הוידאו יופעל.

עריכת תמונות

בעת הצגת צלום, הקש על **מסך התפריט** > **ערום**.

מחיקת תמונות/סרטוני וידאו

השתמש באחת השיטות הבאות:

- בຕיקיה, הקש על ובחר תמונות/סרטוני וידאו על-ידי סימון, ולאחר מכן הקש **על מחק**.
- כשהת צופה בתמונה/וידאו, הקש על .

הגדרה בטפט

בעת הצגת צלום, הקש על **מסך התפריט** > **הגדר תמונה בהתאם** כדי להגדיר את התמונה בהתאם לאותה לאיש קשר.

הערה:

- חולק מתבניות הקבצים אין נטמכות, בהתאם לתוכנת המחשב.
- אם גודל הקובץ חורג מכמות הדיכאון הפנו, עלולה להתרחש שגיאה בעת פתיחת קבצים.

סרטוני וידאו

טלפון שלך כולל נגן וידאו מובנה שמאפשר לך להציג את כל סרטוני הוידאו המoadפים שלך. כדי לגשת לנגן הוידאו, הקש על > **הכרטיסייה ישומים** > **סרטוני וידאו**.

הפעלת קובץ וידאו

- 1** הקש על > הכרטיסייה "ישומים" > סרטוני וידאו.
- 2** בחר בסרטון הוידאו שברצונך להפעיל.

	הקש על הכיוון הרצוי עבור זום שמע.
	הקש כדי להשתמש בתוכנה 'מיקוד לצורך מעקב'.
	הקש כדי להיכנס למסך Qslide.
	הקש כדי לשתף את התמונה שלך באמצעות הפונקציה SmartShare.
	הקש כדי לנעל מסך וידאו.
	הקש כדי להציג את רשיימת הוידאו.
	הקש כדי להשוו את הפעלת הוידאו.
	הקש כדי לחדש את הפעלת הוידאו.
	הקש כדי לעبور 10 שניות קידמה.
	הקש כדי לעبور 10 שניות אחורה.
	הקש כדי לנהל את עוצמת הקול של הוידאו.
	הקש כדי לשנות את יחס הגובה-רוחב של מסך הוידאו.

כדי לשנות את עוצמת הקול במהלך צפייה בוידאו, הקש על מקשי הגברת/הנמכת עוצמת הקול שבגב הטלפון.
גע נגעה ממושכת באחד הסרטונים בראשימה. יוצגו אפשרויות **שיתוף, מחיקה, חיתוך ופרטים**.

עורר הווידיאו

באפשרותך לעורר את התמונות ואת סרטוני הווידאו המאוחסנים בטלפון.

◀ הקש על > הניווטית יישומים > עורך וידאו.

הערה: פונקציית ערכת הוידאו נתמכת רק עבור תמונות או סרטוני וידאו שהוקלטו בטלפון זה.

< מסך רשימת פרויקטים >



צור פרויקט חדש.



שתף את פרויקט הוידאו עם יישומים אחרים, כגון YouTube.



יצא את הפרויקט שהסתיים כדי להפעיל אותו ביישומים אחרים.




מחק את פרויקט הוידאו.



הציג מידע העזרה.



< מסך ערך פרויקטים >



הקש כדי להציג את מסך רישימת הפרויקטים.



הקש כדי להפעיל את הקליפ הנוכחי.



הקש כדי להסיר את הקליפ האחרון שנבחר.



הקש כדי להוסיף קליפים נוספים של וידאו.



הקש כדי לבחור סגנון וידאו.



הקש כדי לבחור סגנון וידאו.



הקש כדי לבחור סגנון וידאו.

**מוסיקה**

הטלפון שלך כולל נגן מוסיקה מבנה שמאפשר לך להשמיע את כל הרצונות המועדףת שלו. כדי לגשת לנגן המוסיקה, הקש על > הCarthyיסיה **ישומים > מוסיקה**.

הוסף קובצי מוסיקה לטלפון

התחל על-ידי העברת קובצי מוסיקה לטלפון:

- העבר מוסיקה באמצעות סנכרון מדיה (MTP).

- הורד מה인터넷 אל חוטי.
- סyncrn את הטלפון עם מחשב.
- קבל קבצים באמצעות Bluetooth.

העבר מוסיקה באמצעות סyncrn מדיה (MTP)

- 1 חבר את הטלפון למחשב באמצעות כבל-USB.
- 2 בחר באפשרות סyncrn מדיה (MTP). הטלפון שלך יופיע ככונן קשיח נוסף במחשב. לחץ על הכונן כדי להציג אותו. העתק את הקבצים מהמחשב לתיקיית הכונן.
- 3 לאחר שתסǐים להעביר קבצים, החלק מטה את שורת המצב והקש על האפשרות USB מחובר < טען את מס' הטלפון. CUT תוכל לנתק את ההתקן בבטחה.

השמעת שיר

- 1 Tap  > Apps tab > Music.
- 2 הקש על שירים.
- 3 בחר בשיר שברצונך להשמע.

הקש כדי להשווות את הפעלה.	
הקש כדי לחדש את הפעלה.	
הקש כדי לדלג לרצועה הבאה באלבום, בראשימת השמעה או בהשמעה אקראית. הקש וווחזק כדי להריץ קידימה.	
הקש כדי להפעיל מחדש את הרצועה הנוכחית או לדלג אל הרצועה הקודמת באלבום, בראשימת השמעה או בהשמעה אקראית. הקש וווחזק כדי להריץ אחורה.	
הקש כדי להציג את פס המחוון של עוצמת הקול, ולאחר מכן התאם את עוצמת הקול של השמעה בפס המחוון.	

הקש כדי להציג אפקטים קוליים.	
הקש כדי למצוא את הקבצים ב-YouTube.	
הקש כדי לפתח את רשימת השמעה הנוכחיית.	
הקש כדי להוסיף שיר למועדפים שלך.	
הקש כדי להפעיל את רשימת השמעה הנוכחיית במצב אקריאי (הרצאות מופולות בסדר אקריאי).	
הקש כדי להחליפ בין מצב הזרה 'חזר על כל השירים', 'חזר על השיר הנוכחי', או 'הזרה מושבתת'.	
הקש כדי לשთף את המוסיקה שלך באמצעות הפונקציה SmartShare.	

כדי לשנות את עצמת השמע בעת האזנה למוסיקה, לחץ על לחצני ההגברה או הנמוכה של עצמת הקול שבגב הטלפון. גע ברציפות בשיר כלשהו ברשימה. יוצגו האפשרויות הפעל, הוסף לרשימת השמעה, שטף, הגדר מודיקה כ-, מחק, פרטים וחפש.

הערה:

- חלק מתכניות הקבצים אינם נתמכות, בהתאם לתוכנת המחשב.
- אם גודל הקובץ חורג מכמויות הזיכרון הפנוי, עלולה להתרחש שגיאה בעת פתיחת קבצים.

הערה: זכויות היוצרים של קובצי מוסיקה עשוות להיות מגנות על ידי אמנה בינלאומיות וחוקי זכויות יוצרים לאומיים.

לפיכך יתכן שתצטרכ להציג אישור או רישיון כדי לשכפל או להעתיק מוסיקה. במדינות מסוימות, החוק המקומי אסור על העתקה פרטית של חומרם המוגנים בזכויות יוצרים. לפני הורדת או העתקה של הקובץ, בדוק את החוקים הלאומיים של המדינה הרלוונטיים ביחס לשימוש בחומרים מסוג זה.

גלאש הצידה (החלפת משימות מהירה עם שלוש אצבעות)

תוכל להחליף במהירות למשימה אחרת באמצעות שלוש אצבעות.

- 1** מקום שלוש אצבעות על המסר שאתהעובד בו כעת והחלק את המסר שמאלה. המסר הנוכחי נשמר והוא יכול לבצע משימה אחרת.
- באפשרותך לשמור עד 3 (שלושה) יישומים בצד השמאלי של המסר.
- 2** כדי לפתח מחדש את המסר שנשמר ולהמשיך להשתמש ביחסים, הנהן שלוש אצבעות על מסך כלשהו והחלק אותו ימינה.

הערה: היזהר שלא להנגן עוד אצבעות או כף יד על המסר.

מצב אורך

כדי להגן על פרטיויך או להגביל גישת ילדים ליישומים מסוימים, תוכל להשתמש ב'מצב אורך'.

כאשר אתה משתמש בתלפון אחרים, תוכל להגביל את היישומים שייצגו. הגדר מראש את 'מצב אורך' והתאם אישית את האפשרויות.

הערה: כדי להשתמש ב'מצב אורך', יש להגדיר מראש את תבנית הנעילה.

- 1** הקש על < הגדרות > ה Karttisya ישומים כליי > מצב אורך.
- 2** הקש על 'השתמש במצב אורך' כדי להוסיף סימן ביקורת.

הגדרת התראתא

1 הקש על < ה Karttisya ישומים < התראתא/שעון < .

2 לאחר הגדרת התראתא, הטלפון שלך יודיע לך כמה זמן נותר עד להשמעת התראתא.

3 הגדר חזקה, משך זמן נסדקיק, רטט, צליל התראתא, עוצמת הקול של התראתא, הפעלת יישום אוטומטי, נעילת פאלז ותזכורת. הקש על שמור.

הערה: כדי לשנות את הגדרות ההתראה במסך רשייתן התאראות, הקש על מקש התפריט ובחירה באפשרות הגדרות.

שימוש במחשבון

- 1 הקש על > הCarthyסיה "ישומים" > מחשבון.
- 2 הקש על מקשי הספרות כדי להזין מספרים.
- 3 לビיעו חישובים פשוטים, הקש על הפונקציה שברצונך לבצע (+, -, × או ÷), ולאחר מכן =.
- 4 עברו חישובים מורכבים יותר, החלק לשמאלי ולאחר מכן בחר באפשרויות חוס, cos, tan, log וכן הלאה.
- 5 כדי לעין בהיסטוריה, הקש על הסמל .

הוסףת אירוע ללוח השנה

- 1 הקש על > הCarthyסיה "ישומים" > לוח שנה.
- 2 במסך, תוכל למצוא את סוג הציגות השונים של לוח השנה ([Day](#), [Week](#), [Month](#), שנה, לוח זמנים, כיכר החימאים).
- 3 הקש על התאריך שבו ברצונך להוסיף אירוע והקש על .
- 4 הקש על האפשרות שם אירוע והזן את שם האירוע.
- 5 הקש על האפשרות מיקום והזן את המיקום. סמן את התאריך והזן את שעת ההתחלה והסיום של האירוע.
- 6 אם ברצונך להוסיף הערה לאירוע, הקש על האפשרות קישור הערה כדי לבחור בתמונה המחברת שנשמרה. (זמן רק בלוח השנה של הטלפון)
- 7 אם ברצונך לחזור על התראה, הגדר **חזרה** והגדר **תזכורות** במקרה הצורך.
- 8 הקש על שומר כדי לשמר את האירוע בלוח השנה.

רשמקול

השתמש ברשמקול כדי להקליט תזכורות קוליות או קובצי שמע אחרים.

הקלטה צליים או קול

- 1 הקש על  > הCarthyסיה יישומים > **הקלטה קולית**.
- 2 הקש על  כדי להתחילה בהקלטה.
- 3 הקש על  כדי לסיים את ההקלטה.
- 4 הקש על  כדי להאזין להקלטה שערכת.

הערה: הקש על  כדי לגשת לאלבום. תוכל להאזין להקלטה שנשמרה. זמן ההקלטה הזמן עשוי להיות שונה מזמן ההקלטה בפועל.

שליחת ההקלטה הקולית

- 1 לאחר סיוםת את ההקלטה, תוכל לשЛОוח את קלייפ השמע על-ידי הקש על .
- 2 בחר מבין האפשרויות **Bluetooth**, **דוור אלקטרוני**, **Gmail**, **זיכרון**, **הודעות או SmartShare Beam**. כשתבחר באפשרויות **SmartShare Beam**, **דוור אלקטרוני**, **Gmail**, **זיכרון**, **הודעות** תצופר להודעה. לאחר מכן תוכל ל כתוב ולשלוח את ההודעה כרגע.

מנהל המשימות

באפשרותך לנגן את היישומים שלך באמצעות מנהל המשימות. ניתן לבדוק בקהלות את מספר היישומים הפעילים בעת ולסגור יישומים מסוימים.

ניתן לסנן מ ShiMaHa זו מול חשבון MS Exchange. ניתן ליצור ShiMaHa, לעורו
אותה ואף למחוק אותה ב-MS Outlook Web או ב-MS Office Outlook Access.

כדי לסנן מול MS Exchange

- 1 במסך הראשי, הקש על הגדרות.
- 2 הקש על הניווטית כללי חשבונות וסנכרון הוסף חשבון.
- 3 הקש על Microsoft Exchange כדי ליצור כתובת דוא"ל וסיסמה.
- 4 הקפד לסמן את המשימה 'סנכרון'.

הערה: יתכן שלא תהיה תמייה ב-MS Exchange, בהתאם לשרת הדואר האלקטרוני.

POLARIS Viewer 5

Polaris Office הוא פתרון מקצועי למשרד הניד, שמאפשר למשתמשים להציג
בוחות סוגים שונים של מסמכים משרדיים, כולל קובצי Word, Excel,
PowerPoint, בכל מקום ובכל זמן, באמצעות המכשירים הנידים שלהם.
הקש על הניווטית יישומיים POLARIS Viewer 5

הציג קבצים
כעת יכולים משתמש נידים להציג מגוון רחב של סוגי קבצים, לרבות מסמכים
Microsoft Office-Adobe PDF-PDF, יישירות במכשיר הניד. בעת ההציגה של
מסמכים בעזרת Polaris Office 4, האובייקטים והפריסה נותרים כפי שהיו
במסמכים המקוריים.

Google+

השתמש בישום זה כדי לשמר על קשר עם אנשים באמצעות שירות הרשות החברתית של Google.

- **הקש על  > הכרטיסיה "ישומים" > **.

הערה: יתכן שישום זה לא יהיה זמין, בהתאם לאזרור או לספק השירות.

חיפוש קולי

השתמש בישום זה כדי לחפש דפי אינטרנט באמצעות קולך.

- 1 **הקש על  > הכרטיסיה "ישומים" >  חיפוש קולי.**

2 אמרור מילת מפתח או צירוף מילים כשהאPhraseות דבר עכשו מופיעה על המסר.
בחר את מילות המפתח המוצעות שיופיעו.

הערה: יתכן שישום זה לא יהיה זמין, בהתאם לאזרור או לספק השירות.

הורדות

השתמש בישום זה כדי לראות אילו קבצים הורדו בישומים.

- **הקש על  > הכרטיסיה "ישומים" >  הורדות.**

הערה: יתכן שישום זה לא יהיה זמין, בהתאם לאזרור או לספק השירות.

אינטרנט

השתמש בຍישום זה כדי לגלוש באינטרנט. הדף מעניק לך עולם מהיר וצבעוני של משחקים, מוסיקה, חדשות, ספורט, בידור והרבה יותר, היישר לטלפון הנייד שלך, בכל מקום ובעור כל תחומי העניין שלך.

הערה: יהולו חיבורים נוספים בעט התחרבות לשירותים אלה והודת תוכן. בדקו את טריפי העברת הנתונים אצל ספק הרשת שלכם.

1 **הקש על  > הכרטייסיה  יישומים >  אינטרנט.**

שימוש בסרגל הכלים של האינטרנט

הקש והחלק אותו כלפי מעלה בעזרת האצבע כדי לפתח.

הקש כדי לחזור דף אחד אחורה. 
הקש כדי להתקדם דף אחד קדימה, לדף שאלוי התחרבות אחרי הדף הנוכחי. זוהי הפעולה הפוכה לעומת הקשה על  , שמחזירה אותך לדף הקודם. 
הקש כדי לעבור לדף הבית. 
הקש כדי להוסיף חלון חדש. 
הקש כדי לגשת לסימניות. 

הציג דפי אינטרנט

הקש על שדה הכתובת, הzin את כתובת האינטרנט והקש על עبور.

פתיחת דף

כדי לעבור אל דף חדש, הקש על  >  .
כדי לעבור לדף אינטרנט אחר, הקש על  , גולול מעלה או מטה והקש על הדף
כדי לבחור אותו.

חיפוש באינטרנט באופן קווי

הקש על שדה הכתובת, הקש על  , אמרו מילת מפתח ולאחר מכן בחר אחת
ממלואות המפתח המוצעות שיופיעו.

הערה: יתכן שתכונה זו לא תהיה זמינה, בהתאם לאזרור או לספק השירות.

סימניות

כדי לסמן את דף האינטרנט הנוכחי בסימנייה, הקש על  > **הוסף לסימניות >**
אישור.

כדי לפתח דף אינטרנט שסומן בסימנייה, הקש על  ובחירה אחת הסימניות.

ההיסטוריה

הקש על  > **היסטוריה** כדי לפתח דף אינטרנט מתוך רשימת דפי האינטרנט
שבהם ביקרת לאחרונה. כדי לנוקוט את ההיסטוריה, הקש על **מקס התפריט**  >
מחיקת כל ההיסטוריה.

שימוש בדף מוקף

השתמש בתכונה זו כדי לגשת לאינטרנט מבלי' לסגור את היישום הנוכחי.
זמן שאתה צופה בתוכן, כגון קשר או פתקים המכילים כתובות אינטרנט,
בחר כתובת אינטרנט ולאחר מכן הקש על **'דף מוקף'** כדי לפתח את הדף
המוקף. גע וגורר את הדף במסך מלא, הקש על  .

כדי לסגור את הדף, הקש על  .

Chrome

השתמש ב-**Chrome** כדי לחפש מידע ולגלוש בדף אינטרנט.

1 הקש על  > הכרטיסיה "ישומים" > **Chrome**.

הערה: יתכן שישום זה לא יהיה זמין, בהתאם לאזרע ולספק השירות.

הציגת דפי אינטרנט

הקש על שדה הכתובת ולאחר מכן הزن כתובת אינטרנט או קרייטריון חיפוש.

פתיחת דף

כדי לעبور לדף חדש, הקש על  > **+ כרטיסיה חדשה**.

כדי לעبور לדף אינטרנט אחר, הקש על , גלול מעלה או מטה והקש על הדף כדי לבחור אותו.

סנכרון עם מכשירים אחרים

סנכרן כרטיסיות פרטיות וסימניות כדי להשתמש בהן ב-**Chrome** במכשיר אחר כשאתה מחובר עם אותו חשבון Google.

כדי להציג כרטיסיות פרטיות במכשירים אחרים, הקש על **מקש התפריט** <  **מכשירים אחרים**.

בחר דף אינטרנט כדי לפתחו אותו.

כדי להוסיף סימניות, הקש על .

סעיף זה מספק מבט כולל על פריטים שונים לשונות באמצעות תפריטי הגדרות המערכת של הטלפון.

כדי לגשת לתפריט 'הגדרות':

הקש על  >  הגדרות מערכת.

- לחולפן -

הקש על  >  הגדרות.

רשתות

< Wi-Fi >

Wi-Fi - מפעילה את Wi-Fi כדי להתחבר לרשתות Wi-Fi זמיןות.

עזה! כיצד להשיג את כתובת ה-MAC

כדי להציג חיבור ברשותות אלחוטיות מסוימות עם מסנני MAC, יתכן שתידרש להזין את כתובת ה-MAC של הטלפון שלך בנתב.

ניתן למצוא את כתובת ה-MAC במכשיר המשמש הבא: הקש על  >  הגדרות > הרטיסייה רשתות >  Wi-Fi > מתקדם > כתובת MAC.

< Bluetooth >

הפעל או כבה את התוכנה האלחוטית של Bluetooth כדי להשתמש ב-Bluetooth.

< נתוני סולריים >

להציג השימוש בנתונים והגדרת גבולות לשימוש בהעברת נתונים סולריים.

< שיחה >

קבע את התצורה של הגדרות שיחת טלפון, כגון הפניות שיחה, וכן תוכנות מיוחדות אחרות שספק השירות שלך מציע.

תא קולי – מאפשר לך לבחור את שירות התא הקולי של הספק שלך.

מספרי חיבור קבועים – הפעיל וצורך רשימה של מספרים שאלייהם ניתן להתקשר מהטלפון שלך. לצורך כך נדרש לקובד PIN שנitin להציגו אצל מפעיל השירות שלך. מטלפון שלך ניתן להתקשר רק למספרים הכלולים ברשימה מספרי החיבור הקבועים.

חלונית שיחה כניסה – הגז חולונית שיחה כניסה בעת שימוש במכשירו וידאו **דוחית שיחות** – מאפשר להגדיר את פונקציית דוחית שיחה. בחר בין **מצב דוחית שיחה או רשות דוחית**.

סרב עם הודעה – כשבuczן לדוחות שיחה, באפשרות לשולח הודעה מהירה באמצעות פונקציה זו. אפשרות זו שימושית כאשר אתה נדרש לדוחות שיחה במהלך פגישה.

שומר הפרטיות – מסתיר את השם ואת המספר של המתקשך עבור שיחה כניסה.

העברת שיחה – בחר אם להפנות את כל השיחות שהקו תפום, כאשר תשובה או כשאין אותן.

מענה אוטומטי – הגדיר את משך הזמן לפני שדיבורית מחוברת תענה באופן אוטומטי לשיחה כניסה. בחר בין האפשרויות 'לא זמן', 'שנייה', '3 שניות' ו-'5 שניות'.

רטט התקשרות – הטלפון שלך רוטט כשהצד השני משיב לשיחה.
הגברת קול – מגביר את איכות הקול בסביבות רuousות כדי שתוכל לשמוע יותר היטב.

שומר מספרים לא ידועים – הוסף מספרים לא ידועים לאנשי קשר לאחר שיחה. לחוץ הפעלה מסיים שיחה – אפשרות לרך לבחור סיום שיחה.

חסימת שיחות – גצל שיחות כניסה, יציאות או בינלאומיות.
משר שיחה – הגז את משך הזמן של שיחות, כולל שיחה אחרת, כל השיחות, שיחות יציאות ושיחות כניסה.

הגדירות נוספות – מאפשר לך לשנות את ההגדירות הבאות:

שיחת מזוהה: בחר אם להציג את המספר שלך בשיחה יוצאה.

שיחת ממתינה: אם שיחה ממתינה מופעלת, הטלפון יודיע על שיחה נכנסת

כאשר אתה כבר משוחח בטלפון (בהתאם לספק הרשת).

< שתף והתחבר >

NFC – הטלפון שלך הוא טלפון נייד שתומך ב-NFC. NFC (תקשורת שדה קרוב)

היא טכנולוגיה לתקשורות אלחוטיות המאפשרת תקשורת דו-כיוונית בין מכשירים

אלקטרוניים. טכנולוגיה זו פועלת למרחק של סנטימטרים ספורים. באפשרותך

לשתח את התוכן שלך עם תגית NFC או מכשיר אחר התומך ב-NFC פשוט

על-ידי הקשה עליו באמצעות המכשיר שלך. אם תקיש על תגית NFC באמצעות

המכשיר שלך, תוכן התגית יוצג במכשיר.

כדי להפעיל או לכבות את NFC: מתוך המסך הראשי, גע ב מגירת התתראות

והחלקאותו כלפי מטה באמצעות האצבע, ולאחר מכן בחר בסמל NFC כדי

להפעיל אותו.

הערה: כאשר מצב טישה מופעל, ניתן להשתמש ביחסם NFC.

שימוש ב-NFC: כדי להשתמש ב-NFC, ודא שהמכשיר פועל והפעיל את

הגדרת NFC אם היא אינה פועלת.

Direct/Android Beam – כשתconeנו זו פועלת, אפשרותך לשדר תוכן מהיחסם

למכשיר אחר התומך ב-NFC על-ידי החזקת המכשירים סמוכים זה לזה.

פשוט קרב את המכשירים זה לזה (בדרכ כל גב אל גב) ולאחר מכן הקש על

המסך. היחסם קובע מה ישודר.

SmartShare Beam – אפשר לקבל קבצים מטלפונים של LG.

Miracast – שקף את המסך וציליל הטלפון באופן אלחוטי להתקן Miracast או

למכשיר הטלוויזיה.

אחסון אלחוטי – באפשרות לנצל במכשיר קבצים שנמצאים בטלפון או להעתיק קבצים לטלפון מהמחשב ללא חיבור USB. לאחר הפעלת 'אחסון אלחוטי', ודא שהטלפון והמחשב מחוברים לאוთה רשת. לאחר מכן, הוזן את כתובות האינטרנט המוצגות בטלפון בשורת הכתובות של הדפדפן במכשיר.

< האמדת התקנים ורשתות >

נקודה חמה ניידת Wi-Fi – באפשרות גם להשתמש בטלפון כדי לספק חיבור פס רחב נייד. צור נקודה חמה ושתף את החיבור. עין בנושא "שיטוף חיבור הנתונים של הטלפון" למידע נוסף.

חיבור כמודם סולרי באמצעות Bluetooth – מאפשר לך להגדיר את הטלפון שלך בין אם אתה עושה שימוש משותף בחיבור לאינטרנט ובין אם לא. עדשה – הקש כדי להציג את מידע העזרה בנוגע לנקודה חמה ניידת Wi-Fi. ולפונקציות שיתוף אינטרנט ב-Bluetooth.

מצב טיסה – לאחר המעבר למצב טיסה, כל החיבורים האלחוטיים מושבתים. הערה: עליך להגדיר קוד PIN לנעילת המסך כדי שתוכל להשתמש במאגר האישורים.

רשתות ניידות – הגדר אפשרויות לנידית נתונים, מצב רשות ומפעליים, שמות נקודות גישה (APN) וכו'.

הגדרות VPN – הצגת רשימה של הרשותות הווירטואליות הפרטיות (VPN) שאת תצורתן קבועת בעבר. האפשרות מאפשרת לך להוסף סוגים שונים של רשותות VPN.

פרופיל צליל – בחר בין האפשרויות 'צליל', 'רטט בלבד' או 'שקט'.

עוצמת צליל – התאם את הגדרות עוצמת הצליל של הטלפון כך שהיא תאים לצרכים ולסיבבה שלך.

עוצמת רטט – מאפשר לך להגדיר את עוצמת הרטט עבור שיחות, התראות ותגובה ללחיצה על מקשיים.

מצב שקט – הגדר את 'מצב שקט'. הקש על המתג **הפעל** **מצב שקט** **עכשו כדי** להפעיל או להשבית אותו. באפשרותך לתזמן את 'מצב שקט' כך שיופיע באופן אוטומטי ולקבוע חריגים ל'מצב שקט'.

קבע זמן שקט: הקש על המתג כדי להפעיל או להשבית אותו. באפשרותך גם להגדיר את הימים והשעות שבהם 'מצב שקט' יופעל באופן אוטומטי.

הגדרות שיחה נכונות

חסום שיחות נכונות: סימן ביקורת המאפשר לך לחסום את כל השיחות הנכונות.

אפשר שיחות חוזרת ונשנות: סימן ביקורת כדי לאפשר שיחה החזרת בתוך 3 דקות.

אנשי קשר מאופשיים: קבע אילו שיחות אנשי קשר יאפשרו.
תשובה אוטומטית לשיחות חסומות: הגדר כיצד ברצונך להשיב אוטומטית לשיחות מושתקות.

RINGTONE טלפון – הגדר את הצלול עבור שיחות. תוכל גם להוסיף צלול עליידן  בפינה הימנית העליונה של המסך.

צלול חכם – סימן ביקורת המאפשר לך להגדיר את עוצמת הצלול בסביבה רועשת.

רטט בשיחה נכונות – מגדר את אפשרויות הרטט של שיחה נכונות.

רטט קל – סימן ביקורת המאפשר לך להגדיר רטט בהדרגה עד לעוצמה המוגדרת הנוכחיית.

צלצול עם רטט – סימן ביקורת המאפשר לך להגדיר שהטלפון ירטוט בנוסף לצלצול בעת קבלת שיחות.

התראה קולית – הקש על המתג התראה קולית כדי להפעיל או להשבית אותה. הפעלה מאפשרת להתקין להודייע על שיחה כניסה וירועי הודעות באופן אוטומטי.

צליל התראה – מאפשר לך להגדיר את הצליל עבור התראות. תוכל גם להוסיף צליל התראה – מאפשר לך להגדיר את הצליל המקורי (צלילים /

מערכת וגובה ללחיצה על מקשים – מאפשר לך להגדיר את התגובה (צלילים / או רטט) בזמן השימוש בהתקן.

תצוגה

< המסר הראשי >

הגדר את מערכת נושא, טפט, אפקט החלקת מסך, לאפשר לולאות מסך בית או תצוגה אנכית בלבד.

גיבוי ושחזור בית – באפשרותך לגבות ולשזר פריסות ומערכות נושא של יישום/רכיב רפואי.

הידעת? – סימן ביקורת המאפשר לך להציג את הידעת במסך בית נוספת.

< געילת מסך >

בחר געילת מסך – הגדר סוג געילת מסך כדי לאבטח את הטלפון. האפשרות פותחת סדרה של מסכים שמדריכה אותך בשרטוט תבנית ביטול געילה של המסך. הגדר ללא, החלקה, שחרור געילה באמצעות דיזמי פנים, תבנית, PIN או סיסמה.

אם הפעלה סוג געילת תבנית כשאתה מפעיל את הטלפון או מעיר את המסך, תتابקש לצייר את התבנית ביטול הנעילה כדי לבטל את געילת המסך.

אפקט החלקת מסך – מגדיר את אפשרות האפקט של החלקת מסך. בחר מבין גל עם עלים, טיפת טל, אור לבן, חלקיק וקריסטל.

הערה: שם הגדרה זו עשוי להיות 'אפקט התבנית' אם געילת המסך מוגדרת "תבנית".

הנפשת מזג אוויר – סימן ביקורת המאפשר לך להציג את הנפשות מזג האויר עבור המיקום הנוכחי או הגדרת עיר עיקרית ב'מזג אוויר' לפי עדכוני נתונים אוטומטיים.

טפט – מגדר את הטפט של מסך הנעילה. בחר מתוך גלריה או גלריה טפטים. **קיזורי דרך** – אפשר לך לשנות את קיזורי הדרך במסך הנעילה של החלקה. **פרטי בעליים** – הוסיף סימן ביקורת כדי להגדיר את שם הבעלים של ההתקן שיציג במסך הנעילה. הקש על ☰ כדי להזין את הטקסט שיוצג בפרטி הבעלים. **שעון ערך לנעילה** – מגדר את פרק הזמן לפני שהמסך יונעלא באופן אוטומטי לאחר שהזמן הקצוב עברו המסך הסתיים.

נעילה באמצעות לחץ הפעלה – סמן כדי לנעול את המסך באופן מיידי בעת לחיצה על Power/Lock Key. הגדרה זו עוקפת את הגדרת הטימר לנעילת אבטחה.

< מקשי מגע קדמיים >

הגדר את מקשי המגע הקדמיים המוצגים בתחתית כל המסכים. הגדר אילו מהם יוצגו, המיקום שלהם בסרגל וכיידם יראו. בחר את המקשיים ואת הסדר, ערכת הנושא והרקיע.

< תצוגה >

בahirot – התאמת בהירות המסך. עברו ביצועי סוללה מיטביים, השתמש בהירות הנמוכה ביותר הנוחה לשימוש.

כיבוי מסך אוטומטי – מגדר את משך הזמן לפני שהמסך יכבה.

אפקט כיבוי מסך – מגדר את אפקט כיבוי המסך. בחר בין האפשרויות 'פשוט', 'חור שחולר' ו'טלוייזיה רטרו'.

סיבוב מסך אוטומטי – סימן ביקורת המאפשר לך להגדיר את הטלפון כך שייסובב באופן אוטומטי את המסך לפי כיוון הטלפון (לאורך או לרוחב).

חלום בהקיין – הקש על המתג 'חלום בהקיין' כדי להפעיל או להשיבת אותו. באמצעות האפשרות 'מופעל' ניתן להגדיר ששומר המסר יציג כאשר הטלפון ישן במהלך עגינה /או טעינה. בחר מבין האפשרויות 'שעון', 'צבעים', 'מסגרת תמונה' ו'ittelat תМОנות'.

< גוף >

סוג גוף – מגדר את סוג הגוף המשמש עבור הטלפון והתפריטים.

גודל גוף – מגדר את גודל הגוף המוצג בטלפון ובתפריטים.

< SMART פעיל >

מסך חכם – סימן ביקורת המאפשר לך לשמר שמה麝ך לא יכבה כאשר הרתךן מזהה שעיניך מתבוננות במסך.

וידאו חכם – סימן ביקורת המאפשר לך להשווות את הוידאו כאשר הוא אינו מזהה שעיניך מתבוננות במסך.

< הגדרה מתקדמת >

תאורית הוועדה – הקש על המתג כדי להפעיל או להשיבת אפשרות זו. האפשרות 'מופעל' תביא להפעלת אור LED עבור ההודעות שתבחר, בצלע שתגדיר עבור כל אחת.

תיקון יחס מסך – מאפשר לך לשנות את יחס הגובה-רוחב של יישום שהורד כדי לתקן עייפות מסך.

כללי

< מחוות >

כאשר המסר דולק/כבוי – סימן ביקורת כדי לאפשר להפעיל מסך להדליק ולכבות את המסך. הקש פעמיים במהירות על המסך המרכז כדי להפעיל אותו. הקש פעמיים על שורת המצב, על איזור ריק במסך הבית או על מסך הנעילה כדי לכבות את המסך. עבור התוצאות המיטביות, אל תזיז את הטלפון בעת השימוש בתוכנה 'הפעיל מסך'.

השב לשיחה נכנסת – סימן ביקורת כדי לאפשר לך לקרב את הטלפון לאוזן על מנת לענות באופן אוטומטי על השיחה הנכנסת.

עמעם צלצול – סימן ביקורת כדי לאפשר לך להרים את הטלפון מהמשטח הישר כדי לעמעם את הצלצול של השיחה הנכנסת.

השתק שיחות נכנסות – סימן ביקורת כדי לאפשר לך להפוך את הטלפון על מנת להשתיק שיחות נכנסות.

נדניק או כבה שעון מעורר – סימן ביקורת כדי לאפשר לך פשוט להפוך את ההתקן על מנת להשנות או להפסיק את התתראה.

השנה יידאו – סימן ביקורת כדי לאפשר לך פשוט להפוך את ההתקן על מנת להשנות את הוויידאו המופיע עתה.

הזנת פריטים במסך הבית – סימן ביקורת המאפשר לך להזין סמל למסך אחר על-ידי הטיית הטלפון. הקש והחזק את הסמל והטה את הטלפון שמאליה או ימינה, ולאחר מכן עצוב במסך, מקום שבו ברצונך למקם את הסמל.

עדרה – פותח מדריך עדירה בנוגע לאופן השימוש בתכונות המוחוות בהתקן.

coil חישון תנועה – מאפשר לך לשפר את הדיוק של ההטיה והמהירות של החישון.

> **תפעול ביד אחת** <

מקשי חיוג – סימן ביקורת כדי לאפשר לך להזין את מקשי החיוג לצד ימין או שמאל של ההתקן. פשוט הקש על החץ כדי להזין אותו לצד אחד או לצד השני.

מקלדת LG – סימן ביקורת כדי לאפשר לך להזין את המקלדת לצד ימין או שמאל של ההתקן. פשוט הקש על החץ כדי להזין אותו לצד אחד או לצד השני.

שליטת מחוות – סימן ביקורת כדי לאפשר לך להפעיל את המקלדת שמאליה או ימינה על מנת לכוון את המיקום של מקלדת LG.

מסך נעליה – סימן ביקורת המאפשר לך להזין את לוח המקשיים של מסך הנעליה בעזרת PIN לצד ימין או שמאל של ההתקן. פשוט הקש על החץ כדי להזין אותו לצד אחד או לצד השני.

עדרה – מציג מידע בנוגע לתפעול ביד אחת.

> אחסון <

אחסון פנימי – הציגת השימוש באחסון הפנימי.

> סוללה <

מידע על הסוללה

המידע על טעינת הסוללה מוצג באיוור של סוללה, לצד אחוז הטעינה הנותר והמצב.

גע בסמל טענת הסוללה כדי להציג את מסך ניצול הסוללה, על מנת לבדוק את רמת השימוש בסוללה ואת פרטיה השימוש בסוללה. האיוור מציג אילו רכיבים ווישומים צורכים את הכמות הרבה ביותר של אנרגיית סוללה. הקש על אחד מהערכיים כדי להציג עוד מידע מפורט.
אחוז סוללה – סימן ביקורת כדי להציג את אחוז רמת הסוללה בשורת המצב לצד סמל הסוללה.

חיסכון בחשמל

הקש על המתג 'חיסכון בחשמל' כדי להפעיל או להשיבו אותו. הקש על 'חיסכון בחשמל' כדי לגשת להגדירות הבאות:

הפעל חיסכון בחשמל – מגדיר את רמת אחוז טענת הסוללה שתפעיל באופן אוטומטי את התוכנה 'חיסכון בחשמל'. בחר מבין האפשרויות 'מיד', '10% סוללה', '20% סוללה', '30% סוללה' ו-'50% סוללה'.

פריטי חיסכון באנרגיית הסוללה

סמכן באופן אוטומטי – סימן ביקורת כדי להסביר את האפשרות 'סמכן באופן אוטומטי' כאשר 'חיסכון בחשמל' מופעל.

Wi-Fi – סימן ביקורת כדי להסביר את Wi-Fi כאשר לא נעשה שימוש בנתונים בזמן שהתוכנה 'חיסכון בחשמל' מופעלת.

Bluetooth – סימן ביקורת כדי לcccccccbbbccc את Bluetooth כאשר הוא אינו מחובר בזמן שהתוכנה 'חיסכון בחשמל' מופעלת.

רטט במגע – סימן ביקורת כדי לבטל משוב מגע בזמן שהתוכנה 'חיסכון בחשמל' מופעלת.

בhairot – סימן ביקורת כדי להגדיר את בהירות המסר בזמן שהתקונה 'חיסכון בחשמל' מופעלת. הקש על ☺ כדי לשנות את ההגדירה.

כibi מסך אוטומטי – סימן ביקורת כדי להגדיר את הכיבוי האוטומטי של המסר בזמן שהתקונה 'חיסכון בחשמל' מופעלת. הקש על הסמל 'הגדרות' כדי לשנות את ההגדירה.

כibi מסך אוטומטי – סימן ביקורת כדי להגדיר את הכיבוי האוטומטי של המסר בזמן שהתקונה 'חיסכון בחשמל' מופעלת. הקש על הסמל 'הגדרות' כדי לשנות את ההגדירה.

טיפים לחיסכון בחשמל – מציג טיפים לשימוש בפונקציה 'חיסכון בחשמל'.

> **וישומים** <

הציג ונהל את ה>'וישומים' שלך.

> **גlesh czida** <

הקש על המתג **גlesh czida** כדי להזכיר אותו למצב 'מופעל', על מנת להשתמש בתוכונה 'גlesh czida'. (עין **בגlesh czida**).

> **חוובונות וסנכרון** <

מתיר לישום לסקרן נתונים ברקע, בין אם אתה עובד אתם באופן פעיל ובין אם לא. ביטול הבדיקה של הגדרה זו יכול להשוך בכוח הסוללה ולהפחית (אך לא לבטל) את השימוש בנתונים.

> **ענן** <

הוסף חשבון ענן על מנת להשתמש במהירות ובקלות בשירות ענן בישומי G7.

> **מצב אורח** <

כדי להגן על פרטייך או להגביל גישת ילדים לישומים מסוימים, תוכל להשתמש ב'**מצב אורח**'.

כאשר אתה משאל את הטלפון לאחרים, תוכל להגביל את ה>'וישומים' שיוצגו. הגדר מראש את '**מצב אורח**' והתאמם אישית את האפשרויות.

< גישה למיקום >

גישה למיקום שלו – אם בחרת את שירות המיקום של Google, הטלפון יקבע את מיקומך המשוער באמצעות רשתות Wi-Fi ורשתות סלולריות. כאשר תבחר באפשרות זו, תישאל אם אתה מסכים לאפשר ל-Google להשתמש במיקומך בעת אספקת שירותי אלה.

לווייני GPS – אם תבחר בלווייני GPS, הטלפון יקבע את מיקומך המדויק ברמת הרחוב.

מיקום ברשת Wi-Fi ורשת סלולרית – אפשר לישומים להשתמש בתנאים המקוריים כגון רשתות Wi-Fi ורשתות סלולריות כדי לקבוע את מיקומך המשוער.

< אבטחה >

הצפן טלפוני – אפשר לך להצפין נתונים בטלפון למטרת אבטחה. תידרש להזין PIN או סיסמה כדי לבטל את הצפנה הטלפון בכל פעם שתפעיל אותן.

הגדיר נעלית כרטיס SIM – הגדיר נעלית כרטיס Micro-USIM או שנה את קוד ה-NPIN של כרטיס ה-Micro-USIM.

הציג סיסמה תוך כדי הקלה – הצג את התו האחרון של סיסמה מוסתרת תוך כדי הקלה.

מנהל התקנים – הצג או השבת מנהלי התקנים.

מקורות לא ידועים – הגדרת ברירת המחדל להתקנת יישומים שמוקרים אינם Play Store.

אמת יישומים – הזהר או אל תאפשר התקינה של יישומים העולמים לגורם נזק.

אישורים מהרימנים – הצגת אישורי CA מהרימנים.

התקן מהאחסון – להתקנת אישורים מוצפנים.

נקה אישורים – להסרת כל האישורים.

< שפה וקלט >

השתמש בהגדירות שפה וקלט כדי לבחור את השפה עבור הטקסט שיוצג בטלפון וכן כדי לקבוע את תצורת המקלדת על המסך, לרבות מיללים שהוסףת למילון.

< גיבוי ו恢復 >

שנו את הגדרות לניהול ההגדירות והנתונים שלך.
גבהת את הנתונים שלך – הגדר כדי לגבות את ההגדירות ואת נתוני היישומים שלך
לשרת Google.

גבהת חשבון – הגדר כדי לגבות את החשבון שלך.
恢復 אוטומטי – הגדר כדי לשחזר את ההגדירות ואת נתוני היישומים כאשר
הយישומים מותקנים מחדש במכשיר שלך.
שירות LG Backup LG – מבצע גיבוי של כל המידע בהתקן ומשחזר אותו במקרה
של אובדן נתונים או החלפה.

איפוס נתונים יצירן – איפוס ההגדירות לערכי ברירות המחדל שהגדר היצירן
ומחקת כל הנתונים. אם תapus את הטלפון בצורה כזו, תתבקש להציג מחדש את
אותו מידע שהזנת בפעם הראשונה שהפעלת אתroid.

< תאריך ושעה >

השתמש בהגדירות **תאריך ושעה** כדי לקבוע את אופן הציגות של התאריך. כמו
כך, באפשרות להשתמש בהגדירות אלה כדי להגדר את השעה ואת אזור הזמן
שלך, מקום לקבל את השעה הנוכחית מהרשות הנידית.

< נגישות >

השתמש בהגדירות **ה נגישות** כדי לקבוע את התצורה של כל יישומי ח-ו-געפוק
ל נגישות שהתקנת בטלפון.

הערה: מחייב אפשרות לבחור יישומי ח-ו-געפוק נוספים.

< חיבור PC >

בחר שיטת חיבור **USB** – הגדר את מצב הרצין: טען את מכשיר הטלפון,
סינכרון מדיה (MTP), הצמדת התקנים, תוכנת LG או שלח תמונות (PTP).
שאל בעת חיבור – שאל במצב חיבור USB בעת התחברות למחשב.
עזרה – עזרה עבור חיבור USB.

Wi-Fi PC Suite – סמן אפשרות זו כדי להשתמש ב-LG PC Suite LG עם חיבור Wi-Fi. שים לב כי יש לחבר רשת Wi-Fi ל-LG PC Suite דרך חיבור Wi-Fi. On-Screen Phone – סמן אפשרות זו כדי לקבל בקשה לחיבור Wi-Fi מ-On-Screen Phone עזרה – עזרה עבור תוכנת LG.

< אביזר >

נרתיק QuickWindow – הפעל כדי להפוך לזמןנות תכונות, כגון מוסיקה, מג אוויר ושעון, בעת שימוש בנרתיק QuickWindow. USB אחסן מסוג Plug & Pop – מגדיר את התוכנה Plug & Pop עברו אמצעי אחסון מסוג USB. סמן את האפשרות פאנל אפליקציה כדי להציג באופן אוטומטי את פאנל האפליקציה בעת חיבור כבל USB מסוג OTG (On-the-Go). הקש על עורך את פאנל האפליקציה כדי לשנות את היישומים שברצונך להפוך לזמןנים. אוזניות – מגדיר את התוכנה Plug & Pop עברו אוזניות. סמן את האפשרות פאנל אפליקציה כדי להציג באופן אוטומטי את פאנל האפליקציה בעת חיבור אוזניות. הקש על עורך את פאנל האפליקציה כדי לשנות את היישומים שברצונך להפוך לזמןנים.

< אודוט הטלפון >

הציג מידע משפטית ובודק את מצב הטלפון ואת גרסת התוכנה שלו.

< מידע תקינה ובטיחות >

כדי להציג מידע תקינה ובטיחות, הקש על  הגדרות > הקריםיסיה כללית > אודות הטלפון > תקינה ובטיחות.

תוכנת מחשב (LG PC Suite)

תוכנת המחשב LG PC Suite היא תוכנית שיעזרת לך לחבר את המכשיר למחשב באמצעות Wi-Fi וכבל USB. לאחר ההתחברות תוכל להשתמש בפונקציות של המכשיר מהמחשב.

בעזרת תוכנת המחשב LG PC, ניתן...

- לנהל ולהפעיל את תוכני המדיה (מוסיקה, סרטיים, תמונות) מהמחשב.
- לשЛОח תוכן מולטימדיה למכשיר.
- לסנן נתונים (לוחות זמנים, אנשי קשר, סימניות) במכשיר ובמחשב.
- לגבוט את היישומים במכשיר.
- לעדכן את התוכנות במכשיר.
- לגבוט ולשחרר את נתונים הקיימים.
- להפעיל תוכן מולטימדיה מהמחשב באמצעות מכשיר אחר.
- לגבוט, ליצור ולחזור את המזקרים במכשיר

הערה: באפשרותך להשתמש בתפריט העזרה של היישום כדי לגלוות כיצד להשתמש בתוכנת המחשב LG PC Suite.

התקנת תוכנת המחשב LG PC Suite

נתן להוריד את תוכנת המחשב LG PC Suite מדף האינטרנט של LG.
1 עברו אל WWW.LG-MOBILE.CO.IL ובחרו מדינה.

2 עברו אל **תמיכה > תמיכה בנייד > טלפונים ניידים של LG >** בחר את הדגם
ואו

העברו אל **תמיכה > נייד >** בחר את הדגם.

3 לחץ על **PC SYNC** מתוך **MANUALS & DOWNLOAD**, ולאחר מכן על **DOWNLOAD** כדי להוריד את תוכנת המחשב LG PC Suite.

תוכנת מחשב (LG PC Suite)

דרישות מערכת עבור תוכנת המחשב LG PC Suite

- מערכת הפעלה: Windows Vista ,Windows XP (Service pack 3) 32bit
- Windows 7
- Windows 8,Windows 8.1
- CPU : 1 GHz ומעלה
- זיכרון: רכיבי RAM בונפח 512 ומעלה
- כרטיס מסך: רזולוציה של 1024 x 768 סיביות ומעלה
- HDD: שטח דיסק פנוי של לפחות 500 MB (ייתכן שהיא צריכה יותר בסطח רב יותר, בהתאם לנפח הנתונים המאוחסנים).
- תוכנה דרישה: מנהלי התקנים מושלבים של LG , Windows Media Player 10 ואילך

הערה: מנהל התקן USB מושלב של LG

מנהל התקן USB מושלב של LG נדרש כדי לחבר מכשיר של LG למחשב. הוא מותקן באופן אוטומטי בעת התקינה של "يسم" תוכנת המחשב LG PC Suite.

סינכרון המכשיר עם המחשב

באמצעות תוכנת המחשב LG PC Suite ניתן לסנכרן בקלות ובנוחות נתונים מהמכשיר ומהמחשב. ניתן לסנכרן אנשי קשר,לוחות זמנים וסימניות. התהילה הוא כדלקמן:

- 1 חיבור את המכשיר למחשב (השתמש בכבל USB או בחיבור Wi-Fi).
- 2 האפשרות בחר שיטת חיבור USB תופיע, ולאחר מכן בחר באפשרות **תוכנת LG**.
- 3 לאחר ההתחברות, הפעיל את התוכנית ובחירה מקטע המכשיר מתווך הקטגוריות בצד שמאל של המסך.
- 4 לחץ על **פרטים אישיים** כדי לבחור.
- 5 סמן את תיבות הסימון של התוכן שברצונכם לסנכרן, ולחוץ על הלחץ **סינכרון**.

הערה: כדי לסנן את הטלפון עם המחשב, עליך להתקין במחשב את LG PC Suite .
כדי להתקין את התוכן את LG PC Suite, עיין בדף הקודמים.

העברת אנשי קשר מהמכשיר הקודם למכשיר החדש

- 1 יצאו את אנשי הקשר מהמכשיר הישן כקובץ CSV למחשב באמצעות תוכנית סינכרון עם מחשב.
- 2 תחליה התקין את LG PC Suite LG במחשב. הפעל את התוכנית וחבר את טלפון ה-Android שברשותך למחשב בcabbel-USB.
- 3 בתפריט העליון, בחר באפשרות **מחשייר > יבא איש קשר**.
- 4 יופיע חלון מוקפץ לבחירת סוג הקובץ והקובץ ליבוא.
- 5 בחילון המוקפץ, לחץ על **בחר קובץ וירטואלי Windows Explorer**. יופיע.
- 6 בחר בקובץ אנשי הקשר ליבוא בס"ר Windows ולחץ על **פתח**.
- 7 לחצו על אישור.
- 8 יופיע חלון מוקפץ **מיופיע שדות לצורך קישור אנשי קשר במכשיר לנוטונים החדשים של אנשי קשר**.
- 9 אם קיימים קונפליקטים בין הנוטונים של אנשי הקשר מהמחשב לבין אנשי הקשר מהמכשיר, בצע את הבחירה או השינויים הדרושים ב-LG PC Suite -
10 לחץ על אישור.

עדכן תוכנת הטלפון

עדכן תוכנת הטלפון הנייד של LG מהאינטרנט

למיידנו נספ אודות השימוש בפונקציה זו, בקר בכתובת

← <http://www.lg.com/common/index.jsp> או <http://update.lgmobile.com>
בחר את המדינה והשפה שלך.

תוכנה זו מאפשרת לך לעדכן בנוחות את הקושחה של הטלפון לגרסה חדשה יותר מהאינטרנט, ללא צורך לבקר במרכז שירות. תוכנה זו תהיה זמינה רק אם LG תיצור גרסה קושחה חדשה שתיהיה זמינה למכשיר שלך.

מהחר שעדכן הקושחה של הטלפון הנייד דורש את תשומות לבו המלאה של המשמש במשר כל תהליך העדכן, הקפד לקרוא את כל ההוראות וההערות שיופיעו בכל שלב לפני שתתקדם הלאה. חשוב לזכור שהסתדרת כבל ה-USB או הסוללה במהלך השדרוג עלולה לגרום נזק חמור לטלפון הנייד.

הערה: LG שומרת על זכורה, על פי שיקול דעתה הבלעדי, להעמיד את עדכוני הקושחה לרשות דגמים נבחרים בלבד ואני ערבה לזמן התגובה החדש של הקושחה לכל דגם הטלפון.

עדכן תוכנת הטלפון הנייד של LG באופן אלחוטי (OTA)

תוכנה זו מאפשרת לך לעדכן בנוחות את תוכנת הטלפון לגרסה חדשה יותר דרך OTA, מביי להתחבר באמצעות כבל נתונים USB. תוכנה זו תהיה זמינה רק אם LG תיצור גרסה קושחה חדשה שתיהיה זמינה למכשיר שלך.

תחליה עלייך לבדוק את גרסת התוכנה בתלפון הנייד שלך: **הגדרות > אודות הטלפון > מרכז עדכנים > עדכן תוכנה > חופשי עדכנים** כתעת.

הערה: הנתונים האישיים שלך משטח האחסון הפנימי בטלפון—לרבותות פרטן חשבו Google וכל חשבון אחר, נתונים והגדירות של המערכת/הישומים שלך, יישומים שהודו ורישון ה-DRM שלך—עשויים לאלץ לאיבוד בתהילך עדכון התוכנה של הטלפון. לפיכך, LG ממליצה לך לגבוט את הנתונים האישיים שלך לפני שתעדכן את תוכנת הטלפון. LG לא תישא באחריות לאובדן נתונים אישיים כלשהם.

הערה: תוכנה זו תלויה בספק שירות הרשות, באזרע ובמדינה שלך.

אודות מדריך למשתמש זה

- לפני השימוש במכשיר, אנא קרא בעיון מדריך זה. הדבר יבטיח שתשתמש טלפון שלך בצורה נכונה ובטוחה.
- חלק מה坦ונות ומצלומי המסך המופיעים במדריך זה עשויים להיראות שונים טלפון שלך.
- התיכון שלך עשוי להיות שונה מה מוצר הסופי או מהתוכנה המספקת עליידי ספק' שירות או מפעלים סולוריים. תוכן זה נתן לשינויים ללא הודעה מוקדמת. לקבלת הגרסה העדכנית של מדריך זה, בקר באתר האינטרנט של LG בכתבות WWW.LG-MOBILE.CO.IL.
- היישומים טלפון שלך והפונקציות שלהם עשויים לשינויים בהתאם למדיינה, לאזור או למפרט החומרה. LG לא תישא אחריות לביעות ביצועים הנובעות שימוש ביישומים שפותחו על-ידי ספקים פרט ל-LG.
- LG לא תישא אחריות לביעות ביצועים או חסור תאמיות הנובעות מuracyת הגדרות רישום או משינויים בתוכנת מערכת ההפעלה. כל ניסיון להתאים אישית את מערכת ההפעלה שלך עלול לגרום למカリ או ליישומים שלו להפסיק לפעול מצופה.
- תוכנות, שמע, טפטים, תמונות ופריטי מדיה אחרים שסופקו יחד עם המכשיר שלך מורשים לשימוש מוגבל. אם תחלץ חומר זה ותשימוש בו למטרות מסחריות או אחרות, אתה עלול להפר חוקי זכויות יוצרים. כמשתמש, אתה נושא באחריות מלאה ובולדית לשימוש לא חוקי במידיה.
- יתכן שיחולו חיבטים נוספים תמורה שירותי נתונים, כגון שירות הדעות, הعلاה והורדת סמכון אוטומטי או שימוש בשירותי מיקום. כדי להימנע מחיבטים נוספים, בחר תוכנית נתונים מתאימה לצרכיך. פנה אל ספק השירות לקבלת פרטיים נוספים.

סימנים מסחריים

- LG והלוגו של LG הם סימני מסחר רשמיים של LG Electronics.
- כל יתר הסימנים המסחריים וזכויות היוצרים הם רכושם של בעליهم בהתאם.



אודות סרטוני DivX®: DivX® הוא פורטט וידאו דיגיטלי שיצרה LLC DivX Corporation. זהה התקן® DivX Certified רשמי שuber בדיקות קפדניות כדי לאשר שנית להפעיל בו סרטוני X-Div. קיבלת מידע נוספת נספּן. וכל תוכנה להמרת קבצים לתובנית וידאו X-Div, בקר בכתובת www.divx.com. אודוט וידאו לפי דרישת (VOD) בתבנית DivX: כדי להפעיל סרטי וידאו לפי דרישת (VOD) בהתקן זה הנושא את אישור® DivX Certified, יש לבצע רישום של ההתקן. קיבלת קוד הרישום, אטר את המקטע VOD DivX בתפריט ההגדרות של ההתקן. קיבלת מידע נוסף על אופן הרישום: www.divx.vod.com.

אודות סרטוני וידאו X-Div® עד 720p HD, כולל תוכן מעולה.

DivX® וסמלו הלוגו הקשורים הם סימני מסחר של Rovi Corporation והשימוש בהם מתבצע ברישיון.



Dolby Digital Plus ,Dolby Laboratories. Dolby Digital Plus ,Dolby Laboratories .
סמל ה-D ההפוך הם סימני מסחריים של Dolby Laboratories.


הודעה: תוכנות קוד פתוח

לקבלת קוד המקור המתאים במסגרת GPL, LGPL, MPL ורישיונות קוד פתוח אחרים,
בקר בכתובת <http://opensource.lge.com>
כל תנאי הרישיון, כתבי הוויתור וההודעות המצורפים מופיעים להורדה עם קוד המקור.

האביזרים הבאים זמינים לשימוש עם הטלפון שלך. (האביזרים המתוירים להלן עשויים להיות אופציונליים.)



אוזניות סטריאו



מתאים לסיועת



כבל נתונים



מדריך להתחלה
 מהירה



כלי לשילוף
Micro-USIM

הערה:

- השתמש תמיד באביזרים מקוריים של LG.
- שימוש באביזרים שאינם מקוריים עלול לבטל את האחוריות.
- סוג האביזרים עשוי להשתנות מאזור לאזור.

פרק זה מוגנות מספר בעיות שאתה עלול להיתקל בהן במהלך השימוש בטלפון. בעיות מסוימות יצריכו פניה לספק השירות, אך את רובן תוכל לפתור בקלות בעצמך.

הודעה	גורםים אפשריים	אפשרויות לתקן הבעיה
שגיאת כרטיס Micro-USIM	אין כרטיס -Micro-USIM בטלפון או שהוא הוכנס בצורה לא נכונה.	ודא שכרטיס ה-Micro-USIM הוכנס כהלכה.
אין חיבור לרשת/החיבור חלש	האות חלש או שאתה נמצא מחוץ לטווח הרשת של ספק השירות.	התקרב לחלוון או צא לאזור פתוח. בדוק את מנת היכיסוי של מפעיל הרשת הסלולרית.
הקודים אינם תואמים	המספר היחיל שירותי חדשים.	בדוק אם גילו של כרטיס ה-Micro-USIM עולה על 6~12 חודשים. אם כן, החלף את כרטיס ה-Micro-USIM בסניף הקרוב ביותר של ספק הרשת שלך. פנה אל ספק השירות.
לא ניתן להציג יישומים	כדי לשנות קוד אבטחה, יש להזין את הקוד החדש שוב כדי לאחר מכן. שני הקודים שהוזנו אינם זהים זה זהה.	אם שכחת את הקוד, פנה אל ספק השירות.
	הוא לא נתמך על-ידי ספק השירות או שמדובר בעבורו.	פנה אל ספק השירות.

הודעה	גורםים אפשריים	אפשרויות לתקן הבעיה
לא ניתן לבצע שייחות	טעות בחיבור	הרשות החדשת אינה מורשית.
	הוכנס כרטיס Micro-SIM חדש.	בדוק אם קיימות מגבלות חדשות.
	הגעת למגבלות החיבור ששולם מראש.	צור קשר עם חברת הסלולר או אפס את המגבלה בעזרת PIN2.
לא ניתן להפעיל את הטלפון	מקש הדלקה/כיבוי נלחץ Maher MDI.	לחץ על מקש הפעלה/כיבוי למשך שתי שניות לפחות.
	הסוללה לא נטענה.	טען את הסוללה. בדוק אם מחוון הטעינה בתצוגה.
	הסוללה לא נטענה.	טען את הסוללה.
שגיאת טיעינה	הטמפרטורה החיצונית גבוהה או גבוהה מדי.	ודא שהטלפון נתען בטמפרטורה הרגילה.
	בעיית מגעים	בדוק את המטען ואת החיבור שלו לטלפון.
	אין מתח	חברו את המטען לשקע אחר.
	הטען פגום	החלף את המטען.
	טען לא מתאים	השתמש רק באביזרים מקוריים של LG.
	פונקציית מספר קבוע מראש פעולת.	בדוק את התפריט 'הגדרות' ונטרל את הפונקציה.

הודעה	גורםים אפשריים	אפשרויות לתקן הבעיה
לא ניתן לקבל/לשלוח הודעות SMS ותמונות	הזיכרון מלא	מחק חלק מההודעות השמורות בטלפון.
הקבצים אינם נפתחים	אין תמייה בתבנית הקובץ	בדוק את תבניות הקובץ הנתמכות.
המסמך אינו מתקבל מתקבלת-mail או שיחת-	בעיה בהישן הקרה	אם אתה משתמש בנווטייק או כיסוי להגנה, וdia שהוא אינו מכסה את האזורי שסביב ח'ישן ההקרה. וdia שהאזור שמסביב לח'ישן ההקרה נקי.
אין ציליל	מצב רטט	בדוק את מצב הגדרות בתפריט הצליל כדי לוודא שאין במצב רטט או שקט.
ניטוק או קפיאה	בעיה של נתק בתוכנה	נסה לעדכן את התוכנה דרך אתר האינטרנט.

תת קטגוריה	שאלה	תשובה
BT Bluetooth מכשירים	אילו הן הפונקציות הزمיניות דרך Bluetooth	באפשרות לחבר התקן שמע של Bluetooth, כגון אוזניות סטריאו/mono או דיבורית. כמו כן, כשרט FTP מחבר למכשיר תאום, ניתן לשתף תוכן המאוחסן במדיה האחסון.
BT Bluetooth אוזניות	אם אוזניות Bluetooth מושם של מחוברות, האם אני יכול להאזין למוסיקה דרך אוזניות. כתוצאה לכך, לא תוכל להאזין למוסיקה דרך אוזניות חוטיות. של?	כאשר אוזניות Bluetooth מושם כל הצלילים של המערכת מושמעים דרך האוזניות. כתוצאה לכך, לא תוכל להאזין למוסיקה דרך אוזניות חוטיות.
נתונים אנשי קשר גיבוי	איך ניתן לגבות את אנשי הקשר? אפשר לScarica את נתוני אנשי הקשר בין הטלפון ו-Gmail™.	אפשר לגבות את אנשי הקשר על ידי סינכרון חד ציווני בין הטלפון ו-Gmail™.
נתונים סינכרון	אם יש אפשרות להגדיר סינכרון חד ציווני עם Gmail?	קיים רק סינכרון דו ציווני.
נתונים סינכרון	אם ניתן לScarica את כל תיקיות הדוא"ל?	תיבת הדואר הנכנס מסונכרנת באופן אוטומטי. אפשר להציג תיקיות אחרות על-ידי הקשה על מקש התפריט [=] ובבחירה באפשרות תיקיות כדי לבחור תיקייה.

קטgorיה תת קטgorיה	שאלה	תשובה
שירות Google™ כניסה ל-Gmail	אם עלי' להיכנס ל-Gmail בכל פעם שברצוני לגשת אל Gmail?	לאחר שנכנסת ל-Gmail, אין צורך להיכנס ל-Gmail שוב.
שירות Google™ חשבון Google	אם ניתן לSEN הודעות דוא"ל דרך הטלפון, אין תמיינה בסינון הודעות דוא"ל?	לא, אין תמיינה בסינון הודעות דוא"ל דרך הטלפון.
פונקציות הטלפון דוא"ל	מה קורה כאשר מפעלים יישום אחר בשעה שcottbins הודעת דוא"ל?	הודעת הדוא"ל תישמר באופן אוטומטי כתיהה.
פונקציות הטלפון צלול	אם קיימת מגבלת גודל אשר ברצוני להשתמש בקובץ MP3 קרינטן?	אין מגבלה על גודל הקובץ.
פונקציות הטלפון שעת ההודעה	טלפון לא מציג את שעת קבלת הודעה עבור הודעות שהתקבלו באותו יום.	אפשר לראות רק את שעת קבלת הודעה של הודעות שהתקבלו לפני 24 שעות. אין אפשרות לשנות זאת?
פונקציות הטלפון নিয়ন্ত্রণ	אם ניתן להתקין ולחמש בכל יישום שזמן ב-Play Store ותואם לחומרה.	ניתן להתקין ולהשתמש בכל יישום שזמן ב-Play Store ותואם לחומרה.

תת קטgorיה	קטgorיה	שאלה	תשובה
פונקציות הטלפון סנכרון	האם ניתן לسانכרן את אנשי הקשר מכל חשבונות הדואל שלי?	ניתן לسانכרן רק אנשי קשר מ-Gmail ו-MS Exchange server (שרת דוא"ל של החברה).	אם ניתן לسانכרן את
פונקציות הטלפון המטען והשאה	האם ניתן לשמר איש קשר שבוצעו עליי פעולות המטען והשאה?	אם העברת איש קשר כאשר פונקציות המטען או השאה נשמרו עם מספרו, לא תוכל להשתמש בתכונות אלה. תצטרכך לשומרשוב כל מספר.	כיצד לשמר עם פונקציות המטען והשאה?
פונקציות הטלפון אבטחה	מהו סמל הראשי, הקש על הסמל טלפוני.	1. חיגג את המספר ולאחר מכן הקש על במקש התפרקיט  . 2. חיגג את המספר ולאחר מכן הקש על הוסף השאה של 2 שניות או על הוסף המותנה.	האם ניתן לשמר איש קשר שבוצעו עליי פעולות המטען והשאה?
פונקציות הטלפון אבטחה	מהן פונקציות האבטחה של הטלפון?	ניתן להגדיר את הטלפון כך שהוא ידרש הזנת תבנית ביטול נעליה כתנאי לגישה או לשימוש בטלפון.	האם ניתן להגדיר את הטלפון כך שהוא ידרש הזנת תבנית ביטול נעליה כתנאי לגישה או לשימוש בטלפון.

קטgorיה תת קטgorיה	שאלה	תשובה
פונקציות טלפון ביטול נעליה תבנית	נעליה?	<p>1. במסך הראשי, הקש על מקש התפריט.</p> <p>2. הקש על הגדרות מערכת > הכרטיסייה צוגה > מסך נעליה.</p> <p>3. הקש על בחירה נעלית מסך > תבנית. בפעם הראשונה שתעשה זאת תופיע הדריכה קצרה על יצירת תבנית ביטול נעליה.</p> <p>4. הגדר על-ידי ציר התבנית פעם אחת, ולאחר מכן ציר אותהשוב לאישור.</p> <p>יש לנוקוט אמצעי זהירות בעת שימוש בביטול נעלית התבנית. חשוב מאוד לזכור את התבנית ביטול הנעליה שהוגדרה. אם תשתמש בתבנית שגואה חמיש פעים, תאבד את הגישה לטלפון. לרשותך חמישה ניסיונות להציג את התבנית ביטול הנעליה, קוד-h-PIN או הסיסמה. אם ניצלת את כל 5 הניסיונות, תוכל לנוסות שוב לאחר 30 שניות. (לחלופין, אם קבעת מראש את קוד-h-PIN לגיבוי, תוכל להשתמש בקוד זה כדי לבטל את נעלית התבנית).</p>

תת קטגוריה	שאלה	תשובה
פונקציות הטלפון	מה עליי לעשות אם שכחתי את תבנית ביטול הנעילה ולא יצרתי את חשבון Google בטלפון?	אם נכנסת לחשבון Google בטלפון, אך לא הצליחה להציג את התבנית הנכונה 5 פעמים, הקש על הלחץ 'שכחת את התבנית?'. לאחר מכן תידרש להיכנס לחשבון Google שלך כדי לבטל את נעילת הטלפון. אם לא יוצרת חשבון Google בטלפון או שכחת אותו, תצטרכ לבצע איפוס תבנית חשבון Google בטלפון? קשה.
זהירות:	אם תבצע איפוס נתונים ייצן, כל יישומי המשמש נתונים המשמש ימחקו. זכור לגבות את כל הנתונים החשובים לפני ביצוע איפוס להגדרת היצן.	
פונקציות הטלפון זיכרון	האם אדע שהזיכרון שלי מלא?	כן, קיבל התראה.

קטgorיה תת קטgorיה	שאלה	תשובה
פונקציות הטלפון תמיינה בשפה	האם ניתן לשנות את השפה של הטלפון?	טלפון יש יכולות רב-לשונית. כדי לשנות את השפה: 1. מהמסך הראשי, הקש על מקש התפריט ולאחר מכן הקש על הגדרות מערכת . 2. הקש על הCRTSISYAH CALLI > שפה OKLLT > שפה . 3. הקש על השפה הרצוייה.
פונקציות הטלפון VPN	כיצד מגדרים VPN?	תוצרת הגישה ל-VPN שונה מחברה לחברה. כדי לקבוע תוצרת של גישה ל-VPN מהטלפון, עליך לקבל את המידע ממנהל הרשות בחברה שלך.
פונקציות הטלפון ביבי אוטומטי של המסך	המסך שלי כבב לאחר 15 שניות בלבד. איך ניתן לשנות את פרקי הזמן עד לביבי או הרקע במסך?	1. במסך הראשי, הקש על מקש התפריט . 2. הקש על הגדרות מערכת < crtSISyAh תצוגה. 3. הקש על ביבי מסך אוטומטי . 4. הקש על פרק הזמן המועדף עד לביבי התואורה האחוריית של המסך .

תת קטgorיה	קטgorיה	שאלה	תשובה
פונקציות הטלפון Wi-Fi ניידת	טלפון	באיזה שירות משתמש הטלפון?	בעת שימוש בנתונים, יתכן שברירת המחדל של הטלפון תהיה חיבור Wi-Fi (אם קישוריות Wi-Fi מוגדרת בטלפון שלך כמופעלת). עם זאת, לא תתקבל התראה על כך שהטלפון עבר מקישוריות אחת לאחרת.
פונקציות הטלפון המסר הראשי	טלפון	האם אפשר להסיר יישום מהמסך הראשי?	כדי לדעת איזה חיבור נתונים משמש בעת, הבט בסמל של הרשת הניידת או בסמל Wi-Fi המוצג בראש המסך.
פונקציות הטלפון יישום	טלפון	הורדתי יישום שגרם הרבה שגיאות. איך אפשר להסיר אותו?	cn. פשוט גע נגיעה ממושכת בסמל עד שיויע סמל פח האשפה בחלק העליון במרכז המסך. לאחר מכן, מבלי להרים את האצבע, גרור את הסמל לפח האשפה.
1. במסר הראשי, הקש על מקש התפריט  . 2. הקש על הגדרות מערכת > הכרטיסייה כללית > יישומים > שהורדו . 3. הקש על היישום , ולאחר מכן הקש על הסר התקינה .	טלפון		

קטgorיה תת קטgorיה	שאלת	תשובה
פונקציות טלפון טען	אם ניתן לטעון את הטלפון באמצעות כבל נתוני של USB מוביל להתקין את מנהל ההתקן החדש של ?USB	כן, הטלפון יטען דרך כבל-USB בין אמ' מנהלי הרתקנים הדורשים מותקנים ובין אמ' לא.
פונקציות טלפון התראה	אם ניתן להשתמש בקובצי מוסיקה להתראה?	1. גע ברציפות בשיר בראשימת ספרייה. <i>In the menu that opens, tap Set music as > Ringtone or Contact .ringtone</i> 2. במסך של הגדרת שמעון מעורר, בחר את השיר כRingtone.
פונקציות טלפון התראה	אם ההתראות ישמעו בכל מקרה, או שגם ההתראות יוכבו כאשר הטלפון מכובה?	לא, אין תמיינה בכך.

תת קטgorיה	שאלה	תשובה
פונקציות הטלפון התראה	אם עוצמת הצלול הוגדרה ככוביה או רטט, ההתראה מתוכנתת להישמע אפילו בתרחישים אלו. אם אשמעו את ההתראה?	אם עוצמת הצלול הוגדרה ככוביה או רטט, ההתראה מתוכנתת להישמע אפילו בתרחישים אלו. אם אשמעו את ההתראה?
פתרונות התואשות שימוש באיפוס קשייח (איפוס להగדרות היצן)	אם הטלפון אינו מתחזר למצוין נתוני יצנן אם אני יכול המקור, יש להשתמש באיפוס קשייח LAGASH לפרט ההגדרות (איפוס להגדרות יצנן כדי לאתחל אתו).	כיצד ניתן לבצע שחזור אם הטלפון לא מתחזר למצוין נתוני יצנן אם אני יכול המקור, יש להשתמש באיפוס קשייח LAGASH לפרט ההגדרות (איפוס להגדרות יצנן כדי לאתחל אתו)?



LG

ENGLISH

User Guide

The Video Guide introduces you to the new key features of G2. This is available on the phone:

▶ Press > > **Video Guide**. (Available in English, French, Italian, German, Spanish(ES), and Traditional Chinese.)

- Screen displays and illustrations may differ from those you see on actual phone.
- Some of the contents of this guide may not apply to your phone, depending on the software and your service provider. All information in this document is subject to change without notice.
- This handset is not suitable for people who have a visual impairment due to the tap screen keyboard.
- Copyright ©2013 LG Electronics, Inc. All rights reserved. LG and the LG logo are registered trademarks of LG Group and its related entities. All other trademarks are the property of their respective owners.
- Google™, Google Maps™, Gmail™, YouTube™, Hangouts™ and Play Store™ are trademarks of Google, Inc.




Table of contents

Guidelines for safe and efficient use	5	Sharing your phone's data connection	37
Important notice	14	Wi-Fi Direct	39
Getting to know your phone.....	20	Using SmartShare.....	39
Phone overview	20	PC connections with a USB cable.....	41
Installing the micro-USIM card.....	22		
Charging your phone	23		
Locking and unlocking the screen.....	24		
KnockON.....	24		
Stereo headset with microphone.....	25		
Plug & Pop.....	26		
Your Home screen.....	27		
Touch screen tips	27		
Home screen	28		
Extended home screen	28		
Customizing the Home screen	29		
Returning to recently-used applications	30		
Notifications panel.....	30		
Opening the notifications panel.....	31		
Indicator icons on the Status Bar	31		
On-screen keyboard	33		
Entering accented letters.....	33		
Google account setup.....	34		
Connecting to Networks and Devices.....	35		
Wi-Fi	35		
Connecting to Wi-Fi networks	35		
Turning Wi-Fi on and connecting to a			
Wi-Fi network.....	35		
Bluetooth.....	36		
Calls	42		
Making a call	42		
Calling your contacts	42		
Answering and rejecting a call	42		
Adjusting the in-call volume.....	43		
Making a second call	43		
Viewing your call logs	43		
Call settings.....	44		
Contacts	45		
Searching for a contact.....	45		
Adding a new contact	45		
Favourites contacts.....	45		
Creating a group	46		
Messaging.....	47		
Sending a message	47		
Threaded box	48		
Changing your message settings	48		
E-mail	49		
Managing an email account	49		
Working with account folders.....	49		
Composing and sending email	50		
Camera	51		
Getting to know the viewfinder	51		
Using the advanced settings	52		

Taking a quick photo	53
Using Shot & Clear mode	53
Using Dual camera mode	54
Using Time catch shot mode	54
Once you've taken a photo.....	55
From your Gallery	56
Video camera	57
Getting to know the viewfinder	57
Using the advanced settings	58
Recording a quick video.....	59
After recording a video.....	59
From your Gallery	60
Adjusting the volume when viewing a video	60
Using Audio Zoom.....	60
Using Dual recording mode.....	61
Using Tracking zoom mode	61
Function	62
QuickMemo	62
Using the QuickMemo options	63
Viewing the saved QuickMemo	63
QuickTranslator	64
QSlide.....	65
QuickRemote	66
Zoom to Track.....	67
VuTalk	68
Register VuTalk Before Use	68
VuTalk Settings	69
Communicate Visually with VuTalk	69
Voice Mate.....	70
Use Voice Mate	70
Voice Mate Settings	70
LG SmartWorld	71
How to Get to LG SmartWorld from Your Phone	71
How to use LG SmartWorld.....	71
On-Screen Phone	72
On-Screen Phone icons.....	72
On-Screen Phone features	72
How to install On-Screen Phone on your PC	73
Multimedia	74
Gallery	74
Viewing pictures	74
Playing videos	75
Editing photos.....	75
Deleting photos/videos	75
Setting as wallpaper	75
Videos	75
Playing a video	76
Video Editor	77
Music	78
Add music files to your phone.....	78
Transfer music using Media sync (MTP)	79
Playing a song	79
Utilities	81
Slide Aside (Quick task-switching with THREE fingers)	81
Guest Mode	81
Setting your alarm	81

Table of contents

Using your calculator	82	PC software (LG PC Suite)	101
Adding an event to your calendar.....	82	Phone software update	104
Voice Recorder	83	Phone software update.....	104
Recording a sound or voice	83		
Sending the voice recording	83		
Task Manager.....	83	About this user guide	106
Tasks.....	84	About this user guide.....	106
POLARIS Viewer 5.....	84	Trademarks	106
Google+	85	DivX HD	107
Voice Search.....	85	Dolby Digital Plus.....	107
Downloads	85	Accessories.....	108
The Web	86	Troubleshooting	109
Internet.....	86	FAQ	113
Using the Web toolbar	86		
Viewing webpages	86		
Opening a page	87		
Searching the web by voice	87		
Bookmarks.....	87		
History	87		
Using Popup Browser	87		
Chrome	88		
Viewing webpages	88		
Opening a page	88		
Syncing with other devices	88		
Settings.....	89		
Networks.....	89		
Sound.....	92		
Display	93		
General.....	95		

Guidelines for safe and efficient use

Please read these simple guidelines. Not following these guidelines may be dangerous or illegal.

Exposure to radio frequency energy

Radio wave exposure and Specific Absorption Rate (SAR) information.

This mobile phone model **LG G2** has been designed to comply with applicable safety requirements for exposure to radio waves. These requirements are based on scientific guidelines that include safety margins designed to assure the safety of all persons, regardless of age and health.

- The radio wave exposure guidelines employ a unit of measurement known as the Specific Absorption Rate (SAR). Tests for SAR are conducted using standardised methods with the phone transmitting at its highest certified power level in all used frequency bands.
- While there may be differences between the SAR levels of various LG phone models, they are all designed to meet the relevant guidelines for exposure to radio waves.
- The SAR limit recommended by the International Commission on Non-Ionizing Radiation Protection (ICNIRP) is 2 W/kg averaged over 10g of tissue.
- The highest SAR value for this model phone tested for use at the ear is 0.409 W/kg (10 g) and when worn on the body is 0.470 W/Kg (10 g).
- This device meets RF exposure guidelines when used either in the normal use position against the ear or when positioned at least 1.5 cm away from the body. When a carry case, belt clip or holder is used for body-worn operation, it should not contain metal and should position the product at least 1.5 cm away from your body. In order to transmit data files or messages, this device requires a quality connection to the network. In some cases, transmission of data files or messages may be delayed until such a connection is available. Ensure the above separation distance instructions are followed until the transmission is completed.

Guidelines for safe and efficient use

Product care and maintenance

WARNING

Only use batteries, chargers and accessories approved for use with this particular phone model. The use of any other types may invalidate any approval or warranty applying to the phone and may be dangerous.

- Do not disassemble this unit. Take it to a qualified service technician when repair work is required.
- Repairs under warranty, at LG's discretion, may include replacement parts or boards that are either new or reconditioned, provided that they have functionality equal to that of the parts being replaced.
- Keep away from electrical appliances such as TVs, radios and personal computers.
- The unit should be kept away from heat sources such as radiators or cookers.
- Do not drop.
- Do not subject this unit to mechanical vibration or shock.
- Switch off the phone in any area where you are required to by special regulations. For example, do not use your phone in hospitals as it may affect sensitive medical equipment.
- Do not handle the phone with wet hands while it is being charged. It may cause an electric shock and can seriously damage your phone.
- Do not charge a handset near flammable material as the handset can become hot and create a fire hazard.
- Use a dry cloth to clean the exterior of the unit (do not use solvents such as benzene, thinner or alcohol).
- Do not charge the phone when it is on soft furnishings.
- The phone should be charged in a well ventilated area.
- Do not subject this unit to excessive smoke or dust.

- Do not keep the phone next to credit cards or transport tickets; it can affect the information on the magnetic strips.
- Do not tap the screen with a sharp object as it may damage the phone.
- Do not expose the phone to liquid or moisture.
- Use accessories like earphones cautiously. Do not touch the antenna unnecessarily.
- Do not use, touch or attempt to remove or fix broken, chipped or cracked glass. Damage to the glass display due to abuse or misuse is not covered under the warranty.
- Your phone is an electronic device that generates heat during normal operation. Extremely prolonged, direct skin contact in the absence of adequate ventilation may result in discomfort or minor burns. Therefore, use care when handling your phone during or immediately after operation.
- If your phone gets wet, immediately unplug it to dry off completely. Do not attempt to accelerate the drying process with an external heating source, such as an oven, microwave or hair dryer.
- The liquid in your wet phone, changes the color of the product label inside your phone. Damage to your device as a result of exposure to liquid is not covered under your warranty.

Efficient phone operation

Electronics devices

All mobile phones may receive interference, which could affect performance.

- Do not use your mobile phone near medical equipment without requesting permission. Avoid placing the phone over pacemakers, for example, in your breast pocket.
- Some hearing aids might be disturbed by mobile phones.
- Minor interference may affect TVs, radios, PCs etc.

Guidelines for safe and efficient use

- Use your phone in temperatures between 0°C and 40°C, if possible. Exposing your phone to extremely low or high temperatures may result in damage, malfunction, or even explosion.

Road safety

Check the laws and regulations on the use of mobile phones in the area when you drive.

- Do not use a hand-held phone while driving.
- Give full attention to driving.
- Pull off the road and park before making or answering a call if driving conditions so require.
- RF energy may affect some electronic systems in your vehicle such as car stereos and safety equipment.
- When your vehicle is equipped with an air bag, do not obstruct with installed or portable wireless equipment. It can cause the air bag to fail or cause serious injury due to improper performance.
- If you are listening to music whilst out and about, please ensure that the volume is at a reasonable level so that you are aware of your surroundings. This is of particular importance when near roads.

Avoid damage to your hearing



To prevent possible hearing damage, do not listen at high volume levels for long periods.

Damage to your hearing can occur if you are exposed to loud sound for long periods of time. We therefore recommend that you do not turn on or off the handset close to your ear. We also recommend that music and call volumes are set to a reasonable level.

- When using headphones, turn the volume down if you cannot hear the people speaking near you, or if the person sitting next to you can hear what you are listening to.

NOTE: Excessive sound pressure from earphones and headphones can cause hearing loss

Glass Parts

Some parts of your mobile device are made of glass. This glass could break if your mobile device is dropped on a hard surface or receives a substantial impact. If the glass breaks, do not touch or attempt to remove it. Stop using your mobile device until the glass is replaced by an authorised service provider.

Blasting area

Do not use the phone where blasting is in progress. Observe restrictions and follow any regulations or rules.

Potentially explosive atmospheres

- Do not use your phone at a refueling point.
- Do not use near fuel or chemicals.
- Do not transport or store flammable gas, liquid or explosives in the same compartment of your vehicle as your mobile phone or accessories.

Guidelines for safe and efficient use

In aircraft

Wireless devices can cause interference in aircraft.

- Turn your mobile phone off before boarding any aircraft.
- Do not use it on the ground without permission from the crew.

Children

Keep the phone in a safe place out of the reach of small children. It includes small parts which may cause a choking hazard if detached.

Emergency calls

Emergency calls may not be available on all mobile networks. Therefore you should never depend solely on your phone for emergency calls. Check with your local service provider.

Battery information and care

- You do not need to completely discharge the battery before recharging. Unlike other battery systems, there is no memory effect that could compromise the battery's performance.
- Use only LG batteries and chargers. LG chargers are designed to maximise the battery life.
- Do not disassemble or short-circuit the battery.
- Replace the battery when it no longer provides acceptable performance. The battery pack may be recharged hundreds of times before it needs replacing.
- Recharge the battery if it has not been used for a long time to maximise usability.
- Do not expose the battery charger to direct sunlight or use it in high humidity, such as in the bathroom.

- Do not leave the battery in hot or cold places, as this may deteriorate battery performance.
- There is risk of explosion if the battery is replaced with an incorrect type.
- Dispose of used batteries according to the manufacturer's instructions. Please recycle when possible. Do not dispose as household waste.
- If you need to replace the battery, take it to the nearest authorised LG Electronics service point or dealer for assistance.
- Always unplug the charger from the wall socket after the phone is fully charged to save unnecessary power consumption of the charger.
- Actual battery life will depend on network configuration, product settings, usage patterns, battery and environmental conditions.
- Make sure that no sharp-edged items such as animal's teeth or nails, come into contact with the battery. This could cause a fire.
- For your safety, do not remove the battery incorporated in the product.

DECLARATION OF CONFORMITY

Hereby, **LG Electronics** declares that this **LG-D802** product is in compliance with the essential requirements and other relevant provisions of Directive **1999/5/EC**. A copy of the Declaration of Conformity can be found at <http://www.lg.com/global/support/cedoc/RetrieveProductCeDOC.jsp>

Notice: Open Source Software

To obtain the corresponding source code under GPL, LGPL, MPL and other open source licences, please visit <http://opensource.lge.com/>

All referred licence terms, disclaimers and notices are available for download with the source code.

Guidelines for safe and efficient use

Regulatory and Safety

Go to "System settings > About phone > Regulatory and Safety" to get regulatory and safety information

Contact office for compliance of this product :

LG Electronics Inc.

EU Representative, Krijgsman 1,
1186 DM Amstelveen, The Netherlands



Disposal of your old appliance

- When this crossed-out wheeled bin symbol is attached to a product it means the product is covered by the European Directive 2002/96/EC.
- All electrical and electronic products should be disposed of separately from the municipal waste stream via designated collection facilities appointed by the government or the local authorities.
- The correct disposal of your old appliance will help prevent potential negative consequences for the environment and human health.
- For more detailed information about disposal of your old appliance, please contact your city office, waste disposal service or the shop where you purchased the product.



Disposal of waste batteries/accumulators

- When this crossed-out wheeled bin symbol is attached to batteries/ accumulators of your product it means they are covered by the European Directive 2006/66/EC.
- This symbol may be combined with chemical symbols for mercury (Hg), cadmium (Cd) or lead (Pb) if the battery contains more than 0.0005% of mercury, 0.002% of cadmium or 0.004% of lead.
- All batteries/accumulators should be disposed separately from the municipal waste stream via designated collection facilities appointed by the government or the local authorities.
- The correct disposal of your old batteries/accumulators will help to prevent potential negative consequences for the environment, animal and human health.
- For more detailed information about disposal of your old batteries/ accumulators, please contact your city office, waste disposal service or the shop where you purchased the product.

Important notice

Please read this before you start using your phone!

Please check to see whether any problems you encountered with your phone are described in this section before taking the phone in for service or calling a service representative.

1. Phone memory

When there is less than 10% of space available in your phone memory, your phone cannot receive new messages. You need to check your phone memory and delete some data, such as applications or messages, to make more memory available.

To uninstall applications:

- 1 Tap  >  > Apps tab >  Settings > General tab > Apps.
- 2 Once all applications appear, scroll to and select the application you want to uninstall.
- 3 Tap **Uninstall**.

2. Optimizing battery life

Extend your battery's power by turning off features that you don't have to run constantly in the background. You can monitor how applications and system resources consume battery power.

Extending your phone's battery life:

- Turn off radio communications when you are not using. If you are not using Wi-Fi, Bluetooth or GPS, turn them off.
- Reduce screen brightness and set a shorter screen timeout.
- Turn off automatic syncing for Gmail, Calendar, Contacts and other applications.
- Some applications you have downloaded may reduce battery power.
- While using downloaded applications, check the battery charge level.

NOTE: If you accidentally press the Power/Lock Key while the device is in your pocket, the screen will turn off automatically in order to save battery power.

To check the battery power level:

- Tap  >  > Apps tab >  Settings > General tab > About phone > Battery.

The battery status (charging or discharging) and battery level (percentage charged) is displayed at the top of the screen.

To monitor and control how battery power is being used:

- Tap  >  > Apps tab >  Settings > General tab > About phone > Battery > Battery use.

Battery usage time is displayed on the screen. It tells you how long it has been since you last connected your phone to a power source or, if currently connected, how long the phone was last running on battery power. The screen shows the applications or services using battery power, listed in order from the greatest to smallest amount used.

3. Before installing an open source application and OS

WARNING

If you install and use an OS other than the one provided by the manufacturer it may cause your phone to malfunction. In addition, your phone will no longer be covered by the warranty.

WARNING

To protect your phone and personal data, only download applications from trusted sources, such as Play Store™. If there are improperly installed applications on your phone, the phone may not work normally or a serious error may occur. You must uninstall those applications and all associated data and settings from the phone.

Important notice

4. Using an unlock pattern

Set an unlock pattern to secure your phone. Tap > > **Apps** tab > **Settings** > **Display** tab > **Lock screen** > **Select screen lock** > **Pattern**. This opens a screen that will guide you through how to draw a screen unlock pattern. You have to create a Backup PIN as a safety measure in case you forget your unlock pattern.

Caution: Create a Google account before setting an unlock pattern and remember the Backup PIN you created when creating your pattern lock.

WARNING

Precautions to take when using pattern lock.

It is very important to remember the unlock pattern you set. You will not be able to access your phone if you use an incorrect pattern 5 times. You have 5 opportunities to enter your unlock pattern, PIN or password. If you have used all 5 opportunities, you can try again after 30 seconds.

When you can't recall your unlock Pattern, PIN or Password:

< If you have forgotten your pattern >

If you logged in to your Google account on the phone but failed to enter the correct pattern 5 times, tap the **Forgot pattern?** button at the bottom of the screen. You are then required to log in with your Google Account or you have to enter the Backup PIN which you entered when creating your Pattern Lock.

If you have not created a Google account on the phone or you forgot Backup PIN, you have to perform a hard reset.

< If you have forgotten your PIN or Password >

If you forget your PIN or Password, you will need to perform a hard reset.

Caution: If you perform a hard reset, all user applications and user data will be deleted.

NOTE: If you have not logged into your Google Account and have forgotten your Unlock Pattern, you will need to enter your Backup PIN.

5. Using the Hard Reset (Factory Reset)

If your phone does not restore to its original condition, use a Hard Reset (Factory Reset) to initialize it.

- 1 Turn the power off.
- 2 Press and hold the **Power/Lock key + Volume Down key** on the back of the phone.
- 3 Release the **Power/Lock Key** only when the LG logo is displayed, then immediately press and hold the **Power/Lock Key** again.
- 4 Release all keys when the Factory hard reset screen is displayed.
- 5 Press the **Power/Lock Key** to continue or either of the **Volume Keys** to cancel.
- 6 Press the **Power/Lock Key** once more to confirm or either of the **Volume Keys** to cancel.



WARNING

If you perform a Hard Reset, all user applications, user data and DRM licenses will be deleted. Please remember to backup any important data before performing a Hard Reset.

6. Opening and switching applications

Multi-tasking is easy with Android, you can keep more than one application running at the same time. There is no need to quit an application before opening another one. Use and switch between several open applications. Android manages each application, stopping and starting them as needed to ensure that idle applications don't consume resources unnecessarily.

Important notice

- 1 Touch and hold the **Home Key**  A list of recently used applications will be displayed.
 - 2 Tap the application you want to access. This does not stop the previous app running in the background on the phone. Make sure to tap **Back Key**  to exit an app after using it.
- To stop applications, tap **Task Manager** from the recent apps list, then tap **Stop** or **Stop all**.
 - To remove an app from the recent apps list, swipe the app preview to the left or right. To clear all apps, tap **Clear all**.

7. Transferring music, photos and videos using Media sync (MTP)

- 1 Tap  >  > **Apps** tab >  **Settings** > **General** tab > **Storage** to check out the storage media.
- 2 Connect the phone to your PC using the USB cable.
- 3 **Select USB connection mode** will appear on your phone screen, Select the **Media sync (MTP)** option.
- 4 Open the memory folder on your PC. You can view the mass storage content on your PC and transfer the files from PC to Device memory folder or vice versa.
- 5 After transferring files ,slide down the status bar and tap **USB connected** and select **Charge phone** from USB connection type list.

8. Hold your phone upright

Hold your cell phone vertically, as you would a regular phone. Your phone has an internal antenna. Be careful not to scratch or damage the back of the phone, as this may affect performance.

When making/receiving calls or sending/receiving data, avoid holding the lower part of the phone where the antenna is located. Doing so may affect call quality.

9. When the screen freezes

If the screen freezes or the phone does not respond when you try to operate it:

Press and hold the **Power/Lock** key for 10 seconds to turn your phone off. If it still does not work, please contact the service center.

10. Do not connect your phone when you power on/off your PC

Make sure to disconnect your phone from the PC when powering your PC on or off as it might result in PC errors.

11. Hardware key control mode


If your phone display is damaged or broken, you can answer an incoming call, end a call, or turn off an alarm using the hardware keys.

- 1 Turn your phone off.
- 2 Press and hold the **Power/Lock Key** and the **Volume Keys** at the same time for more than 6 seconds to enter the Hardware key control mode.
- 3 Press the **Volume Keys** to scroll to the desired option, then press the **Power/Lock Key** to confirm.
 - **Answer a call:** Press the **Volume Keys** at the same time.
 - **End a call:** Press the **Power/Lock Key** during a call.
 - **Stop an alarm:** When an alarm rings, press and hold the **Volume Up Key** or **Volume Down Key** to stop the alarm.

NOTE: If you use your phone with a broken display glass, your phone can break even more or you can be injured. Make sure to visit the LG authorized service center to get your phone repaired.

Getting to know your phone

Phone overview




NOTE: Proximity sensor

When receiving and making calls, the proximity sensor automatically turns the backlight off and locks the touch screen by sensing when the phone is near your ear. This extends battery life and prevents you from unintentionally activating the touch screen during calls.

⚠️ WARNING

Placing a heavy object on the phone or sitting on it can damage the LCD and touch screen functions. Do not cover the LCD proximity sensor with protective film. This could cause the sensor to malfunction.



⚠️ WARNING

- This part encloses the battery compartment. Please do not open the back cover.
- Be careful not to damage the NFC touch point on the phone, which is part of the NFC antenna.

Getting to know your phone


Installing the micro-USIM card

Before you start exploring your new phone, you may choose to insert the micro-USIM card.

The eject button is a small round aperture just above the tray door. To install a new micro-USIM card:

- 1 Insert the micro-USIM ejection tool that comes with the phone (or a thin pin) into the eject button aperture, and push gently but firmly until the tray pops out.
- 2 Remove the tray and place the micro-USIM card inside it, with the contacts out and the angled corner to the right. There is only one possible way to fit the card snugly into the tray.
- 3 Carefully reposition the tray in the slot and push it gently back into the phone.

NOTE: Make sure the gold contact area on the card is facing downwards.




Charging your phone

Charge the battery before using it for the first time. Use the charger to charge the battery. A computer can be also used to charge the device by connecting them via the USB cable.

WARNING

Use only LG-approved chargers, batteries and cables. If you use unapproved chargers, batteries or cables, it may cause battery charging delay or pop up the message regarding slow charging, Or this can cause the battery to explode or damage the device, which are not covered by the warranty.

The charger connector is at the bottom of the phone. Insert the charger and plug it into an electrical outlet.



NOTE:

- The battery must be fully charged initially to improve battery lifetime.
- Do not open the back cover while your phone is charging.

Getting to know your phone

Locking and unlocking the screen

If you do not use the phone for a while, the screen will be automatically turned off and locked. This helps to prevent accidental taps and saves battery power.

When you are not using the phone, press the **Power/Lock key**  to lock your phone.

If there are any programs running when you lock your screen, they may be still running in Lock mode. It is recommended that you exit all programs before entering Lock mode to avoid unnecessary charges (e.g. phone calls, web access and data communications).

To wake up your phone, press the **Power/Lock key** . The Lock screen will appear. Touch and slide the Lock screen in any direction to unlock your Home screen. The last screen you viewed will open.

KnockON

You can lock or unlock the screen by just double-tap.

To activate KnockON feature

- 1 Tap  >  **Settings** > **General** tab > **Gestures**.
- 2 Place a checkmark on **Screen on/off**.


Double-tap the center screen quickly to unlock the screen. To lock the screen, double-tap the status bar in any screen (except on the camera viewfinder) or empty area on the Home screen.

NOTE: When turning the screen on, make sure you do not cover the proximity sensor. Doing so will turn the screen off immediately after turning it on in order to prevent abnormal turning on in your pocket or bag.

Stereo headset with microphone

With the headset connected, you can enjoy music or video with stereo sound, and easily switch from your music/video to take and end calls.

< Front >




Volume Up/Down Buttons

Call/End Button


- For an incoming call, press to receive or end a call.
- When you listen to music, press to stop playback or resume. Press twice to play the next track.

< Back >



Microphone

- 1 Plug in the headset as shown below.



Getting to know your phone

- 2 The applications panel displays and you can select an app to run.

NOTE: You can edit the applications to display on the panel and set not to show the applications panel. Please see < Accessory >.

- 3 If a call is coming when the headset is connected to the phone, press the  to take the call.
4 To end the call, press the  again.

Plug & Pop

Plug & Pop allows you to quickly choose apps to use when plugging in an earphone or On-the-Go device, such as a mouse or keyboard.

- 1 Plug in earphone or OTG (On-the-Go) device (i.e., mouse, keyboard, etc.).
2 The applications panel will display and you can select an app to run.

NOTE: You can edit the applications to display on the panel and set not to show the applications panel.

- Tap  >  >  **Settings** > General tab > **Accessory** > **USB Storage** or **Earphone**.

Your Home screen

Touch screen tips

Here are some tips on how to navigate on your phone.

Tap or touch – A single finger tap selects items, links, shortcuts and letters on the on-screen keyboard.

Touch and hold – Touch and hold an item on the screen by tapping it and not lifting your finger until an action occurs. For example, to open a contact's available options, touch and hold the contact in the Contacts list until the context menu opens.

Drag – Touch and hold an item for a moment and then, without lifting your finger, move your finger on the screen until you reach the target position. You can drag items on the Home screen to reposition them.

Swipe or slide – To swipe or slide, quickly move your finger across the surface of the screen, without pausing when you first tap it (so you don't drag an item instead). For example, you can slide the screen up or down to scroll through a list, or browse through the different Home screens by swiping from left to right (and vice versa).

Double-tap – Double-tap to zoom on a webpage or a map. For example, quickly double-tap a section of a webpage to adjust that section to fit the width of the screen. You can also double-tap to zoom in and out while viewing the picture.

Pinch-to-Zoom – Use your index finger and thumb in a pinching or spreading motion to zoom in or out when using the browser or Maps, or when browsing pictures.

Rotate the screen – From many applications and menus, the orientation of the screen adjusts to the device's physical orientation.

NOTE:

- To select an item, tap the center of the icon.
- Do not press too hard; the tap screen is sensitive enough to pick up a light, yet firm tap.
- Use the tip of your finger to tap the option you want. Be careful not to tap any other keys.

Your Home screen

Home screen

The Home screen is the starting point for many applications and functions, and it allows you to add items like application shortcuts, or Google widgets to give you instant access to information and applications. This is the default canvas and accessible from any menu by tapping .



Status Bar

Shows phone's status information including the time, signal strength, battery status, and notification icons.

Widget

Widgets are self-contained applications that can be accessed through the Apps screen or on the Home screen or an extended home screen. Unlike a shortcut, the Widget appears as an on-screen application.

Application Icons

Tap an icon (application, folder, etc.) to open and use it.

Location Indicator

Indicates which Home screen canvas you are viewing.

Quick Key Area

Provides one-touch access to the function in any home screen canvas.

Front Touch Keys

Extended home screen

The operating system provides multiple Home screen canvases to provide more space for adding icons, widgets, and more.

- ▶ Slide your finger left or right across the Home screen.

Customizing the Home screen

You can customize your Home screen by adding apps, widgets or changing wallpapers.

To add items on your Home screen

- 1 Touch and hold the empty part of the Home screen.
- 2 In the Add Mode menu, select the item you wish to add. You will then see this added item on the Home screen.
- 3 Drag it to the desired location and lift your finger.

TIP! To add an application icon to the Home screen from the Apps menu, touch and hold the application you want to add.

To remove an item from the Home screen

- ▶ **Home screen** > touch and hold the icon you want to remove > drag it to .

To add an app as a Quick key

- ▶ From the Apps menu or on the Home screen, touch and hold an application icon and drag it to the Quick key area. Up to 7 apps can be added.

To remove an app from the Quick key area

- ▶ Touch and hold the desired quick key and drag it to .

NOTE:  Apps key cannot be removed.

To customize apps icons on the Home screen

- 1 Touch and hold an application icon until it is unlocked from its current position. Then drop it on the screen. The editing icon  will appear in the upper right corner of the application.
- 2 Tap the application icon again and select the desired icon design and size.
- 3 Tap **OK** to save the change.

Your Home screen

Returning to recently-used applications


- 1 Touch and hold . The screen displays a pop-up containing the icons of applications you used recently.
- 2 Tap an icon to open the application. Or tap  to return to your previous screen.

Notifications panel

Notifications alert you the arrival of new messages, calendar events, and alarms, as well as to ongoing events, such as when you are on a call.

When a notification arrives, its icon appears at the top of the screen. Icons for pending notifications appear on the left, and system icons such as Wi-Fi or battery strength shown on the right.

NOTE: The available options may vary depending on the region or service provider.



Opening the notifications panel

Swipe down from the status bar to open the notifications panel.



Quick Toggle Area

Tap each quick toggle key to turn it on/off. Touch and hold the key to access the settings menu of the function. To see more toggle keys, swipe left or right. Tap to remove, add, or rearrange toggle keys.

QSlide Apps

Tap a QSlide app to open as a small window on your screen. Tap to remove, add, or rearrange QSlide apps.

Tap to clear all the notifications.

Notifications

The current notifications are listed, each with a brief description. Tap a notification to view it.

To close the notifications panel, touch and drag the tab toward the top of the screen.

Indicator icons on the Status Bar

Indicator icons appear on the status bar at the top of the screen to report missed calls, new messages, calendar events, device status and more.



Your Home screen

The icons displayed at the top of the screen provide information about the status of the device. The icons listed in the table below are some of the most common ones.

Icon	Description	Icon	Description
	No SIM card inserted		Ringer is silenced
	No network signal available		Vibrate mode is on
	Airplane mode is on		Battery fully charged
	Connected to a Wi-Fi network		Battery is charging
	Wired headset connected		Phone is connected to PC via USB cable
	Call in progress		Downloading data
	Missed call		Uploading data
	Bluetooth is on		GPS is on
	NFC is on		Receiving location data from GPS
	System warning		Data is synchronizing
	An alarm is set		New Gmail message available
	New voicemail available		New Hangouts message available

	New text or multimedia message		Choose input method
	A song is currently playing		DLNA content share
	Mobile hotspot is active		DLNA music playing

NOTE: The icons location in the status bar may differ according to the function or service.

On-screen keyboard

You can enter text using the on-screen keyboard. The on-screen keyboard appears automatically on the screen when you need to enter text. To manually display the keyboard, simply tap a text field where you want to enter text.

Using the keypad & entering text

Tap once to capitalize the next letter you type. Double-tap for all caps.

abc Tap to switch to the numbers and symbols keyboard.

Tap to switch to handwriting mode.

Tap to enter a space.

Tap to create a new line.

Tap to delete the previous character.

Entering accented letters

When you select French or Spanish as the text entry language, you can enter special French or Spanish characters (e.g. "á").

For example, to input "á", touch and hold the "a" key until the zoom-in key grows bigger and displays characters from different languages.

Then select the special character you want.

Google account setup

When you first turn on your phone, you have the opportunity to activate the network, to sign into your Google Account and select how you want to use certain Google services.

To set up your Google account:

- Sign into a Google Account from the prompted set-up screen.
OR
- Tap  >  > **Apps** tab > select a Google application, such as **Gmail** > select **New** to create a new account.

If you have a Google account, tap **Existing**, enter your email address and password, then tap .

Once you have set up your Google account on your phone, your phone automatically synchronizes with your Google account on the Web.

Your contacts, Gmail messages, Calendar events and other information from these applications and services on the Web are synchronized with your phone. (This will depend on your synchronization settings.)

After signing in, you can use Gmail™ and take advantage of Google services on your phone.

Connecting to Networks and Devices

Wi-Fi

With Wi-Fi, you can use high-speed Internet access within the coverage of the wireless access point (AP). Enjoy wireless Internet using Wi-Fi, without extra charges.

Connecting to Wi-Fi networks

To use Wi-Fi on your phone, you need to access a wireless access point or ‘hotspot’. Some access points are open and you can simply connect to them. Others are hidden or use security features; you must configure your phone to be able to connect to them. Turn off Wi-Fi when you're not using it to extend the life of your battery.

NOTE: If you are out of the Wi-Fi zone or have set Wi-Fi to **OFF**, additional charges may be applied by your mobile operator for mobile data use.

Turning Wi-Fi on and connecting to a Wi-Fi network

- 1 Tap  >  > **Apps** tab >  **Settings** > **Networks** tab > **Wi-Fi**.
- 2 Set **Wi-Fi** to **ON** to turn it on and start scanning for available Wi-Fi networks.
- 3 Tap the Wi-Fi menu again to see a list of active and in-range Wi-Fi networks.
 - Secured networks are indicated by a lock icon.
- 4 Tap a network to connect to it.
 - If the network is secured, you are prompted to enter a password or other credentials. (Ask your network administrator for details)
- 5 The status bar displays icons that indicate Wi-Fi status.

Connecting to Networks and Devices

Bluetooth

You can use Bluetooth to send data by running a corresponding application, but not from the Bluetooth menu as on most other mobile phones.

NOTE:

- LG is not responsible for the loss, interception or misuse of data sent or received via the Bluetooth wireless feature.
- Always ensure that you share and receive data with devices that are trusted and properly secured. If there are obstacles between the devices, the operating distance may be reduced.
- Some devices, especially those that are not tested or approved by Bluetooth SIG, may be incompatible with your device.

Turning on Bluetooth and pairing up your phone with a Bluetooth device

You must pair your device with another device before you connect to it.

- 1 Tap  >  > Apps tab >  Settings > Networks tab > set Bluetooth to ON.
 - 2 Tap the **Bluetooth** menu again. You will see the option to make your phone visible and option to search devices. Now tap **Search for devices** to view the devices in the Bluetooth Range.
 - 3 Choose the device you want to pair with from the list.
- Once the paring is successful, your device will connect to the other device.

NOTE: Some devices, especially headsets or hands-free car kits, may have a fixed Bluetooth PIN, such as 0000. If the other device has a PIN, you will be asked to enter it.

Send data using the Bluetooth wireless feature

- 1 Select a file or item, such as a contact, calendar event or media file, from an appropriate application or from **Downloads**.
- 2 Select the option for sending data via Bluetooth.

NOTE: The method for selecting an option may vary by data type.

- 3 Search for and pair with a Bluetooth-enabled device.

Receive data using the Bluetooth wireless feature

- 1 Tap > > **Apps** tab > **Settings** > **Networks** tab > set **Bluetooth** to **ON**.
- 2 Tap the **Bluetooth** menu again and mark the checkbox at the top of the screen to visible on other devices.

NOTE: To select the length of time that your device will be visible, tap > **Visibility timeout**.

- 3 Select **Accept** to confirm that you are willing to receive data from the device.

Sharing your phone's data connection

USB tethering and portable Wi-Fi hotspot are great features when there are no wireless connections available. You can share your phone's mobile data connection with a single computer via a USB cable (USB tethering). You can also share your phone's data connection with more than one device at a time by turning your phone into a portable Wi-Fi hotspot.

When your phone is sharing its data connection, an icon appears in the status bar and as an ongoing notification in the notifications drawer.

For the latest information about tethering and portable hotspots, including supported operating systems and other details, visit <http://www.android.com/tether>.

Connecting to Networks and Devices

To share your phone's data connection as a portable Wi-Fi hotspot

- 1 Tap  >  > Apps tab >  Settings > Networks tab > Tethering & networks > Wi-Fi hotspot switch to activate.
- 2 Enter a password and tap **Save**.

TIP! If your computer is running Windows 7 or a recent distribution of some flavours of Linux (such as Ubuntu), you will not usually need to prepare your computer for tethering. But, if you are running an earlier version of Windows or another operating system, you may need to prepare your computer to establish a network connection via USB. For the most current information about which operating systems support USB tethering and how to configure them, visit <http://www.android.com/tether>.

To rename or secure your portable hotspot

You can change the name of your phone's Wi-Fi network name (SSID) and secure its Wi-Fi network.

- 1 Tap  >  > Apps tab >  Settings > Networks tab > Tethering & networks > Wi-Fi hotspot.
- 2 Tap **Set up Wi-Fi hotspot**.
 - The **Set up Wi-Fi hotspot** dialogue box will open.
 - You can change the **Network SSID** (name) that other devices see when scanning for Wi-Fi networks.
 - You can also tap the **Security** menu to configure the network with Wi-Fi Protected Access 2 (WPA2) security using a pre-shared key (PSK).
 - If you touch the **WPA2 PSK** security option, a password field is added to the **Set up Wi-Fi hotspot** dialogue box. If you enter a password, you will need to enter that password when you connect to the phone's hotspot with a computer or other device. You can set **Open** in the **Security** menu to remove security from your Wi-Fi network.
- 5 Tap **Save**.

ATTENTION! If you set the security option as Open, you cannot prevent unauthorised usage of online services by other people and additional charges may be incurred. To avoid unauthorized usage, you are advised to keep the security option active.

Wi-Fi Direct

Wi-Fi Direct supports a direct connection between Wi-Fi enabled devices without an access point. Due to the high battery usage of Wi-Fi direct, it is recommended that you plug your phone into a power outlet while using the Wi-Fi Direct feature. Check your Wi-Fi & Wi-Fi Directed network in advance and make sure the users are connected to the same network.

To turn on Wi-Fi Direct:

- 1 Tap the **Menu Key**  > **System settings** > **Wi-Fi**.
- 2 Tap  **Wi-Fi Direct** at the bottom of the screen.
- 3 Select a device to connect with from the scanned device list.

Using SmartShare

SmartShare uses DLNA (Digital Living Network Alliance) technology to share digital content through a wireless network. Both devices must be DLNA certified to support this feature. You can enjoy SmartShare feature on Gallery, Music, Video, and Polaris Office.

- 1 On the content you want to play or beam, tap .
- 2 Tap **Play** or **Beam** in the dialog box.
 - **Play:** You can stream your content via TV, Bluetooth speaker, etc.
 - **Beam:** You can send your content to Bluetooth devices or SmartShare Beam*- supported LG phones or tablets.

*SmartShare Beam quickly transfers multimedia contents through Wi-Fi Direct.

- 3 Tap the device to play or receive on the list.

Connecting to Networks and Devices

- If the device is not on the list, make sure on the device that Wi-Fi, Wi-Fi Direct, or Bluetooth connection is turned on. And tap **Rescan**.

4 Tap **Send**.

To enjoy content from nearby devices such as a computer or mobile device on your phone

- To connect the nearby devices to your phone, tap **Nearby devices** on **Gallery**, **Music**, or **Video** application as below.


<Gallery>



<Music>



<Video>



- Ensure that your phone and nearby devices are connected to the same Wi-Fi network.
- Make sure DLNA feature on the nearby device is turned on.

2 Tap the device to connect.

If the device is not on the list, tap **Search nearby devices**.

After connection, you can enjoy the contents from the nearby device on your phone.

PC connections with a USB cable

Learn to connect your device to a PC with a USB cable in USB connection modes.

Transferring music, photos and videos using the USB mass storage mode

- 1 Connect your phone to a PC using a USB cable.
- 2 If you haven't installed the LG Android Platform Driver on your PC, you will need to manually change the settings. Choose **System settings > General tab > PC connection > Select USB connection method**, then select **Media sync (MTP)**.
- 3 You can now view the mass storage content on your PC and transfer the files.

Synchronize with Windows Media Player

Ensure that Windows Media Player is installed on your PC.

- 1 Use the USB cable to connect the phone to a PC on which Windows Media Player has been installed.
 - 2 Select the **Media sync (MTP)** option. When connected, a pop-up window will appear on the PC.
 - 3 Open Windows Media Player to synchronize music files.
 - 4 Edit or enter your device's name in the pop-up window (if necessary).
 - 5 Select and drag the music files you want to the sync list.
 - 6 Start synchronization.
- The following requirements must be satisfied to synchronize with Windows Media Player.

Items	Requirement
OS	Microsoft Windows XP SP2, Vista or higher
Window Media Player version	Windows Media Player 10 or higher

- If the Windows Media Player version is lower than 10, install version 10 or higher.

Calls

Making a call

- 1 Tap  to open the keypad.
- 2 Enter the number using the keypad. To delete a digit, tap the .
- 3 Tap  to make a call.
- 4 To end a call, tap the **End** icon .

TIP! To enter "+" to make international calls, touch and hold .

Calling your contacts

- 1 Tap  to open your contacts.
- 2 Scroll through the contact list or enter the first few letters of the contact you want to call by tapping **Search contacts**.
- 3 In the list, tap  you want to call.

Answering and rejecting a call

When you receive a call in Lock state, swipe the  in any direction to Answer the incoming call.

Swipe the  in any direction to Decline an incoming call.

Swipe the **Decline with message** icon from the bottom if you want to send a message.

TIP! Decline with message

You can send a message quickly using this function. This is useful if you need to reject a call with message during a meeting.

Adjusting the in-call volume

To adjust the in-call volume during a call, use the Volume up and down keys on the left-hand side of the phone.

Making a second call

- 1 During your first call, tap **Menu key**  > **Add call** and dial the number. You can also go to the recently dialled numbers list by tapping  or can search contacts by tapping  and selecting the contact you want to call.
- 2 Tap  to make the call.
- 3 Both calls are displayed on the call screen. Your initial call is locked and put on hold.
- 4 Tap the displayed number to toggle between calls. Or tap  **Merge calls** to start a conference call.
- 5 To end active calls, tap **End** or tap  and slide the notification bar down and select the **End call** icon .

NOTE: You are charged for each call you make.

Viewing your call logs

On the Home screen, tap  and choose the **Call logs** tab .

View a complete list of all dialled, received and missed calls.

TIP!

- Tap any call log entry to view the date, time and duration of the call.
- Tap the **Menu key** , then tap **Delete all** to delete all the recorded items.

Call settings

You can configure phone call settings such as call forwarding, as well as other special features offered by your carrier.

- 1 On the Home screen, tap .
- 2 Tap .
- 3 Tap **Call settings** and choose the options that you wish to adjust.

Contacts

Add contacts to your phone and synchronize them with the contacts in your Google account or other accounts that support contact syncing.

Searching for a contact

On the Home screen

- 1 Tap  to open your contacts.
- 2 Tap **Search contacts** and enter the contact name using the keyboard.

Adding a new contact

- 1 Tap , enter the new contact's number, then tap the **Menu key** . Tap **Add to Contacts > New contact**.
- 2 If you want to add a picture to the new contact, tap the image area. Choose from **Take photo** or **Select from Gallery**.
- 3 Select the contact type by tapping .
- 4 Tap a category of contact information and enter the details about your contact.
- 5 Tap **Save**.

Favourites contacts

You can classify frequently called contacts as favourites.

Adding a contact to your favourites

- 1 Tap  to open your contacts.
- 2 Tap a contact to view its details.
- 3 Tap the star to the right corner of the contact's name. The star will turn yellow color.

Contacts

Removing a contact from your favourites list

- 1 Tap  to open your contacts.
- 2 Tap the  tab, and choose a contact to view its details.
- 3 Tap the yellow color star to the right corner of the contact's name. The star turns grey color and the contact is removed from your favourites.

Creating a group

- 1 Tap  to open your contacts.
- 2 Tap **Groups** and tap the **Menu key** . Select **New group**.
- 3 Enter a name for the new group. You can also set a ringtone for the newly created group.
- 4 Tap **Save** to save the group.

NOTE: If you delete a group, the contacts assigned to that group will not be lost. They will remain in your contacts.

Messaging

Your phone combines SMS and MMS into one intuitive, easy-to-use menu.

Sending a message

- 1 Tap  on the Home screen and tap  to open a blank message.
- 2 Enter a contact name or contact number in the **To** field. As you enter the contact name, matching contacts will appear. You can tap a suggested recipient. You can add more than one contact.

NOTE: You will be charged for a text message for every person to whom you send the message.

- 3 Tap the **Enter message** field and begin composing your message.
- 4 Tap  to open the Options menu. Choose from **Quick message**, **Insert smiley**, **Schedule sending**, **Add subject** and **Discard**.

TIP! You can tap the  icon to attach the file, that you want to share with message.

- 5 Tap **Send** to send your message.
- 6 Responses will appear on the screen. As you view and send additional messages, a message thread is created.

WARNING:

- The 160-character limit may vary from country to country, depending on the language and how the SMS is coded.
- If an image, video or audio file is added to an SMS message, it is automatically converted into an MMS message and you are charged accordingly.

Messaging

Threaded box

Messages (SMS, MMS) exchanged with another party can be displayed in chronological order so that you can conveniently see an overview of your conversation.

Changing your message settings

Your phone message settings are pre-defined, so you can send messages immediately. You can change the settings according to your preferences.

- Tap the **Messaging** icon on the Home screen, tap  and then tap **Settings**.

E-mail

You can use the E-mail application to read emails from services like Gmail. The E-mail application supports the following account types: POP3, IMAP and Exchange.

Your service provider or system administrator can provide you with the account settings you need.

Managing an email account

The first time you open the **E-mail** application, a set-up wizard opens to help you to set up an email account.

After the initial set-up, E-mail displays the contents of your inbox.

To add another email account:

- Tap  >  > Apps tab > **E-mail** > tap  > **Settings** > .

To change an email account's settings:

- Tap  >  > Apps tab > **E-mail** > tap  > **Settings** > **General settings**.

To delete an email account:

- Tap  >  > Apps tab > **E-mail** > tap  > **Settings** > tap  > **Remove account** > Select the account to delete > **Remove** > select **Yes**.

Working with account folders

Tap  >  > Apps tab > **E-mail** > tap  and select **Folders**.

Each account has an Inbox, Outbox, Sent and Drafts folder. Depending on the features supported by your account's service provider, you may have additional folders.

Composing and sending email

To compose and send a message

- 1 While in the E-mail application, tap the 
- 2 Enter an address for the message's intended recipient. As you enter text, matching addresses will be proposed from your Contacts. Separate multiple addresses using semicolons.
- 3 Tap the  to add a Cc/Bcc and tap  to attach files, if required.
- 4 Enter the text of the message.
- 5 Tap .

TIP! When a new email arrives in your Inbox, you will be notified by a sound or vibration.

Camera

With the OIS (Optical Image Stabilizer) camera on the phone, you can take a clearer picture by removing physical shaking. The Multi Point AF (Autofocus) feature enables you to get a clearer and natural picture even if the objects are not in the center.

To open the Camera application, tap **Camera**  on the Home screen.

Getting to know the viewfinder



- ① **Flash** – Choose from Off , On , Auto .
- ② **Swap camera** – Switch between the rear-facing camera lens and the front-facing camera lens.
- ③ **Shot mode** – Choose from **Normal**, **Shot & Clear**, **Dynamic tone (HDR)**, **Panorama**, **VR panorama**, **Burst shot**, **Beauty shot**, **Dual camera**, **Time catch shot**, **Intelligent auto**, **Sports** or **Night**.
- ④ **Settings** – Tap this icon to open the settings menu.
- ⑤ **Video mode** – Tap and slide down this icon to switch to video mode.
- ⑥ **Capture button**
- ⑦ **Gallery** – Tap to view the last photo you captured. This enables you to access your gallery and view saved photos while in camera mode.

NOTE: Please ensure the camera lens is clean before taking pictures.

Camera

Using the advanced settings

In the viewfinder, tap  to open the advanced options. You can change the camera settings by scrolling through the list. After selecting the option, tap .

	To take a photo, say one of the following words: Cheese, Smile, Whisky, Kimchi or LG.
	Defines and controls the amount of sunlight entering the photo.
	Tap to select the focus mode.
	Selects photo resolution. If you choose high resolution, file size will increase, which means you will be able to store fewer photos in the memory.
	The ISO rating determines the sensitivity of the camera's light sensor. The higher the ISO, the more sensitive the camera. This is useful in darker conditions when you cannot use the flash.
	Improves color quality in various lighting conditions.
	Applies artistic effects to your pictures.
	Sets a delay after the capture button is pressed. This is ideal if you want to be in the photo.
	Activate this to use your phone's location-based services. Take pictures wherever you are and tag them with the location. If you upload tagged pictures to a blog that supports Geotagging, you can see the pictures displayed on a map. NOTE: This function is only available when the GPS function is active.
	Selects a shutter sound.
	Set the Volume Key whether to use for the capture or zoom.

	Opens the help guide to know how a function operates.
	Restores all camera default settings.

TIP!

- When you exit the camera, some settings return to their defaults, such as white balance, color effect, timer and shot mode. Check these before you take your next photo.
- The setting menu is superimposed over the viewfinder, so when you change photo color or quality elements, you will see a preview of the changed image behind the Settings menu.

Taking a quick photo

- Open the **Camera** application and point the lens toward the subject you want to photograph.
- Focus boxes will appear in the center of the viewfinder screen. You can also tap anywhere on the screen to focus on that spot.
- When the focus box turns green, the camera has focused on your subject.
- Tap to capture the photo.

Using Shot & Clear mode

This feature allows the camera to identify objects you may not want in your photo. After taking the photo, tap an outlined object* to remove it, then save the photo.

- Open the Camera application.
- Tap > **Shot & Clear**.
- Tap to take a picture.

Camera

4 Tap any of the outlined objects to remove them from the photo, then tap .

* When taking a picture, moving objects are shown as dashed lines.

NOTES

- Take a picture after fixing the camera in one place.
- If the color of a subject is similar to the background, only a part may be detected or it may be difficult to erase.
- If a moving subject is too small or too large, it may be difficult to erase.
- If the subject is moving insignificantly, it may not be detected.

Using Dual camera mode

Allows you to take a picture with the front and rear cameras at the same time, combined into one picture.

1 Open the **Camera** application.

2 Tap  >  **Dual camera**.

3 A small viewfinder box appears on the main viewfinder screen. Set up your shot.

- Drag the small viewfinder to move it where you want it in the shot.
- Touch and hold the small viewfinder to resize it, if necessary.
- Tap the small viewfinder to swap the lens between the main viewfinder and the small viewfinder.

4 Tap  to take the combined picture.

Using Time catch shot mode

Sets the camera to capture missing moments by taking five sequential pictures before  is tapped.

1 Open the **Camera** application.

2 Tap  >  **Time catch shot**.

- 3 Tap  to take a picture.
- 4 To view the moments just before the picture was taken, tap the image thumbnail at the bottom of the Camera screen.
- 5 Select the pictures that you want to keep, then tap  at the top of the screen.

Once you've taken a photo

Tap the image thumbnail at the bottom of the Camera screen to view the last photo you took.

	Tap to share your photo using the SmartShare function.
	Tap to take another photo immediately.
	Tap to send your photo to others or share it via social network services.
	Tap to delete the photo.

TIP! If you have an SNS account and set it up on your phone, you can share your photo with your SNS community.

NOTE: Additional charges may apply when MMS messages are downloaded while roaming.

Tap the **Menu key**  to open all advanced options.

Set image as – Tap to use the photo as a **Contact photo**, **Home screen wallpaper** or **Lock screen wallpaper**.

Move – Tap to move the photo to another place.

Copy – Tap to copy the selected photo and save it to another album.

Copy to Clip Tray – Tap to copy the photo and store in the Clip Tray.

Camera

Rename – Tap to edit the name of the selected photo.

Rotate left/right – To rotate left or right.

Crop – Crop your photo. Move your finger across the screen to select the area to be cropped.

Edit – View and edit the photo.

Slideshow – Automatically shows you the images in the current folder one after the other.

Add location – To add the location information.

Details – Find out more information about the file.

From your Gallery

Tap  **Gallery** and select **Camera**.

- To view more photos, scroll left or right.
- To zoom in or out, double-tap the screen or place two fingers and spread them apart (move your fingers closer together to zoom out).

Video camera

Getting to know the viewfinder



- ① **Flash** – Choose from Off , On , Auto .
- ② **Swap camera** – Switch between the rear-facing camera lens and the front-facing camera lens.
- ③ **Recording mode** – Choose from Normal, Live effect, Dual recording, or Tracking zoom.
- ④ **Settings** – Tap this icon to open the settings menu.
- ⑤ **Camera mode** – Tap and slide up this icon to switch to camera mode.
- ⑥ **Start recording**
- ⑦ **Gallery** – Tap to view the last video you recorded. This enables you to access your gallery and view your saved videos while in video mode.

TIP!

When recording a video, place two fingers on the screen and pinch to use the Zoom function.

Video camera

Using the advanced settings

Using the viewfinder, tap  to open all the advanced options.

	Tap to turn on Audio zoom feature. You can record only the sound you want clearly and loudly. After turning this on, focus the subject you want to zoom, on inside the blue circle. To zoom in on sounds as well as sight, pinch in.
NOTES	<ul style="list-style-type: none">Only available in landscape view.Do not cover the microphones on both sides.
	Tap to set the size (in pixels) of the video you are recording.
	Defines and controls of the amount of sunlight entering the lens. Slide the brightness indicator along the bar towards “-” for a lower brightness video or towards “+” for a higher brightness video.
	Improves color quality in various lighting conditions.
	Choose a colour tone to use for your new view.
	Activate this to use your phone's location-based services.
	Set the Volume Key whether to use for the record or zoom.
	Opens the help guide to know how a function operates.
	Restores all camera default settings.

Recording a quick video

- 1 Open the **Camera** application and slide the **Video mode** button.
- 2 The video camera viewfinder appears on the screen.
- 3 Holding the phone, point the lens towards the subject you wish to capture in your video.
- 4 Tap  once to start recording.
- 5 A red light will appear at the top left corner of the viewfinder with a timer showing the length of the video.
- 6 Tap  on the screen to stop recording.

TIP!

 – Tap to capture image during recording a video.

 – Tap to pause during recording a video.

After recording a video

In the viewfinder, tap the video thumbnail at the bottom of the screen to view the last video you took.

	Tap to share your video using the SmartShare function.
	Tap to record another video immediately.
	Tap to send your video to others or share it via social network services.
	Tap to delete the video.

NOTE: Additional charges may apply when MMS messages are downloaded while roaming.

Video camera

From your Gallery

Tap  **Gallery** and select **Camera**. Tap on video play icon  to play the video.

Adjusting the volume when viewing a video

To adjust the volume of a video while it is playing, use the volume keys on the left side of the phone.

Using Audio Zoom

Focuses the audio recording on a particular area of your choosing; this will increase microphone sensitivity and reduce background noise.

- 1 Open the **Camera** application and change to video mode
- 2 Tap  >  **Audio zoom** and select **On**.
- 3 Tap an empty space on viewfinder to close the Setting pop-up window.
- 4 Hold the phone horizontally and tap  to start recording.
- 5 Focus the subject you want to zoom in on inside the blue circle. Then, pinch to zoom in to increase sound sensitivity and decrease noise.
- 6 Tap  to stop recording.

NOTES

- Do not cover the side microphones while using this feature.
- You must record in landscape orientation to use this function.

Using Dual recording mode

Allows you to record videos with the front and rear cameras at the same time, combined into one recording.

- 1 Open the **Camera** application and change to video mode
- 2 Tap  **Dual recording**.
- 3 A small viewfinder box appears on the main viewfinder screen. Set up your shot.
 - Drag the small viewfinder to move it where you want it in the shot.
 - Touch and hold the small viewfinder to resize it, if necessary.
 - Tap the small viewfinder to swap the lens between the main viewfinder and the small viewfinder.
- 4 Tap  to start dual recording.
- 5 Tap  to stop dual recording.

Using Tracking zoom mode


Allows you to define an area of the recording to focus on and enlarge. You can set the area before recording, then move it as necessary during the recording.

- 1 Open the **Camera** application and change to video mode
- 2 Tap  **Tracking zoom**.
- 3 Drag the magnifying glass to the area to enlarge. The small screen shows the defined focus in large view.
- 4 Tap  to start recording.
- While recording, you can move the small screen. Touch and drag it to the desired location.
- 5 Tap  to stop recording.


Function

QuickMemo

The **QuickMemo** allows you to create memos and capture screen shots. Capture screens, draw on them and share them with family and friends with QuickMemo.




OR




- 1 (While screen is switched off) Press and hold the Volume Up key.

OR

- 2 Touch and slide the status bar downward and tap .



- 2 Select the desired menu option from **Pen type**, **Colour**, **Eraser** and create a memo.



- 3 Tap in the Edit menu to save the memo with the current screen. To exit QuickMemo at any time, tap .

NOTE: Please use a fingertip while using the QuickMemo. Do not use your fingernail.

Using the QuickMemo options

You can easily use the QuickMenu options when using the QuickMemo.

	Tap to keep the current QuickMemo as a text overlay on the screen and continue to use the phone.
	Selects whether to use the background screen or not.
	Undo or Redo.
	Selects the pen type and the colour.
	Erases the memo that you created.
	Tap to share the memo with others via any of the available applications.
	Saves the memo with the current screen in the Gallery or Notebook .

Viewing the saved QuickMemo


Tap **Notebook/Gallery** and select the QuickMemo album.

Function

QuickTranslator

Simply aim the camera of your smart phone at the foreign sentence you want to understand. You can get the real-time translation anywhere and anytime.

You can buy additional dictionaries for offline translation from the Google Play Store.



- ① Home language.
- ② Destination language.
- ③ Translation of word.
- ④ Translation of sentence.
- ⑤ Translation of block.
- ⑥ Flash.



- 1 Tap > > Apps tab > **QuickTranslator**.
- 2 Tap **Word, Line or Block**.
- 3 Tap and select the desired language.
- 4 Hold the phone toward the subject you want to translate for a few seconds.

NOTE: Only one dictionary is provided free of charge. Additional dictionaries must be purchased. Please select from the list below the dictionary you would like to install as your complimentary dictionary.

NOTE: There may be a difference in the rate of recognition depending on the size, font, color, brightness and angle of the letters that need to be translated.

QSlide

From any screen, bring up a notepad, calendar, and more as a window inside your screen.



1	[Icon: close window]	Tap to exit the QSlide and return to full window.
2	[Icon: transparency bar]	Tap to adjust transparency.
3	[Icon: end slide]	Tap to end the QSlide.
4	[Icon: size corner]	Tap to adjust the size.


- 1 Touch and slide the status bar downwards > tap QSlide apps or while using applications that support QSlide, tap [Icon: window]. The function will be continuously displayed as a small window on your screen.
- 2 You can make a call, browse the Web, or choose other phone options. You can also use and tap the screen under the small windows when the transparency bar is not full [Icon: transparency bar].

NOTE: The QSlide can support up to two windows at the same time.

Function

QuickRemote

QuickRemote turns your phone into a Universal Remote for your home TV, Set top box, audio system, DVD/Blu-ray players, air conditioner and projector.



- 1 Touch and slide the status bar downwards and tap > ADD REMOTE.

OR

Tap > > Apps tab > QuickRemote > tap .

- 2 Select the type and brand of device, then follow the on-screen instructions to configure the device(s).

- 3 Touch and slide the status bar downwards and use QuickRemote functions.

Tap the Menu key to select Magic Remote setting, Edit remote name, Learn remote, Move remote, Delete remote, Edit room, Settings and Help.

NOTE: The QuickRemote operates the same way as an ordinary remote control infrared (IR) signals. Be careful not to cover the infrared sensor at the top of the phone when you use the QuickRemote function. This function may not be supported depending on the model, the manufacturer or service company.

Zoom to Track

When you play a video, you can enlarge an object while tracking it.

- 1 When you play a video, tap
- 2 Touch the magnifying glass and drag it to the object to track.



Function

NOTE:

- While a video is playing, slide the screen up or down to adjust the screen brightness.
- While playing a video, slide the screen left or right to rewind or fast-forward.
- Do not press too hard; the touch screen is sensitive enough to pick up a light, but firm tap.
- Zoom to Track may not be available if the object moves too fast or off from the screen.

VuTalk

With the VuTalk feature, you can make an interactive and more creative notes with the other party. Visual communication is possible while sharing a photo, a map or camera preview.

NOTE:

- Only available with a phone that supports this feature as well.
- You can also use the VuTalk feature during a call.
- The screen will lock if there is no input.
- Requires data connection. Data charge will apply to both phones.

Register VuTalk Before Use

1 Tap  >  Contacts > .

You can also register VuTalk service while you are in a call.

2 Read the LG apps terms and conditions and privacy policy. If you agree, tap the check boxes, then tap **Accept**.

VuTalk Settings

- 1 Tap  >  Contacts >  VuTalk settings .
- 2 Set the following options as your preferences.
 - **Notification sound:** Select the desired notification sound.
 - **Vibrate:** Select the desired vibrate type.
 - **Show request popup:** Checkmark this option to display a pop-up when a VuTalk request is received.
 - **Contact sync:** Checkmark this option to sync contacts.

Communicate Visually with VuTalk

- 1 Tap  >  Contacts > .
- Only the contacts who use the VuTalk feature will be displayed.
- 2 Tap a contact to start VuTalk with.
- 3 In the contact's details screen, tap  . After the other party accepts your VuTalk request, you can start VuTalk with him/her.
- 4 Use the VuTalk screen to chat and visually communicate with your friend.
 - Tap  to attach a photo, take a new photo, map view, or a sticker.
 - Tap the Pen icon  and Eraser  icon to write on the images you attached.
- 5 When you finish VuTalk, tap  or to exit the VuTalk feature.
The created VuTalk screen is stored in the **Notebook** app.

NOTE: If you tap  and go back to the Home screen, the VuTalk feature still runs in the background.

Function

Voice Mate

Voice Mate allows you hands-free interaction with your devices. You can ask Voice Mate to perform phone functions using your voice, such as calling a contact, setting alarms or searching the web. When you access this feature for the first time, it displays help information to assist you in learning how to use this function.

NOTE:

- You can use Voice Mate after agreeing the End User License Agreement and Privacy policy.
- You can view examples of various commands by swiping the Voice Mate main screen to the left.
- You can also launch Voice Mate using the Quick Access feature.

Use Voice Mate

- 1 Tap  >  >  **Voice Mate**.
- 2 Tap  to turn it on. Say what you want it to do for you.

TIP! Use Voice Mate in a quiet environment so it can accurately recognize your commands.

Voice Mate Settings

- 1 Tap  >  >  **Voice Mate**.
- 2 Tap  > **Settings** to configure the environment settings.

LG SmartWorld

LG SmartWorld offers an assortment of exciting content - games, applications, wallpaper and ringtones - giving LG phone users the chance to enjoy richer "Mobile Life" experiences.

How to Get to LG SmartWorld from Your Phone

- 1 Tap  >  > Apps tab > tap the  icon to access **LG SmartWorld**.
- 2 Tap Sign in and enter ID/PW for LG SmartWorld. If you have not signed up yet, tap Register to receive your LG SmartWorld membership.
- 3 Download the content you want.

NOTE: What if there is no icon?

- 1 Using a mobile Web browser, access LG SmartWorld (www.lgworld.com) and select your country.
- 2 Download the LG SmartWorld App.
- 3 Run and install the downloaded file.
- 4 Access LG SmartWorld by tapping the  icon.

How to use LG SmartWorld

- Participate in monthly LG SmartWorld promotions.

	Search content.
	Find content by category (e.g. Games, Education, Entertainment etc).
	List of downloaded/to-be updated content.

- Try the easy "Menu" buttons to find what you're looking for fast.

Apps for you – Recommended content based on your previous choices.

Settings – Set Profile and Display.

Sign in – Set your ID and Password.

Function

- Try other useful functions as well. (Content Detail screen)

NOTE: LG SmartWorld may not be available from all carriers or in all countries.

On-Screen Phone

On-Screen Phone allows you to view your mobile phone screen from a PC via a USB or Wi-Fi connection. You can also control your mobile phone from your PC, using the mouse or keyboard.

On-Screen Phone icons

	Connects your mobile phone to your PC, or disconnects it.
	Changes the On-Screen Phone preferences.
	Exits the On-Screen Phone programme.
	Maximises the On-Screen Phone window.
	Minimize the On-Screen Phone window.

On-Screen Phone features

- Real-time transfer and control: displays and controls your mobile phone screen when connected to your PC.
- Mouse control: allows you to control your mobile phone by using the mouse to click and drag on your PC screen.
- Text input with keyboard: allows you to compose a text message or note using your computer keyboard.

- File transfer (mobile phone to PC): sends files from your mobile phone (e.g. photos, videos, music and Polaris Office files) to your PC. Simply right-click on the file which you want to send to PC and click on "Save to PC".
- File transfer (PC to mobile phone): sends files from your PC to your mobile phone. Just select the files you wish to transfer and drag and drop them into the On-Screen Phone window. The files sent are stored in internal SD card.
- Real-time event notifications: prompts a pop-up to inform you of any incoming calls or text/multimedia messages.

How to install On-Screen Phone on your PC

- 1 Visit LG Home (WWW.LG-MOBILE.CO.IL) and select a country of your choice.
- 2 Go to **Support > Mobile Phone Support** > Select the Model (LG-D802) > Click **OSP** (On-Screen Phone) to download. You can install the On-Screen Phone on your PC.

Gallery

Open the **Gallery** application to view albums of your pictures and videos.

- 1 Tap  >  > Apps tab >  **Gallery**.

You can manage and share all your image and video files with Gallery.

NOTE:

- Some file formats are not supported, depending on the software installed on the device.
- Some files may not play properly, depending on how they are encoded.

Viewing pictures

Launching Gallery displays your available folders. When another application, such as Email, saves a picture, the download folder is automatically created to contain the picture. Likewise, capturing a screenshot automatically creates the Screenshots folder. Select a folder to open it.

Pictures are displayed by creation date in a folder. Select a picture to view it full screen. Scroll left or right to view the next or previous image.

Zooming in and out

Use one of the following methods to zoom in on an image:

- Double-tap anywhere to zoom in.
- Spread two fingers apart on any place to zoom in. Pinch to zoom out, or double-tap to return.

Playing videos

Video files show the  icon in the preview. Select a video to watch it and tap  . The Videos application will launch.

Editing photos

When viewing a photo, tap the **Menu key**  > **Edit**.

Deleting photos/videos

Use one of the following methods:

- In a folder, tap  and select photos/videos by ticking, and then tap on **Delete**.
- When viewing a photo/Video, tap .

Setting as wallpaper

When viewing a photo, tap the **Menu key**  > **Set image as** to set the image as wallpaper or assign to a contact.

NOTE:

- Some file formats are not supported, depending on the device software.
- If the file size exceeds the available memory, an error can occur when you open files.

Videos

Your phone has a built-in video player that lets you play all of your favorite videos. To access the video player, tap  >  > **Apps tab** >  **Videos**.

Multimedia

Playing a video

- 1 Tap  >  > Apps tab > Videos.
- 2 Select the video you want to play.

	Tap the desired direction for audio zoom.
	Tap to use Zoom to Track feature.
	Tap to enter into Qslide mode.
	Tap to share your video via the SmartShare function.
	Tap to lock a video screen.
	Tap to view the video list.
	Tap to pause video playback.
	Tap to resume video playback.
	Tap to go 10 seconds forward.
	Tap to go 10 seconds backward.
	Tap to manage the video volume.
	Tap to change the ratio of the video screen.

To change the volume while watching a video, press the up and down volume keys on the rear side of the phone.

Touch and hold a video in the list. The **Share**, **Delete**, **Trim** and **Details** options will be displayed.


Video Editor

You can edit the photos or videos stored on the phone.

- ▶ Tap > > Apps tab > Video Editor.

NOTE: Video Editing function is supported only for photos or videos which recorded with this phone.

< Project list screen >



	Create a new project.
	Share the video project with other applications, such as YouTube.
	Export the finished project to play in other applications.
	Delete the video project.
	View the help information.

Multimedia

< Project edit screen >



	Tap to view the Project list screen.
	Tap to play the current clip.
	Tap to remove the last selected clip.
	Tap to add additional video clips.
	Tap to choose to video style.
	Tap to choose to video style.
	Tap to choose to video style.

Music

Your phone has a built-in music player that lets you play all your favorite tracks. To access the music player, tap > > Apps tab > Music.

Add music files to your phone

Start by transferring music files to your phone:

- Transfer music using Media sync (MTP).
- Download from the wireless Web.

- Synchronize your phone to a computer.
- Receive files via Bluetooth.

Transfer music using Media sync (MTP)

- 1 Connect the phone to your PC using the USB cable.
- 2 Select the **Media sync (MTP)** option. Your phone will appear as another hard drive on your computer. Click on the drive to view it. Copy the files from your PC to the drive folder.
- 3 When you're finished transferring files, swipe down on the Status Bar and tap **USB connected > Charge phone**. You may now safely unplug your device.

Playing a song

1 Tap  >  > Apps tab > Music.

2 Tap Songs.

3 Select the song you want to play.

	Tap to pause playback.
	Tap to resume playback.
	Tap to skip to the next track in the album, playlist, or shuffle. Touch and hold to fast forward.
	Tap to restart the current track or skip to the previous track in the album, playlist, or shuffle. Touch and hold to rewind.
	Tap to display the Volume slider bar, then adjust the playback volume on the slider bar.
	Tap to set audio effects.
	Tap to find the files with YouTube.
	Tap to open the current playlist.

Multimedia

	Tap to add the song to your favourites.
	Tap to play the current playlist in shuffle mode (tracks are played in random order).
	Tap to toggle through the repeat modes to repeat all songs, repeat current song, or repeat off.
	Tap to share your music via the SmartShare function.

To change the volume while listening to music, press the up and down volume keys on the back side of the phone.

Touch and hold any song in the list. The **Play**, **Add to playlist**, **Share**, **Set music as**, **Delete**, **Details** and **Search** options will be displayed.

NOTE:

- Some file formats are not supported, depending on the device software.
- If the file size exceeds the available memory, an error can occur when you open files.

NOTE: Music file copyrights may be protected by international treaties and national copyright laws.

Therefore, it may be necessary to obtain permission or a licence to reproduce or copy music.

In some countries, national laws prohibit private copying of copyrighted material. Before downloading or copying the file, check the national laws of the relevant country concerning the use of such material.

Utilities

Slide Aside (Quick task-switching with THREE fingers)

You can quickly switch to another task using three fingers.

- 1 Place three fingers on the screen which you are currently working on and slide the screen to the left. The current screen is saved and you can do another task.
- You can save up 3 (three) apps in the left side of the screen.
- 2 To reopen the saved screen and continue to use the app, place three fingers on a screen and slide it to the right.

NOTE: Please be careful not to place another fingers or palm on the screen.

Guest Mode

To protect your privacy or limit some applications to your children, you can use the Guest mode.

When you lend your phone to others, you can limit the applications to be displayed. In advance, set the Guest mode and customize the options.

NOTE: To use the Guest mode, the pattern lock should be set in advance.

- 1 Tap  >   Settings > General tab > Guest mode.
- 2 Tap Use Guest mode to place a checkmark.

Setting your alarm

- 1 Tap  >  Apps tab > Alarm/Clock > .
- 2 After you set the alarm, your phone lets you know how much time is left before the alarm will go off.
- 3 Set Repeat, Snooze duration, Vibration, Alarm sound, Alarm volume, Auto app starter, Puzzle lock and Memo. Tap Save.

Utilities

NOTE: To change alarm settings in the alarm list screen, tap the **Menu key**  and select **Settings**.

Using your calculator

- 1 Tap  >  > Apps tab > **Calculator**.
- 2 Tap the number keys to enter numbers.
- 3 For simple calculations, tap the function you want to perform (+, -, x or ÷) followed by =.
- 4 For more complex calculations, slide the left then choose sin, cos, tan, log etc.
- 5 To check the history, tap the icon .

Adding an event to your calendar

- 1 Tap  >  > Apps tab > **Calendar**.
- 2 On the screen, you can find the different view types for the Calendar (Day, Week, Month, Year, Agenda, Life Square).
- 3 Tap on the date for which you wish to add an event and tap .
- 4 Tap **Event name** and enter the event name.
- 5 Tap **Location** and enter the location. Check the date and enter the time you wish your event to start and finish.
- 6 If you wish to add a note to your event, tap **Link note** to select the saved notebook image. (Only available on the Phone calendar)
- 7 If you wish to repeat the alarm, set **REPEAT** and set **REMINDERS**, if necessary.
- 8 Tap **Save** to save the event in the calendar.

Voice Recorder

Use the voice recorder to record voice memos or other audio files.

Recording a sound or voice

- 1 Tap  >  > the **Apps** tab > **Voice Recorder**.
- 2 Tap  to begin recording.
- 3 Tap  to end the recording.
- 4 Tap  to listen to the recording.

NOTE: Tap  to access your album. You can listen to the saved recording. The available recording time may differ from actual recording time.

Sending the voice recording

- 1 Once you have finished recording, you can send the audio clip by tapping .
- 2 Choose from **Bluetooth**, **E-mail**, **Gmail**, **Memo**, **Messaging** or **SmartShare Beam**. When you select **Bluetooth**, **E-mail**, **Gmail**, **Memo**, **Messaging** or **SmartShare Beam** the voice recording is added to the message. You may then write and send the message as you usually would.

Task Manager

You can manage your applications using Task Manager. You can easily check the number of applications that are currently running and shut down certain applications.

Utilities

Tasks

This task can be synchronized with MS Exchange account. You can create task, revise it and delete it in MS outlook or MS Office Outlook Web Access.

To Synchronize MS Exchange

- 1 From the Home Screen, Tap  >  >  **Settings**.
- 2 Tap **General** tab > **Accounts & sync** > **Add account**.
- 3 Tap **Microsoft Exchange** to create Email address and Password.
- 4 Make sure if you checkmark Sync task.

NOTE: MS Exchange may not be supported depending on email server.

POLARIS Viewer 5

Polaris Office is a professional mobile office solution that lets users conveniently view various types of office documents, including Word, Excel and PowerPoint files, anywhere or anytime, using their mobile devices.

Tap  >  > **Apps** tab >  **POLARIS Viewer 5**.

Viewing files

Mobile users can now easily view a wide variety of file types, including Microsoft Office documents and Adobe PDF, right on their mobile devices. When viewing documents using Polaris Office 4, the objects and layout remain the same as in the original documents.

Google+

Use this application to stay connected with people via Google's social network service.

- Tap  >  > Apps tab >  Google+.

NOTE: This application may not be available depending on the region or service provider.

Voice Search

Use this application to search webpages using voice.

- 1 Tap  >  > Apps tab >  Voice Search.
- 2 Say a keyword or phrase when Speak now appears on the screen. Select one of the suggested keywords that appear.

NOTE: This application may not be available depending on the region or service provider.

Downloads

Use this application to see what files have been downloaded through the applications.

- Tap  >  > Apps tab >  Downloads.

NOTE: This application may not be available depending on the region or service provider.

The Web

Internet

Use this application to browse the Internet. Browser gives you a fast, full-color world of games, music, news, sports, entertainment and much more, right on your mobile phone wherever you are and whatever you enjoy.

NOTE: Additional charges apply when connecting to these services and downloading content. Check data charges with your network provider.

1 Tap > > Apps tab > Internet.

Using the Web toolbar

Tap slide it upwards with your finger to open.

	Tap to go back one page.
	Tap to go forward one page, to the page you connected to after the current one. This is the opposite of what happens when you tap , which takes you to the previous page.
	Tap to go to the Home page.
	Tap to add a new window.
	Tap to access bookmarks.

Viewing webpages

Tap the address field, enter the web address and tap **Go**.

Opening a page

To go to new page, tap → .

To go to another webpage, tap , scroll up or down, and tap the page to select it.

Searching the web by voice

Tap the address field, tap , speak a keyword, and then select one of the suggested keywords that appear.

NOTE: This feature may not be available depending on the region or service provider.

Bookmarks

To bookmark the current webpage, tap > **Save to bookmarks** > **OK**.

To open a bookmarked webpage, tap and select one.

History

Tap > **History** to open a webpage from the list of recently-visited webpages. To clear the history, tap **Menu key** → **Clear all history**.

Using Popup Browser

Use this feature to access the Internet without closing the current application.

While viewing content, such as contacts or notes that include web addresses, select a web address and then tap Popup Browser to open the pop-up browser. Touch and drag the browser to move it to another location.

To view the browser in full screen, tap .

To close the browser, tap .

The Web

Chrome

Use Chrome to search for information and browse webpages.

- 1 Tap  >  > Apps tab > **Chrome**.

NOTE: This application may not be available, depending on your region and service provider.

Viewing webpages

Tap the Address field, and then enter a web address or search criteria.

Opening a page

To go to a new page, tap  →  **New tab**.

To go to another webpage, tap , scroll up or down and tap the page to select it.

Syncing with other devices

Sync open tabs and bookmarks to use with Chrome on another device when you are logged in with the same Google account.

To view open tabs on other devices, tap **Menu key**  → **Other devices**.

Select a webpage to open.

To add bookmarks, tap .

Settings

This section provides an overview of items you can change using your phone's System settings menus.

To access the Settings menu:

Tap  >  > **System settings**.

- or -

Tap  >  >  **Settings**.

Networks

< Wi-Fi >

Wi-Fi – Turns on Wi-Fi to connect to available Wi-Fi networks.

TIP! How to obtain the MAC address

To set up a connection in some wireless networks with MAC filters, you may need to enter the MAC address of your phone in the router.

You can find the MAC address in the following user interface: tap  >  > **Apps tab** >  **Settings** > **Networks tab** > **Wi-Fi** >  > **Advanced Wi-Fi** > **MAC address**.

< Bluetooth >

Turn the Bluetooth wireless feature on or off to use Bluetooth.

< Mobile data >

Displays the data usage and set mobile data usage limit.

< Call >

Configure phone call settings such as call forwarding and other special features offered by your carrier.

Voicemail – Allows you to select your carrier's voicemail service.

Fixed dialing numbers – Turn on and compile a list of numbers that can be called from your phone. You'll need your PIN2, which is available from your operator. Only numbers within the fixed dial list can be called from your phone.

Settings

Incoming call popup – Display incoming call popup when using camera and videos.

Call reject – Allows you to set the call reject function. Choose from **Call reject mode** or **Reject calls from**.

Decline with message – When you want to reject a call, you can send a quick message using this function. This is useful if you need to reject a call during a meeting.

Privacy keeper – Hides the caller name and number for an incoming call.

Call forwarding – Choose whether to divert all calls when the line is busy, when there is no answer or when you have no signal.

Auto answer – Set the time before a connected hands-free device automatically answers an incoming call. Choose from Disable, 1 second, 3 seconds, and 5 seconds.

Connection vibration – Vibrates your phone when the other party answers the call.

Voice enhancement – Enhances voice quality in noisy environments so you can hear more clearly.

Save unknown numbers – Add unknown numbers to contacts after a call.

Power button ends call – Allows you to select your end call.

Call barring – Lock incoming, outgoing or international calls.

Call duration – View the duration of calls including Last call, All calls, Dialled calls and Received calls.

Additional settings – Allows you to change the following settings:

Caller ID: Choose whether to display your number in an outgoing call.

Call waiting: If call waiting is activated, the handset will notify you of an incoming call while you are on a call (depending on your network provider).

< Share & connect >

NFC – Your phone is an NFC-enabled mobile phone. NFC (Near Field Communication) is a wireless connectivity technology that enables two-way communication between electronic devices. It operates over a distance of a few centimeters. You can share your content with an NFC tag or another NFC support device by simply tapping it with your device. If you tap an NFC tag with your device, it will display the tag content on your device.

To switch NFC on or off: From the Home screen, touch and slide the notification panel down with your finger, then select the NFC icon to turn it on.

NOTE: When airplane mode is activated, the NFC application can be used.

Using NFC: To use NFC, make sure your device is switched on, and activate NFC if disabled.

Direct/Android Beam – When this feature is turned on, you can beam app content to another NFC-capable device by holding the devices close together.

Just bring the device together(typically back to back) and then tap your screen. The app determines what gets beamed.

SmartShare Beam – Enable to receive files from LG phones.

Miracast – Mirror phone screen and sound onto Miracast dongle or TV Wirelessly.

Wireless storage – You can manage files on your phone in the computer or copy files to the phone from the computer without a USB connection. After switching on Wireless storage, make sure that the phone and computer are connected to the same network. Then, enter the web addresses shown on your phone in the address bar of the browser on your computer.

< Tethering & networks >

Wi-Fi hotspot – You can also use your phone to provide a mobile broadband connection. Create a hotspot and share your connection. Please "**Sharing your phone's data connection**" for more information.

Bluetooth tethering – Allows you to set your phone whether you are sharing the Internet connection or not.

Help – Tap to view help information on the Wi-Fi hotspot and Bluetooth tethering functions.

Airplane mode – After switching to Airplane mode, all wireless connections are disabled.

Settings

NOTE: You must set a lock screen PIN or password before you can use credential storage.

Mobile networks – Set options for data roaming, network mode & operators, access point names (APNs) etc.

VPN – Displays the list of Virtual Private Networks (VPNs) that you've previously configured. Allows you to add different types of VPNs.

Sound

Sound profile – Choose the Sound, either Vibrate only or Silent.

Volumes – Adjust the phone's volume settings to suit your needs and your environment.

Vibrate strength – Allows you to set the vibrate strength for calls, notifications, and touch feedback.

Quiet mode – Set up your Quiet mode. Tap the **Turn quiet mode on now** switch to toggle it On or Off. You can schedule Quiet mode to activate automatically and designate exceptions to your Quiet mode.

Set quiet time: Tap the switch to toggle it On or Off. You can also set the days and times to automatically turn Quiet mode on.

Incoming call settings

Block incoming calls: Checkmark to block all incoming calls.

Allow repeated calls: Checkmark to allow a call that is repeated within 3 minutes.

Allowed contact lists: Designate which Contacts calls will be allowed.

Auto reply to blocked calls: Set how to you want to automatically reply to silenced calls.

Phone ringtone – Set the ringtone for calls. You can also add a ringtone by tapping  at the top right corner of the screen.

Smart ringtone – Checkmark to increase phone ringtone volume automatically in noisy environments.

Incoming call vibration – Sets the incoming call vibration Options.

Gentle vibration – Checkmark to gradually increasing vibration up to current strength set.

Ringtone with vibration – Checkmark to set the phone to vibrate in addition to the ringtone when you receive calls.

Voice notifications – Tap the **Voice notifications** switch to toggle it On or Off. On allows your device to incoming call and message events automatically.

Notification sound – Allows you to set the sound for notifications. You can also add a sound by tapping  at the top right corner of the screen.

Touch feedback & system – Allows you to set the feedback (tones and/or vibration) while using your device.

Display

< Home screen >

Set the **Theme**, **Wallpaper**, **Screen swipe effect**, **Allow Home screen looping**, or **Portrait view only**.

Home backup & restore – You can backup and restore app/widget layouts and themes.

Do you know? – Checkmark to display **Do You know** on an additional Home screen.

< Lock screen >

Select screen lock – Set a screen lock type to secure your phone. Opens a set of screens that guide you through drawing a screen unlock pattern. Set **None**, **Swipe**, **Face Unlock**, **Pattern**, **PIN** or **Password**.

If you have enabled a Pattern lock type when you turn on your phone or wake up the screen, you will be asked to draw your unlock pattern to unlock the screen.

Screen swipe effect – Sets the screen swipe effect options. Choose from Ripple, Dewdrop, White light, Particle, and Crystal.

Settings

NOTE: This setting name may be Pattern effect if the Screen lock is set to Pattern.

Weather animation – Checkmark to show weather animation for current location or primary city set in Weather based on auto data updates.

Wallpaper – Sets your Lock screen wallpaper. Select it from **Gallery** or **Wallpaper gallery**.

Shortcuts – Allows you to change the shortcuts on the **Swipe** Lock screen.

Owner info – Checkmark to set the device owner's name to be displayed on the Lock screen. Tap  to enter the text to be displayed as the Owner info.

Lock timer – Sets the amount of time before the screen automatically locks after the screen has timed-out.

Power button instantly locks – Checkmark to instantly lock the screen when the Power/Lock Key is pressed. This setting overrides the Security lock timer setting.

< Front touch buttons >

Set the Front Touch Keys displayed at the bottom of all of the screens. Set which ones are displayed, their position on the bar, and what they look like. Select the keys and order, the theme, and the background.

< SCREEN >

Brightness – Adjusts the brightness of the screen. For best battery performance, use the dimmest comfortable brightness.

Screen timeout – Sets the amount of time before the screen times out.

Screen-off effect – Sets the screen-off effect. Choose from Simple, Black hole, and Retro TV.

Auto-rotate screen – Checkmark to set the phone to automatically rotate the screen based on the phone orientation (portrait or landscape).

Daydream – Tap the Daydream switch to toggle it On or Off. On allows the set screensaver to be displayed when the phone is sleeping while docked and/or charging. Choose from Clock, Colors, Photo Frame, and Photo Table.

< FONT >

Font type – Sets the type of font used for the phone and menus.

Font size – Sets the size of the font displayed in the phone and menus.

< SMART ON >

Smart screen – Checkmark to keep the screen from timing-out when the device detects your eyes looking at the screen.

Smart video – Checkmark to pause the video when it doesn't detect your eyes looking at the screen.

< ADVANCED SETTINGS >

Notification LED – Tap the switch to toggle it On or Off. On will activate the LED light for the notifications you select, in the color you set for each one.

Aspect ratio correction – Allows you to change the aspect ratio of a downloaded application to fix screen distortion.

General

< Gestures >

Screen on/off – Checkmark to enable KnockON to turn the screen on and off. Quickly double-tap center screen to turn it on. Double-tap the Status Bar, an empty area on the Home screen, or the Lock screen to turn the screen off. For the best results, do not move the phone while using the KnockON feature.

Answer an incoming call – Checkmark to enable you to bring the phone to your ear to automatically answer the incoming call.

Fade out ringtone – Checkmark to enable you to pick up the phone from the flat surface to fade out the incoming call ringtone.

Silence incoming calls – Checkmark to enable you to flip the phone to silence incoming calls.

Snooze or turn off alarm – Checkmark to enable you to simply flip the device to snooze or stop the alarm.

Settings

Pause video – Checkmark to enable you to simply flip the device to pause the currently playing video.

Move Home screen items – Checkmark to enable you to move an icon to another screen by tilting the phone. Tap and hold the icon and tilt the phone left or right, then let go on the screen where you want the icon.

Help – Opens a help guide on how to use the Gestures features of your device.

Motion sensor calibration – Allows you to improve the accuracy of the tilt and speed of the sensor.

< One-handed operation >

Dial keypad – Checkmark to enable you move the dial keypad to the right or left side of the device. Simply tap the arrow to move it to one side or the other.

LG keyboard – Checkmark to enable you move the keyboard to the right or left side of the device. Simply tap the arrow to move it to one side or the other.

Gesture control – Checkmark to enable you to swipe the keyboard left or right to adjust the position of LG keyboard.

Lock screen – Checkmark to enable you move the PIN Lock screen keypad to the right or left side of the device. Simply tap the arrow to move it to one side or the other.

Help – Displays information regarding one-handed operation.

< Storage >

INTERNAL STORAGE – View the internal storage usage.

< Battery >

BATTERY INFORMATION

The Battery charge information is displayed on a battery graphic along with the percentage of the remaining charge and its status.

Touch the Battery charge icon to display the Battery use screen to see battery usage level and battery use details. It displays which components and applications are using the most battery power. Tap one of the entries to see more detailed information.

Battery percentage – Checkmark to display the battery level percentage on the Status Bar next to the battery icon.

BATTERY SAVER

Tap the Battery saver switch to toggle it On or Off. Tap Battery saver to access the following settings:

Turn Battery saver on – Sets the battery charge percent level that will automatically turn on Battery saver. Choose from Immediately, 10% battery, 20% battery, 30% battery, and 50% battery.

BATTERY SAVING ITEMS

Auto-sync – Checkmark to turn off Auto-sync when Battery saver is activated.

Wi-Fi – Checkmark to turn Wi-Fi off when data is not being used while Battery saver is activated.

Bluetooth – Checkmark to turn Bluetooth off when not connected while Battery saver is activated.

Vibrate on touch – Checkmark to turn off touch feedback when Battery saver is activated.

Brightness – Checkmark to set the screen brightness when Battery saver is activated. Tap  to change the setting.

Screen timeout – Checkmark to set the screen timeout when Battery saver is activated. Tap the Settings icon to change the setting.

Notification LED – Checkmark to turn off the LED light for notifications when Battery saver is activated.

Battery saver tips – Displays tips for using the Battery saver function.

< Apps >

View and manage your applications.

< Slide Aside >

Tap the **Slide Aside** switch to toggle it on to use Slide Aside feature. (Please see **Slide Aside**.)

Settings

< Accounts & sync >

Permits applications to synchronize data in the background, whether or not you are actively working in them. Deselecting this setting can save battery power and lower (but not eliminate) data usage.

< Cloud >

Add a cloud account to quickly and easily use cloud service on LG apps.

< Guest mode >

To protect your privacy or limit some applications to your children, you can use the Guest mode.

When you lend your phone to others, you can limit the applications to be displayed. In advance, set the Guest mode and customize the options.

< Location access >

Access to my location – If you select Google's location service, your phone determines your approximate location using Wi-Fi and mobile networks. When you select this option, you're asked whether you consent to allowing Google to use your location when providing these services.

GPS satellites – If you select GPS satellites, your phone determines your location to street-level accuracy.

Wi-Fi & mobile network location – Lets apps use data from sources such as Wi-Fi and mobile networks to determine your approximate location.

< Security >

Encrypt phone – Allows you to encrypt data on the phone for security. You will be required to enter a PIN or password to decrypt your phone each time you power it on.

Set up SIM card lock – Set up Micro-USIM card lock or change the Micro-USIM card PIN.

Password typing visible – Show the last character of the hidden password as you type.

Device administrators – View or deactivate phone administrators.

Unknown sources – Default setting to install non-Play store applications.

Verify apps – Disallow or warn before installation of apps that may cause harm.

Trusted credentials – Display trusted CA certificates.

Install from storage – Choose to install encrypted certificates.

Clear credentials – Remove all certificates.

< Language & input >

Use the Language & input settings to select the language for the text on your phone and to configure the on-screen keyboard, including words you've added to its dictionary.

< Backup & reset >

Change the settings for managing your settings and data.

Backup my data – Set to backup your settings and application data to the Google server.

Backup account – Set to backup your account.

Automatic restore – Set to restore your settings and application data when the applications are reinstalled on your device.

LG Backup service – Backs up all information on the device and restores it in the event of data loss or replacement.

Factory data reset – Reset your settings to the factory default values and delete all your data. If you reset the phone this way, you are prompted to re-enter the same information as when you first started Android.

< Date & time >

Use **Date & time** settings to set how dates will be displayed. You can also use these settings to set your own time and time zone rather than obtaining the current time from the mobile network.

< Accessibility >

Use the **Accessibility** settings to configure accessibility plug-ins you have installed on your phone.

Settings

NOTE: Requires additional plug-ins to become selectable.

< PC connection >

Select USB connection method – Set the desired mode: **Charge phone, Media sync (MTP), Tethering, LG software or Send images (PTP)**.

Ask upon connecting – Ask in USB connection mode when connecting to a computer.

Help – Help for USB connection.

PC Suite – Check this to use LG PC Suite with your Wi-Fi connection.

Please note that Wi-Fi network should be connected to LG PC Suite via a Wi-Fi connection.

On-Screen Phone – Check this to receive Wi-Fi connection request from On-Screen Phone.

Help – Help for LG software.

< Accessory >

QuickWindow case – Activate to make features, such as music, weather, and clock, available in small view when using the QuickWindow case.

USB storage – Sets the Plug & Pop feature for USB storage. Checkmark the **App panel** option to automatically display the app panel when connecting an OTG (On-the-Go) USB cable. Tap **Edit app panel** to change the applications you want to make available.

Earphone – Sets the Plug & Pop feature for earphones. Checkmark the **App panel** option to automatically display the app panel when connecting an earphone. Tap **Edit app panel** to change the applications you want to make available.

< About phone >

View legal information and check your phone status and software version.

< Regulatory and Safety Information >

To view regulatory and safety information, tap  **Settings** > **General tab** > **About phone** > **Regulatory and Safety**.

PC software (LG PC Suite)

"LG PC Suite" PC software is a program that helps you connect your device to a PC via a USB cable and Wi-Fi. Once connected, you can use the functions of your device from your PC.

With your "LG PC Suite" PC Software, You Can...

- Manage and play your media contents (music, movie, picture) on your PC.
- Send multimedia contents to your device.
- Synchronizes data (schedules, contacts, bookmarks) in your device and PC.
- Backup the applications in your device.
- Update the softwares in your device.
- Backup and restore the device data.
- Play multimedia contents of your PC from your device.
- Backup and create and edit the memos in your device

NOTE: You can use the Help menu from the application to find out how to use your "LG PC Suite" PC software.

Installing "LG PC Suite" PC Software

"LG PC Suite" PC software can be downloaded from the webpage of LG.

- 1 Go to WWW.LG-MOBILE.CO.IL and select a country of your choice.
- 2 Go to **Support > MOBILE SUPPORT > LG Mobile Phones > Select the Model** or
Go to **Support > Mobile > Select the Model**.
- 3 Click **PC SYNC** from **MANUALS & DOWNLOAD** and click **DOWNLOAD** to download "LG PC Suite" PC software.

PC software (LG PC Suite)

System Requirements for "LG PC Suite" PC software

- OS: Windows XP (Service pack 3) 32bit, Windows Vista, Windows 7, Windows 8
- CPU: 1 GHz or higher processors
- Memory: 512 MB or higher RAMs
- Graphic card: 1024 x 768 resolution, 32 bit color or higher
- HDD: 500 MB or more free hard disk space (More free hard disk space may be needed depending on the volume of data stored.)
- Required software: LG integrated drivers, Windows Media Player 10 or later

NOTE: LG Integrated USB Driver

LG integrated USB driver is required to connect an LG device and PC and installed automatically when you install "LG PC Suite" PC software application.

Synchronizing your Device to a PC

Data from your device and PC can be synchronized easily with "LG PC Suite" PC software for your convenience. Contacts, schedules and bookmarks can be synchronized.

The procedure is as follows:

- 1 Connect your device to PC. (Use a USB cable or Wi-Fi connection.)
- 2 The **Select USB connection method** will appear, then select **LG software**.
- 3 After connection, run the program and select the device section from the category on the left side of the screen.
- 4 Click **Personal information** to select.
- 5 Select the checkbox of contents to synchronize and click the **Sync** button.

NOTE: To synchronize your phone with your PC, you need to install LG PC Suite onto your PC. Please refer to previous pages to install LG PC Suite.

Moving contacts from your Old Device to your New Device

- 1** Export your contacts as a CSV file from your old device to your PC using a PC sync program.
- 2** Install "LG PC Suite" on the PC first. Run the program and connect your Android mobile phone to the PC using a USB cable.
- 3** On the top menu, select **Device > Import to device > Import contacts**.
- 4** A popup window to select the file type and a file to import will appear.
- 5** On the popup, click the **Select a file** and Windows Explorer will appear.
- 6** Select the contacts file to import in Windows Explorer and click the **Open**.
- 7** Click **OK**.
- 8** A **Field mapping** popup to link the contacts in your device and new contacts data will appear.
- 9** If there is a conflict between the data in your PC contacts and device contacts, make the necessary selections or modifications in LG PC Suite.
- 10** Click **OK**.

Phone software update

Phone software update

LG Mobile phone software update from the Internet

For more information about using this function, please visit <http://update.lgmobile.com> or <http://www.lg.com/common/index.jsp> → select your country and language.

This feature allows you to conveniently update the firmware on your phone to a newer version from the Internet without needing to visit a service center. This feature will only be available if and when LG makes a newer firmware version available for your device. Because the mobile phone firmware update requires the user's full attention for the duration of the update process, please make sure you check all instructions and notes that appear at each step before proceeding. Please note that removing the USB data cable during the upgrade may seriously damage your mobile phone.

NOTE: LG reserves the right to make firmware updates available only for selected models at its own discretion and does not guarantee the availability of the newer version of the firmware for all handset models.

LG Mobile Phone software update via Over-the-Air (OTA)

This feature allows you to conveniently update your phone's software to a newer version via OTA, without connecting using a USB data cable. This feature will only be available if and when LG makes a newer firmware version available for your device.

You should first check the software version on your mobile phone: **Settings > About phone > Update Center > Software Update > Check now for update.**

NOTE: Your personal data from internal phone storage—including information about your Google account and any other accounts, your system/application data and settings, any downloaded applications and your DRM licence—might be lost in the process of updating your phone's software. Therefore, LG recommends that you backup your personal data before updating your phone's software. LG does not take responsibility for any loss of personal data.

NOTE: This feature depends on your network service provider, region and country.

About this user guide

About this user guide

- Before using your device, please carefully read this manual. This will ensure that you use your phone safely and correctly.
- Some of the images and screenshots provided in this guide may appear differently on your phone.
- Your content may differ from the final product, or from software supplied by service providers or carriers. This content may be subject to change without prior notice. For the latest version of this manual, please visit the LG website at WWW.LG-MOBILE.CO.IL.
- Your phone's applications and their functions may vary by country, region, or hardware specifications. LG cannot be held liable for any performance issues resulting from the use of applications developed by providers other than LG.
- LG cannot be held liable for performance or incompatibility issues resulting from edited registry settings being edited or operating system software being modified. Any attempt to customize your operating system may cause the device or its applications to not work as they should.
- Software, audio, wallpaper, images, and other media supplied with your device are licensed for limited use. If you extract and use these materials for commercial or other purposes is, you may be infringing copyright laws. As a user, you are fully responsible for the illegal use of media.
- Additional charges may be applied for data services, such as messaging, uploading and downloading, auto-syncing, or using location services. To avoid additional charges, select a data plan that is suitable for your needs. Contact your service provider to obtain additional details.

Trademarks

- LG and the LG logo are registered trademarks of LG Electronics.
- All other trademarks and copyrights are the property of their respective owners.



ABOUT DIVX VIDEO: DivX® is a digital video format created by DivX, LLC, a subsidiary of Rovi Corporation. This is an official DivX Certified® device that has passed rigorous testing to verify that it plays DivX video. Visit divx.com for more information and software tools to convert your files into DivX videos.

ABOUT DIVX VIDEO-ON-DEMAND: This DivX Certified® device must be registered in order to play purchased DivX Video-on-Demand (VOD) movies. To obtain your registration code, locate the DivX VOD section in your device setup menu. Go to vod.divx.com for more information on how to complete your registration.

DivX Certified® to play DivX® video up to HD 720p, including premium content.
DivX®, DivX Certified® and associated logos are trademarks of Rovi Corporation or its subsidiaries and are used under license.

Dolby Digital Plus  **DOLBY
DIGITAL PLUS**

Manufactured under license from Dolby Laboratories. Dolby, Dolby Digital Plus, and the double-D symbol are trademarks of Dolby Laboratories.

Notice: Open Source Software


To obtain the corresponding source code under GPL, LGPL, MPL and other open source licences, please visit <http://opensource.lge.com/>

All referred licence terms, disclaimers and notices are available for download with the source code.

Accessories

These accessories are available for use with your phone. (Items described below may be optional.)

Travel adaptor



Stereo headset



Quick Start Guide



Data cable



Micro-USIM
ejection tool



NOTE:

- Always use genuine LG accessories.
- Failure to do this may void your warranty.
- Accessories may vary in different regions.

Troubleshooting

This chapter lists some problems you might encounter when using your phone. Some problems require you to call your service provider, but most are easy to fix yourself.

Message	Possible causes	Possible corrective measures
Micro-USIM card error	There is no Micro-USIM card in the phone or it is inserted incorrectly.	Make sure that the Micro-USIM card is correctly inserted.
No network connection/ Dropped network	Signal is weak or you are outside the carrier network.	Move toward a window or into an open area. Check the network operator coverage map.
	Operator applied new services.	Check whether the Micro-USIM card is more than 6~12 months old. If so, change your Micro-USIM card at your network provider's nearest branch. Contact your service provider.
Codes do not match	To change a security code, you will need to confirm the new code by re-entering it.	If you forget the code, contact your service provider.
	The two codes you have entered do not match.	

Troubleshooting

Message	Possible causes	Possible corrective measures
No applications can be set	Not supported by service provider or registration required.	Contact your service provider.
Calls not available	Dialling error	New network not authorized.
	New Micro-USIM card inserted.	Check for new restrictions.
	Pre-paid charge limit reached.	Contact service provider or reset limit with PIN2.
Phone cannot be switched on	On/Off key pressed too briefly.	Press the On/Off key for at least two seconds.
	Battery is not charged.	Charge battery. Check the charging indicator on the display.

Message	Possible causes	Possible corrective measures
Charging error	Battery is not charged.	Charge battery.
	Outside temperature is too hot or cold.	Make sure phone is charging at a normal temperature.
	Contact problem	Check the charger and its connection to the phone.
	No voltage	Plug the charger into a different socket.
	Charger defective	Replace the charger.
	Wrong charger	Use only original LG accessories.
Number not allowed	The Fixed dialling number function is on.	Check the Settings menu and turn the function off.
Impossible to receive / send SMS & photos	Memory full	Delete some messages from your phone.
Files do not open	Unsupported file format	Check the supported file formats.

Troubleshooting

Message	Possible causes	Possible corrective measures
The screen does not turn on when I receive a call.	Proximity sensor problem	If you use a protection tape or case, make sure it has not covered the area around the proximity sensor. Make sure that the area around the proximity sensor is clean.
No sound	Vibration mode	Check the settings status in the sound menu to make sure you are not in vibration or silent mode.
Hangs up or freezes	Intermittent software problem	Try to perform a software update via the website.

FAQ

Category Sub- Category	Question	Answer
BT Bluetooth Devices	What are the functions available via Bluetooth	You can connect a Bluetooth audio device such as a Stereo/Mono headset or Car Kit. Also, when the FTP server is connected to a compatible device, you can share content stored on the storage media.
BT Bluetooth Headset	If my Bluetooth headset is connected, can I listen to my music through my 3.5 mm wired headphones?	When a Bluetooth headset is connected, all system sounds are played over the headset. As a result, you will not be able to listen to music through your wired headphones.
Data Contacts Backup	How can I backup Contacts?	The Contacts data can be synchronized between your phone and Gmail™.
Data Synchronization	Is it possible to set up one-way sync with Gmail?	Only two-way synchronization is available.
Data Synchronization	Is it possible to synchronize all email folders?	The Inbox is automatically synchronized. You can view other folders by tapping the Menu Key  and select Folders to choose a folder.
Google™ Service Gmail Log-In	Do I have to log into Gmail whenever I want to access Gmail?	Once you have logged into Gmail, no need to log into Gmail again.

FAQ

Category Sub- Category	Question	Answer
Google™ Service Google Account	Is it possible to filter emails?	No, email filtering is not supported via the phone.
Phone Function Email	What happens when I execute another application while writing an email?	Your email will automatically be saved as a draft.
Phone Function Ringtone	Is there a file size limitation for when I want to use MP3 file as ring tone?	There is no file size limitation.
Phone Function Message Time	My phone does not display the time of receipt for messages older than 24 hrs. How can I change this?	You will only be able to see the times for messages received the same day.
Phone Function Navigation	Is it possible to install another navigation application on my phone?	Any application that is available at Play Store™ and is compatible with the hardware can be installed and used.
Phone Function Synchronisation	Is it possible to synchronize my contacts from all my email accounts?	Only Gmail and MS Exchange server (company email server) contacts can be synchronized.

Category Sub- Category	Question	Answer
Phone Function Wait and Pause	Is it possible to save a contact with Wait and Pause in the numbers?	<p>If you transferred a contact with the W & P functions saved into the number, you will not be able to use those features. You will need to re-save each number.</p> <p>How to save with Wait and Pause:</p> <ol style="list-style-type: none"> 1. From the Home screen, tap the Phone icon . 2. Dial the number, then tap the Menu Key . 3. Tap Add 2-sec pause or Add wait.
Phone Function Security	What are the phone's security functions?	You are able to set the phone to require that an Unlock Pattern be entered before the phone can be accessed or used.

FAQ

Category Sub- Category	Question	Answer
Phone Function Unlock Pattern	How do I create the Unlock Pattern?	<ol style="list-style-type: none">1. From the Home screen, tap the Menu Key .2. Tap System settings > Display tab > Lock screen.3. Tap Select screen lock > Pattern. The first time you do this, a short tutorial about creating an Unlock Pattern will appear.4. Set up by drawing your pattern once, and once again for confirmation. <p>Precautions to take when using the pattern lock. It is very important to remember the unlock pattern you set. You will not be able to access your phone if you use an incorrect pattern five times. You have five chances to enter your unlock pattern, PIN or password. If you have used all 5 opportunities, you can try again after 30 seconds. (Or, if you preset the backup PIN, you can use the backup PIN code to unlock the pattern.)</p>


Category Sub- Category	Question	Answer
Phone Function Unlock Pattern	What should I do if I forget the unlock pattern and I didn't create my Google account on the phone?	<p>If you have forgotten your pattern: If you logged into your Google account on the phone but failed to enter the correct pattern 5 times, tap the forgot pattern button. You are then required to log in with your Google account to unlock your phone. If you have not created a Google account on the phone or you have forgotten it, you will have to perform a hard reset.</p> <p>Caution: If you perform a factory reset, all user applications and user data will be deleted. Please remember to backup any important data before performing a factory reset.</p>
Phone Function Memory	Will I know when my memory is full?	Yes, you will receive a notification.
Phone Function Language Support	Is it possible to change my phone's language?	<p>The phone has multilingual capabilities. To change the language:</p> <ol style="list-style-type: none"> <li data-bbox="520 895 908 981">From the Home screen, tap the Menu Key  and tap System settings. <li data-bbox="520 987 908 1049">Tap General tab > Language & input > Language. <li data-bbox="520 1055 908 1079">Tap the desired language.

Category Sub- Category	Question	Answer
Phone Function VPN	How do I set up a VPN?	VPN access configuration is different for each company. To configure VPN access from your phone, you must obtain the details from your company's network administrator.
Phone Function Screen time out	My screen turns off after only 15 seconds. How can I change the amount of time for the backlight to turn off?	<ol style="list-style-type: none">1. From the Home screen, tap the Menu Key .2. Tap System settings > Display tab.3. Tap Screen timeout.4. Tap the preferred screen backlight timeout time.
Phone Function Wi-Fi & mobile network	When Wi-Fi and mobile network are both available, which service will my phone use?	When using data, your phone may default to the Wi-Fi connection (if Wi-Fi connectivity on your phone is set to On). However, there will be no notification when your phone switches from one to the other. To know which data connection is being used, view the mobile network or Wi-Fi icon at the top of your screen.
Phone Function Home screen	Is it possible to remove an application from the Home screen?	Yes. Just touch and hold the icon until the dustbin icon appears at the top and center of the screen. Then, without lifting your finger, drag the icon to the trash can.

Category Sub- Category	Question	Answer
Phone Function Application	I downloaded an application and it causes a lot of errors. How do I remove it?	<ol style="list-style-type: none"> 1. From the Home screen, tap the Menu Key . 2. Tap System settings > General tab > Apps > DOWNLOADED. 3. Tap the application, then tap Uninstall.
Phone Function Charger	Is it possible to charge my phone using a USB data cable without installing the necessary USB driver?	Yes, the phone will be charged by the USB cable regardless of whether the necessary drivers are installed or not.
Phone Function Alarm	Can I use music files for my alarm?	<p>Yes. After saving a music file as a ringtone, you can use it as your alarm.</p> <ol style="list-style-type: none"> 1. Touch and hold a song in a library list. In the menu that opens, tap Set music as > Ringtone or Contact ringtone. 2. In the alarm clock setting screen, select the song as a ringtone.
Phone Function Alarm	Will my alarm be audible or will it go off if the phone is turned off?	No, this is not supported.
Phone Function Alarm	If my ringer volume is set to Off or Vibrate, will I hear my alarm?	Your alarm is programmed to be audible even in these scenarios.

FAQ

Category Sub- Category	Question	Answer
Recovery Solution Hard Reset (Factory Reset)	How can I perform a factory reset if I can't access the phone's setting menu?	If your phone does not restore to its original condition, use a hard reset (factory reset) to initialize it.





CE0168!